

**SUPPLEMENT**

**Model 1800-V Professional Stereo Power  
Amplifier EQ PCB Assemblies**

This supplement should be added to the Service Manual P/N 181812-S2.  
Listed below and on the back of this page is an update to the Part List.

These parts have been added to the part list for the following EQ PCB Assemblies:  
402, 502A, 502B and 802.

Reference Designator	Description	Part Number
R39	JUMPER, CHIP, 1206	124896

**Complete PCB Assemblies Part List**

Description	Part Number	Description	Part Number
402 EQ PCB Assy	009083	3202 II EQ PCB Assy	011502
502A EQ PCB Assy	009082	4402 II EQ PCB Assy	011504
502B EQ PCB Assy	009081	9702 II EQ PCB Assy	017929
802 EQ PCB Assy	009080	LT II EQ PCB Assy	018485

**The following is an update to the 9702 II EQ PCB Part List  
Service Manual P/N 181812-S2**

**The following component values have been changed. The changes are reflected on  
PCB number 183071 REV 04. There is no need to change any of these component  
values on PCB's before REV 04**

Reference Designator	Description	Part Number
R4	3.65KΩ, 0805, 1/10W, 1%	133625-3651
R10, 11	22.6KΩ, 0805, 1/10W, 1%	133625-2262
R17, 35	JUMPER, CHIP, 1206	124896
R19, 20, 45, 46	90.9KΩ, 0805, 1/10W, 1%	133625-9092
R21	2.80KΩ, 0805, 1/10W, 1%	133625-2801
R22	14.7KΩ, 0805, 1/10W, 1%	133625-1472
R27, 40	40.2KΩ, 0805, 1/10W, 1%	133625-4022
R36	26.1KΩ, 0805, 1/10W, 1%	133625-2612
R37	15.0KΩ, 0805, 1/10W, 1%	133625-1502
R43, 44	16.9KΩ, 0805, 1/10W, 1%	133625-1692
C9, 10	.027uF, BOX, 85, 63V, 5%	137127-273
C12, 30	820pF, DISC, SL, 50V, 10%	137269-820
C13	.0012uF, BOX, 85, 100V, 5%	137127-122
C14, 29	120pF, DISC, SL, 50V, 10%	137269-121
C24	.0022uF, BOX, 85, 100V, 5%	137127-222
C28	.0082uF, BOX, 85, 100V, 5%	137127-822
C31	330pF, DISC, SL, 50V, 10%	137269-331

**The following components have been deleted from the PCB  
number 183071 REV 04.**

Reference Designator	Description	Part Number
R15, 16, 31, 32	JUMPER, CHIP, 0805	133627
R41, 42	34.0KΩ, 0805, 1/10W, 1%	133625-3402