

PARTS LIST AND DESCRIPTIONS (Continued)

TRANSFORMER (POWER)

ITEM No.	RATING		REPLACEMENT DATA				
	PRI.	SEC.	EICO PART No.	Holldorson PART No.	Merit PART No.	Ram PART No.	Stancor PART No.
T1	117V @ .9A	750 VCT @ 5V @ 3V	30016 ①				
		SEC. 3					
		6.3V @ 2.7A					

① Used in Model HF-22.

TRANSFORMER (POWER)

ITEM No.	RATING		REPLACEMENT DATA				
	PRI.	SEC.	EICO PART No.	Holldorson PART No.	Merit PART No.	Ram PART No.	Stancor PART No.
T1	125V @ 1.15A Tap @ 117V @ 1.45A	780VCT @ 5V @ 1.9A	30020 ②	24R38 ③			
		SEC. 3					
		6.3V @ 4.2A					

② Model HF-35

③ Parallel and phase 6.3 Volt windings. Tape center tap on 5V and 6.3V windings.

TRANSFORMER (AUDIO OUTPUT)

ITEM No.	IMPEDANCE		REPLACEMENT DATA					NOTES
	PRI.	SEC.	EICO PART No.	Holldorson PART No.	Merit PART No.	Ram PART No.	Stancor PART No.	
T2	7500Ω 16Ω CT Tap @ 8Ω, 4Ω 1500Ω CT		30004					

FUSES

ITEM No.	TYPE	RATING	REPLACEMENT DATA			
			EICO PART No.	HOLDER	FUSE	BUSS PART No.
M1	3AG	3A 250V	91005	97800	312003 (3AG 3A 250V)	342001 AGC3 HKP

WIRING DATA

General-use Unshielded Hook-up Wire Use BELDEN No. 8530 (Solid) Available in Ten Colors
 Power Cord Use BELDEN No. 8524 (Stranded) Available in Ten Colors
 1725-K (7½ Ft. Length)

CHASSIS—BOTTOM VIEW

