



RESISTORS	R3 TO R10	R11	R12 TO R17	R18 TO R19	R20 TO R21	R26 TO R30	R32 TO R33	R39	R52 TO R53	R54 TO R56	R50 TO R51	R57 TO R60	R61 TO R63	R64 TO R70	R71 TO R72	R75 TO R80	R81 TO R85	R86 TO R87	R88 TO R89	R96 TO R100	R101 TO R102	R103 TO R106	R107 TO R108	R73 TO R113	R109 TO R113	R114 TO R116	R118 TO R119	R120 TO R123	R115 TO R117	R121 TO R122	R124 TO R126	R127 TO R130	R131 TO R132														
CAPACITORS	C1	C2	C3	C4	C13	C14	C32	C33	C34	C30	C35	C36	C37	C41	C43	C45	C46	C47	C48	C49	C50	C51	C54	C55	C56	C57	C58	C59	C60	C63	C64	C65	C66	C67	C68	C69	C70	C71	C72	C73	C74	C75	C76	C77	C78	C79	C80

# PARTS DESCRIPTION LIST

## CAPACITORS

10% tolerance for all fixed capacitors, unless otherwise noted or marked GMV (guaranteed minimum value).

Symbol	Description	Part No.
C1, 2	Ceramic, 100uf, N1500, 100V	C50070-6
C3, 4	Mylar, .022uf, 250V	C50197-49
C13, 14	Mylar, .047uf, 250V	C50197-52
C30, 31	Ceramic, 100uf, N1500, 1000V	C50070-6
C32	Electrolytic, 2 section	C50180-29
	A — 1000uf, 35V	
	B — 1000uf, 35V	
C33	Electrolytic, 4 section	C50180-10
	A — 40uf, 450V	
	B — 10uf, 450V	
	C — 10uf, 450V	
	D — 40uf, 450V	
C34	Electrolytic, 4 section	C50180-30
	A — 30uf, 350V	
	B — 10uf, 250V	
	C — 30uf, 350V	
	D — 10uf, 300V	
C35, 36	Ceramic, .005uf, 20%, 500V	C50089-1
C37, 38	Ceramic, .0039uf, 1000V	C50072-34
C41, 42	Mylar, .1uf, 250V	C50197-54
C43, 44,		
45, 46	Electrolytic, 50uf, 3V	C50283-1
C47, 48	Mylar, .1uf, 250V	C50197-54
C49, 50,		
51, 52	Ceramic, 24uf, 5%, N150, 1000V	C50070-8
C53, 54	Mylar, .033uf, 250V	C50197-51
C55, 56	Ceramic, 2700uf, 1000V	C50072-17
C57, 58	Electrolytic, 50uf, 3V	C50283-1
C59, 60	Ceramic, 300uf, 1000V	C50072-39
C63, 64	Ceramic, 1000uf, 1000V	C50072-3
C65, 66	Ceramic, 220uf, 1000V	C50072-20
C67, 68	Mylar, .68uf, 250V	C50197-57
C69, 70	Ceramic, 220uf, 1000V	C50072-20
C71, 72	Mylar, .047uf, 250V	C50197-52
C73, 74	Mylar, .68uf, 250V	C50197-57
C75, 76,		
77, 78	Electrolytic, 50uf, 3V	C50283-1
C79, 80	Mylar, .68uf, 250V	C50197-57

## RESISTORS AND POTENTIOMETERS

In ohms, 10% tolerance, 1/2 watt, unless otherwise noted. K=Kilohm, M=Megohm.

Symbol	Description	Part No.
R3, 4, 5, 6	Dep. Carbon, 100K, 5%, 1/3 W	R33DC104J
R7, 8,		
9, 10	Dep. Carbon, 120K, 5%, 1/3 W	R33DC124J
R11	Potentiometer, Dual, 250K, aux. 2 level	R50160-71
R12, 13	Dep. Carbon, 100K, 5%, 1/3 W	R33DC104J
R14, 15	Dep. Carbon, 10K, 5%, 1/3 W	R33DC103J
R16, 17	Glass, 2.7K, 5%, 1W	R30G272J
R18, 19	Glass, 330K, 5%, 1W	R30G334J
R20, 21	Dep. Carbon, 4.7M, 5%, 1/3 W	R33DC475J
R26, 27	Dep. Carbon, 220K, 5%, 1/3 W	R33DC224J
R28, 29	Composition, 560K	RC20BF564K
R30	Dep. Carbon, 100K, 5%, 1/3 W	R33DC104J
R32, 33	Potentiometer, Dual, 250K, Mag. 1 & Mag. 2 level	R50160-71
R39	Dep. Carbon, 100K, 5%, 1/3 W	R33DC104J
R50, 51	Dep. Carbon, 120K, 5%, 1/3 W	R33DC124J
R52	Glass, 330, 3W	RPG3W331K
R53	Wirewound, 10K, 7W	R851-128
R54	Glass, 1K, 3W	RPG3W102K
R55	Composition, 47K	RC20BF473K
R56	Glass, 1K, 3W	RPG3W102K
R57, 58	Composition, 1.5M	RC30BF155K
R59	Glass, 5.6K, 3W	RPG3W562K
R60	Glass, 1K, 3W	RPG3W102K

R61, 62	Dep. Carbon, 220K, 5%, 1/3 W	R33DC224J
R63	Glass, 4.7K, 3W	RPG3W472K
R64, 65	Composition, 300K, 5%	RC20BF304J
R66, 67	Dep. Carbon, 100K, 5%, 1/3 W	R33DC104J
R68	Composition, 15K	RC20BF153K
R69, 70	Composition, 1.5K	RC20BF152K
R71, 72	Composition, 330K	RC20BF334K
R73	Dep. Carbon, 4.7M, 5%, 1/3 W	R33DC475J
R75, 76	Dep. Carbon, 220K, 5%, 1/3 W	R33DC224J
R77, 78	Dep. Carbon, 2.7K, 5%, 1/3 W	R33DC272J
R79, 80	Dep. Carbon, 100K, 5%, 1/3 W	R33DC104J
R81, 82	Dep. Carbon, 470K, 5%, 1/3 W	R33DC474J
R83	Potentiometer, dual, 250K, balance	R50160-65
R84, 85,		
86, 87	Dep. Carbon, 470K, 5%, 1/3 W	R33DC474J
R88	Composition, 33	RC20BF330K
R89, 90	Composition, 2.7M, 5%	RC20BF275J
R91, 92	Composition, 2.2M, 5%	RC20BF225J
R93, 94	Dep. Carbon, 470K, 5%, 1/3 W	R33DC474J
R95	Potentiometer, dual, 1M, dimension	R50160-70
R96	Dep. Carbon, 470K, 5%, 1/3 W	R33DC474J
R97, 98	Dep. Carbon, 120K, 5%, 1/3 W	R33DC124J
R99, 100	Composition, 1.8K	RC20BF182K
R101, 102,		
103, 104,		
105, 106	Dep. Carbon, 47K, 5%, 1/3 W	R33DC473K
R107, 108	Composition, 68K, 10%, 1W	R30BF683K
R109, 110	Dep. Carbon, 470K, 5%, 1/3 W	R33DC474J
R111, 112	Dep. Carbon, 10K, 5%, 1/3 W	R33DC103J
R113	Dep. Carbon, 220K, 5%, 1/3 W	R33DC224J
R114, 115	Dep. Carbon, 220K, 5%, 1/3 W	R33DC224J
R116, 117	Dep. Carbon, 2.7K, 5%, 1/3 W	R33DC272J
R118, 119	Dep. Carbon, 22K, 5%, 1/3 W	R33DC223J
R120	Potentiometer, dual, 100K, volume	R50160-69
R121	Dep. Carbon, 470K, 5%, 1/3 W	R33DC474J
R122	Potentiometer, dual, 1M, bass	R50160-66
R123	Potentiometer, dual, 500K, treble	R50160-67
R124	Potentiometer, 500K, center volume	R50160-68
R125, 126	Dep. Carbon, 270K, 5%, 1/3 W	R33DC274J
R127, 128	Composition, 1.5K	RC20BF152K
R129, 130	Composition, 180K	RC20BF184K
R131, 132	Composition, 68K, 1W	R30BF683K

## MISCELLANEOUS

Symbol	Description	Part No.
F1	Fuse, .5 amp., slo-blo	F795-136
I1, 2, 3,		
4, 5	Lamp, #47	150009-1
PC1, 2	Printed Circuit, 3 3/4, tape EQ.	PC50187-7
PC3, 4	Printed Circuit, COL, EQ	PC50187-6
PC5, 6	Printed Circuit, 78, EQ.	PC50187-8
PC7, 8	Printed Circuit, R1AA, 7 1/2, EQ.	PC50187-3
PC9, 10	Printed Circuit, tone control	PC657-140
P1	Plug, dummy	P50181
S1	Switch, low level	S851-126
S2	Switch, mono-stereo	S851-127
S3	Switch, push button	S851-119
S4	Switch, center ch., power	Part of R124
S5, 6, 7,		
8, 9	Switch, slide	S50200-5
S10	Switch, power	Part of R120
SR1, 2	Diode, silicon, SD91	SR851-121
T1	Transformer, power	T851-115
—	Dress panel	AS851-106
—	Shielded cable	AS50004-1
—	Knob, push button	E851-116
—	Knob, dual, front	E50323
—	Knob, dual, rear	E50221
—	Knob	E50325-1
—	Jewel, red	150162-1
—	Jewel, yellow	150162-2
—	Jewel, green	150162-4