

MODELS 504, 504Q

ALIGNMENT PROCEDURE (CONT'D)

3.	REPEAT STEPS #1 & #2.		
4.	ANTENNA WIRE IN SERIES WITH .00025 MICA COND.	1600 KC	OSC. TRIMMER LOCATED ON VARIABLE COND. ACCESSIBLE THRU HOLE IN DIAL BRACKET
5.	" "	1400 KC	ANT. TRIMMER LOCATED ON VARIABLE CONDENSER DIAL

- 3D30 ANT. COIL
- 3D29 OSC. COIL
- 7D6 GANG COND.
- 3D31 FIRST I.F.
- 3D32 SECOND I.F.
- 12D2 OUTPUT TRANS.
- 18D11 SPEAKER

NOTE: BE SURE THAT THE BLACK GROUND LEAD OF RECEIVER IS ATTACHED TO GROUND OF SIGNAL GENERATOR DURING ALL THE ABOVE OPERATIONS.

