


Service Manual

PM17A /F1N, /K1G, /N1G, /S1G

/N1B, /U1B

Integrated amplifier



PM-17SA / mkl

TABLE OF CONTENTS

SECTION	PAGE
1. TECHNICAL SPECIFICATIONS	1
2. BLOCK DIAGRAM	2
3. TEST EQUIPMENT REQUIRED FOR SERVICING	2
4. SCHEMATIC DIAGRAM	3
5. PARTS LOCATION (Pattern Side)	7
6. EXPLODED VIEW AND PARTS LIST	12
7. DC OFFSET VOLTAGE ALIGNMENT	15
8. IDLING CURRENT ALIGNMENT	15
9. ELECTRICAL PARTS LIST	16

Please use this service manual with referring to the user guide (D.F.U.) without fail.
修理の際は、必ず取扱説明書を準備し操作方法を確認の上作業を行ってください。

marantz®

PM-17SA / PM-17mkl


313J855010 MIT
3120 785 22180
First Issue 1989.10

1. TECHNICAL SPECIFICATIONS

Rated power output (20 Hz to 20 kHz, 2CH simultaneous drive)	60 W x 2 (8 Ω load) 80 W x 2 (6 Ω load) 100 W x 2 (4 Ω load)
Total harmonic distortion (20 Hz to 20 kHz, 2CH drive, 8 Ω load)	0.01 %
Cross-modulation distortion (SMPTE)	0.01 %
Output bandwidth (8 Ω load, 0.04 %)	10 Hz to 50 kHz
Frequency response (CD, SOURCE DIRECT)	5 Hz to 70 kHz, +0/-1 dB
Damping factor (8 Ω load, 20 Hz to 20 kHz)	100
Input sensitivity/input impedance	
PHONE (MC)	230 μV/100 Ω
PHONE (MM)	2.5 mV/47 kΩ
HIGH LEVEL	220 mV/22 kΩ
MAIN IN	1.8 V/22 kΩ
Output voltage/output impedance	
PRE OUT	1.6 V/250 Ω
Maximum allowable PHONE input (1 kHz)	
MC	15 mV
MM	150 mV
RIAA deviation (20 Hz to 20 kHz)	±0.2 dB
S/N (IHF A network, input shorted)	76 dB
PHONE (MC)	90 dB
PHONE (MM)	112 dB
HIGH LEVEL	112 dB
Tone control	
BASS (100 Hz)	±8 dB
TREBLE (10 kHz)	±8 dB
Supply voltage	
F version	100 V AC, 50/60 Hz
/K1 version	110 V/220 V AC, 50/60 Hz
/N1, /S1 version	230 V AC, 50 Hz
/U1 version	120 V AC, 60 Hz
Power consumption	180 W
Dimensions (Maximum)	
Width	458 mm
Height	110 mm
Depth	429 mm
Weight	16 kg
Accessories	
Remote control unit (RC-17mkII/PM)	x 1
Dimensions	
Width	44 mm
Height	239 mm
Depth	17.5 mm
Weight (without batteries)	189 g
SUM-4 (R6, "AA" size) dry cell battery	x 2

Design and specifications are subject to change without notice.

2. BLOCK DIAGRAM



3. TEST EQUIPMENT REQUIRED FOR SERVICING

項目	使用 方法
Distortion Analyzer	歪みの測定
歪率計	歪みの測定
Audio Oscillator	Sinewave and squarewave signal source
低周波発生器	正弦波及び矩形波の信号源
AC VTVM	Voltage measurements (AC)
交流電圧の測定	交流電圧の測定
Oscilloscope	Waveform analysis and trouble shooting and ASO alignment
オシロスコープ	波計分析、トラブルシューティング及びASOの調整
DC VTVM	Voltage measurements (DC)
直流電圧の測定	直流電圧の測定
AC Wattmeter	Monitors primary power to amplifier
交流ワットメーター	アンプの一次側消費電力のモニター
Line Voltmeter	Monitors potential of primary power to amplifier
電圧電圧計	アンプの一次側消費電力のモニター
Variable Autotransformer	Adjust level of primary power to amplifier
スライダック	アンプの一次側消費電力の調整
Circuit Tester	Trouble shooting
テストター	トラブルシューティング
Shorting Plug	Shorts amplifier input to eliminate noise pickup
ショートプラグ	雑音を拾わないようにアンプ入力を短絡する

