



## Service Bulletin

No. : MZ04-035

Date: March 6, 2007

**Model:** SR8300/SR9300

**Subject:** SETUP sometimes returns to initial setting.

**Symptom:** The problem can occur when doing the following:

1. Enter the SETUP MENU, Set the Speaker level of SURROUND to "+1dB or more". Then, escape from the MENU.
2. The Sound level is set to "negative infinity" from "other than negative infinity" by VOL Knob.
3. Press the POWER switch to turn off and turn on.
4. "Clear memory" is displayed and SETUP sometimes returns to initial setting.

**Solution:** Update the CPU's software version to V0301234.

Note: before updating please check the CPU (QU01) firmware version. It can be confirmed using the "SERVICE PROGRAM", please refer to page 95 of the SR8200/SR9200 Service Manual for the procedure.

1. Turn on the unit, press **DVD. TUNER** and **MULTI ROOM** key simultaneously more than three seconds.  
**Microprocessor (CPU), DSP Version and FLD Segment Check Mode**

Turn the unit into the Factory Mode (See above) first. Each time **DISPLAY** key is pressed or RC-5 code **161500 (Display)** is entered, information shown on the FLD changes in the following order. Software versions of  $\mu$ -com and DSP can be seen and FLD segments can be checked.

1. Model Name is displayed like "SR9200", "SR8200", "PS9200:."
2. Software version of QU01(CPU) is displayed in the following format.


M	A	I	N	V	0	0	0	4	2	6		0	U
				[Year]	[Month]	[Date]			No	Ver.			

V030123 4

### CONFIDENTIALITY NOTICE:

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.

Please refer to pages 97 and 98 section "9.UPDATE FIRMWARE" in the SR8200/SR9200 service manual for firmware update procedure.



**Parts:**

Ref#	Description	Part Number
NA	Sr9300_01234.mot Firmware update file	*SR8300CD2.zip

**Serial Number Range:**

Update upon customer claim.

---

**CONFIDENTIALITY NOTICE:**

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.