



Service Bulletin

No. : MZ10-032

Date: August 19, 2010

Model: UD8004

Subject: Correction of the firmware.

Countermeasure is applicable only upon claim from the customer.

Symptom: 1) When BD software "Ole Bull Violin Concertos" was reproduced, the "mShuttle" function might not work.
2) When BD software "Clash of the Titans" was reproduced, a sound might be outputted.
3) DVD disc "AVATAR" made in Germany might not be reproduced. After inserting it only shows PLAY in Display.

Solution: We corrected the firmware so that no malfunction occurs.
METHOD OF UPDATE via DPMS (D&M Product Management Server) At the time this bulletin was produced, the firmware update was not uploaded onto the web server for DPMS, we will update the firmware via DPMS once two months.

METHOD OF UPDATE by CD-R The following program files for updating the subject models are available for download. Therefore, please record each program file on a blank CD-R separately, and update the unit upon claim.

* Program Files to be supplied

Folder Name	File Name
BE_Ver000202_FE_Ver000210	DcmUpdate.fw DcmAuthentication
SYS_Ver000205	8004_SYS.ROM
DSP_Ver000101	8004_AD.ROM
DM860_Ver20100422846	8004_860.ROM

CONFIDENTIALITY NOTICE:

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.

Note: Upon recording the Disc:

- a) When recording the supplied file on the blank CD-R, the session shall be "CLOSE".
- b) When recording the supplied file on the disc, please use the lowest recording speed that is available on your PC. If the file is recorded at a higher speed, the rewriting operation may fail due to improperly recorded data on the disc.

Rewriting procedures of the FE/BE ROM

- (1) Download the "DcmUpdate.fw" and "DcmAuthentication" firmware in SDI.
- (2) Please insert the "DcmUpdate.fw" and "DcmAuthentication" firmware into the Root directory.

Root

```
|_____ "DcmUpdate.fw"
|_____ "DcmAuthentication"
```

- (3) Please burn the CD-R.
- (4) Turn the Power Supply of the unit on. Press the "**OPEN/CLOSE**" button and open the Disc Tray.
- (5) Put the recorded CD-R on the Disc Tray and press the buttons on the remote control in the order of "**7**", "**9**", "**2**" and "**RETURN**".
- (6) The Disc Tray will close automatically.
- (7) The FL Display indicates "**LOADING**", then information about updating repetition. Time necessary for update: approximately 25 min.
- (8) The new firmware is installed completely.
- (9) The Disc Tray opens automatically.
- (10) Take out the CD-R from the Disc Tray.

Rewriting procedures of the SYSTEM ROM.

- (1) Download the "**8004_SYS.ROM**" firmware in SDI.
- (2) Please make "**DM_FM_UP**" folder on PC.
- (3) Please insert the "**8004_SYS.ROM**" firmware into "**DM_FM_UP**" folder.

Root ----- DM_FM_UP

```
|_____ "8004_SYS.ROM"
```

- (4) Please burn the CD-R.
- (5) Turn the Power Supply of the unit on. Press the "**OPEN/CLOSE**" button and open the Disc Tray.
- (6) Put the recorded CD-R on the Disc Tray and press the buttons on the remote control in the order of "**7**", "**9**", "**2**" and "**ENTER**".
- (7) The Disc Tray will close automatically.

CONFIDENTIALITY NOTICE:

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.

- (8) The FL Display will indicate information about updating repetition. Time necessary for update: approximately 5 min.
- (9) The unit turns off and turns on, and then "**NO DISC**" is indicated.
- (10) The new firmware is installed completely.
- (11) Press the "**OPEN/CLOSE**" button and open the Disc Tray.
- (12) Take out the CD-R from the Disc Tray.

Rewriting procedures of the DM860ROM.

- (1) Download the "**8004_860.ROM**" firmware in SDI.
- (2) Please make "**DM_FM_UP**" folder on PC.
- (3) Please insert the "**8004_860.ROM**" firmware into "**DM_FM_UP**" folder
Root ----- DM_FM_UP
|_____ "8004_860.ROM"
- (4) Please burn the CD-R.
- (5) Turn the Power Supply of the unit on. Press the "**OPEN/CLOSE**" button and open the Disc Tray.
- (6) Put the recorded CD-R on the Disc Tray and press the buttons on the remote control in the order of "**7**", "**9**", "**2**" and "**ENTER**".
- (7) The Disc Tray will close automatically.
- (8) The FL Display will indicate information about updating repetition. Time necessary for update: approximately 15 min.
- (9) The new firmware is installed completely.
- (10) The Disc Tray opens automatically.
- (11) Take out the CD-R from the Disc Tray.

Rewriting procedures of the DSP ROM.

- (1) Download the "**8004_AD.ROM**" firmware in SDI.
- (2) Please make "**DM_FM_UP**" folder on PC.
- (3) Please insert the "**8004_AD.ROM**" firmware into "**DM_FM_UP**" folder.
Root ----- DM_FM_UP
|_____ "8004_AD.ROM"
- (4) Please burn the CD-R.
- (5) Turn the Power Supply of the unit on. Press the "**OPEN/CLOSE**" button and open the Disc Tray.
- (6) Put the recorded CD-R on the Disc Tray and press the buttons on the remote control in the order of "**7**", "**9**", "**2**" and "**ENTER**".
- (7) The Disc Tray will close automatically.
- (8) The FL Display will indicate information about updating repetition. Time necessary for update: approximately 3 min.
- (9) The new firmware is installed completely.
- (10) The Disc Tray opens automatically.
- (11) Take out the CD-R from the Disc Tray.

CONFIDENTIALITY NOTICE:

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.

Confirmation of the version:

- (1) Press the "OPEN/CLOSE" button and open the Disc Tray.
- (2) Remove the Disc from the Tray.
- (3) Please confirm! "NO DISC" on the FL Display.
- (4) While pushing the "PLAY" and "OPEN/CLOSE" button, turn on the power of unit.
- (5) Plug in AC CORD.
- (6) The indication of "PLAY" and "PAUSE" will be displayed on FL Display.
- (7) Please confirm! "NO DISC" on the FL Display, and wait 10 seconds.
- (8) Press the buttons on the remote control in the order of "3", "2", "6" and "5".
- (9) The version of the firmware will be indicated on the FL Display.
- (10) The firmware list will also be shown on connected TV (GUI).
- (11) Push the "UP" button of cursor button, version of the each firmware will be indicated on the FL Display.

The version of new firmware

	Name	Version
1	Syscom	Ver000205
2	BE	Ver000202
3	FE	Ver000210
4	SACD FPGA	Ver000100 or Ver000200 or Ver000300

	Name	Version
5	DSP	Ver000101
6	AS	Ver000900
7	NC	VerI201004220846

Serial Number Range:

Please apply the above modification to the production models in the following serial numbers. (Full Digits)

*****000001 ~ *****000480

CONFIDENTIALITY NOTICE:

The information contained in this document is intended for the exclusive use by MARANTZ Authorized Service Centers and their employees. This document may contain information that is privileged, confidential and may be protected from disclosure under applicable laws and terms of the MARANTZ Service Agreement. Any distribution, disclosure, dissemination or copying of this document and the information it contains is prohibited. No responsibility will be accepted by MARANTZ for any damage, injury or loss resulting from the misuse of the information contained in this document.