


ONKYO® SERVICE MANUAL

AUDIO VIDEO CONTROL RECEIVER MODEL TX-SV454



Black and Silver models

BMD	120V AC, 60Hz
BMP, BMPT, BMPA, SMP	230V AC, 50Hz
BMWT	120/220V AC, 50/60Hz

SAFETY-RELATED COMPONENT WARNING!!

COMPONENTS IDENTIFIED BY MARK Δ ON THE SCHEMATIC DIAGRAM AND IN THE PARTS LIST ARE CRITICAL FOR RISK OF FIRE AND ELECTRIC SHOCK. REPLACE THESE COMPONENTS WITH ONKYO PARTS WHOSE PARTS NUMBERS APPEAR AS SHOWN IN THIS MANUAL.

MAKE LEAKAGE-CURRENT OR RESISTANCE MEASUREMENTS TO DETERMINE THAT EXPOSED PARTS ARE ACCEPTABLY INSULATED FROM THE SUPPLY CIRCUIT BEFORE RETURNING THE APPLIANCE TO THE CUSTOMER.

TABLE OF CONTENTS

Specifications	2
Service procedures.....	3
Exploded view.....	4
Parts list.....	5
Block diagrams.....	6
Tuner section.....	6
Amp. section.....	33
Microprocessor connection diagram.....	8
Microprocessor terminal descriptions.....	9
IC block diagrams and descriptions.....	10
Printed circuit board parts list.....	14
Adjustment procedures.....	18
Schematic diagrams.....	21
Audio section.....	21
Surround section.....	25
Display/Tuner circuit sections.....	29
Printed circuit board view.....	23
Main circuit section.....	23
Secondary circuit section.....	24
Tone control circuit section.....	24
Volume circuit section.....	27
Rear amplifier section.....	27
Terminal section.....	28
Display and tuner sections.....	31
Power supply section.....	32
Packing view.....	35

ONKYO®
AUDIO COMPONENTS

SPECIFICATIONS

AMPLIFIER SECTION

Power Output

Stereo mode

Front L/R channels: 70 watts per channel, min. RMS at 8 ohms, both channels driven from 20 Hz to 20 kHz with no more than 0.08% total harmonic distortion.

Continuous Power output: 2 × 80 watts at 8 ohms, 1 kHz (DIN)

Surround mode

Front L/R and Center channels: 60 watts per channel, min. RMS at 8 ohms, both channels driven from 20 Hz to 20 kHz with no more than 0.08% total harmonic distortion.

Rear channels (Rear only driven): 20 watts per channel, min. RMS at 8 ohms, both channels driven from 20 Hz to 20 kHz with no more than 0.3% total harmonic distortion.

Total Harmonic Distortion: 0.08% at rated power (Front)

IM Distortion: 0.08% at rated power (Front)

Damping Factor: 60 at 8 ohms (Front)

Sensitivity and Impedance

Phono: 2.5 mV/50 kohms

CD, Multi-CH, Tape Play: 150 mV/50 kohms

Tape Rec: 150 mV/2.2 kohms

Subwoofer Pre out: 2 V/2.2 kohms

Phono Overload: 120 mV RMS at 1 kHz, 0.5% T.H.D.

Frequency Response: 20 Hz to 30 kHz, ±1 dB

RIAA Deviation: 20 Hz to 20 kHz, ±0.8 dB

Tone Control

Bass: ±10 dB at 100 Hz

Treble: ±10 dB at 10 kHz

Signal-to-Noise Ratio

Phono: 80 dB (IHF A, 5 mV input)

CD/Tape: 100 dB (IHF A)

VIDEO SECTION

Signal sensitivity and impedance: 1 Vp-p, 75 ohms (VDP/VCR input, output)

TUNER SECTION

FM

Tuning Range: 87.5 — 108.0 MHz

Usable Sensitivity

Mono: 11.2 dBf, 1.0 μV (75 ohms)

Stereo: 18.2 dBf, 2.2 μV (75 ohms)

50 dB Quieting Sensitivity

Mono: 18.2 dBf, 2.2 μV (75 ohms)

Stereo: 39.2 dBf, 24 μV (75 ohms)

Capture Ratio: 1.5 dB

Image Rejection Ratio

U.S.A. & Canadian models: 40 dB

Other area models: 85 dB

IF Rejection Ratio: 90 dB

Signal-to-Noise Ratio

Mono: 73 dB

Stereo: 67 dB

Alternate Channel Attenuation: 55 dB

Selectivity: 50 dB (DIN)

AM Suppression Ratio: 50 dB

Total Harmonic Distortion

Mono: 0.15%

Stereo: 0.25%

Frequency Response: 30 Hz — 15 kHz, ±1.5 dB

Stereo Separation: 45 dB at 1 kHz

30 dB at 100 Hz — 10 kHz

AM

Tuning Range

U.S.A. & Canadian models: 530—1,710 kHz (10 kHz steps)

European & Australian models: 522—1,611 kHz (9 kHz steps)

Worldwide models: 531—1,602 kHz (9 kHz steps), 530—1,710 kHz (10 kHz steps)

Usable Sensitivity: 30 μV

Image Rejection Ratio: 40 dB

IF Rejection Ratio: 40 dB

Signal-to-Noise Ratio: 40 dB

Total Harmonic Distortion: 0.7%

GENERAL

Power Supply

U.S.A. & Canadian models: AC 120 V, 60 Hz

European & Australian models: AC 230 V, 50 Hz

Worldwide models: AC 220-230 V and 120 V switchable, 50/60 Hz

Power Consumption

U.S.A. & Canadian models: 3.5 A (420 W)

Other area models: 250 W

Dimensions (W × H × D): 435 × 150 × 322 mm
17-1/8" × 5-7/8" × 12-11/16"

Weight: 9.6 kg, 21.2 lbs.

REMOTE CONTROL (RC-371M)

Transmitter: Infrared

Signal range: Approx. 5 meters, 16 ft.

Power supply: Two "AAA" batteries (1.5 V × 2)

Dimensions (W × H × D): 53 × 22 × 197 mm


2-1/16" × 7/8" × 7-3/4"


Weight: 132 grams (4.7 oz.) (including batteries)

Specifications and features are subject to change without notice.

SERVICE PROCEDURES

1. Replacing the fuses

 This symbol located near the fuse indicates that the fuse used is fast operating type. For continued protection against fire hazard, replace with same type fuse. For fuse rating refer to the marking adjacent to the symbol.

 Ce symbole indique que le fusible utilise est a rapide. Pour une protection permanente, n'utiliser que des fusibles de meme type. Ce dernier est indique la qu le present symbol est appose.

CIRCUIT NO.	PART NO.	DESCRIPTION
F901	252164Y	5A-UL/T-237,Primary <D/W>
F902	252076	3.15A-SE-EAK ,Primary <P/W>
F903	252075	2.5A-SE-EAK,Primary <P>
F991, F992	252163Y	4A-UL/T-237,Secondary<D>
	252077	4A-SE-EAK,Secondary<P/W>
		NOTE : <D> : 120V model only
		<P> : 230V model only
		<W> : Worldwide model

2. To Initialize the unit

This device employs a microprocessor to perform various functions and operations. If interference generated by an external power supply, radio wave, or other electrical source results in accident which causes the specified operations and functions to operate abnormally.

To perform a result, please follow the procedure below.

1. Turn the power button "ON"
2. Press and hold down the Video 1 button, then press the SPEAKER A button.
3. After "clear" is displayed, the preset memory and each mode stored in the memory, such as surround, are initialized and will return to the factory settings.

3. Safety-check out

(Only U.S.A. model)

After correcting the original service problem, perform the following safety check before releasing the set to the customer. Connect the insulating-resistance tester between the plug of power supply cord and the screw on the back panel.

Specifications: 3.3 Mohm \pm 10% at 500V.


4. Change of voltage

Worldwide models are equipment with a voltage selector to conform with local power supplies. This switch is located on the back panel.

Be sure to set this switch to match the voltage of the power supply in your area before turning the power switch on.

This switch is set to 220V at the factory. Voltage is changed by

sliding the groove in the switch with the screwdriver to the right or left. Confirm that the switch has been moved all the way to the right or left before turning the power switch on.



5. Memory preservation

This unit does not require memory preservation batteries.

A built-in memory power back-up system preserves contents of the memory during power failures and even when the unit is unplugged.

The unit must be plugged in and the power switch turned on and off once in order to charge the back-up system. Note that since this is not a permanent memory, the power switch must be turned on and off a few times each month the keep the back-up system operative.

The period of the time during which memory contents are preserved after power has last been turned off varies depending on climate and placement of the unit. On the average, memory contents are protected over a period of 3 to 4 weeks (a minimum of 2 weeks) after the last time power has been turned off. This period is shorted when the unit is exposed to very high humidity or used in an area with an extremely humid climate.


6. Setting the tuning step frequency

Worldwide models are equipped with a step band selector switch. This switch is located on the back panel. This switch is set to 9 kHz at the factory, but may have to be reset to 10 kHz depending on the area where the unit is used.

AM band step

Europe: 9 kHz

U.S.A.: 10 kHz




7. Changing the band step

With the exception of the worldwide models, a tuning step selector switch is not provided. When you change the band step, change the parts as shown below.

FM	To 100kHz	To 50kHz
AM	To 10kHz	To 9kHz
R727	Open	Short
R724	3.3kohm	Remove

EXPLODED VIEW




NOTE: THE COMPONENTS IDENTIFIED BY MARK **△** ARE CRITICAL FOR RISK OF FIRE AND ELECTRIC SHOCK. REPLACE ONLY WITH PART NUMBER SPECIFIED.

PARTS LIST


NOTE:
 <D>:120V model only
 <W>:230V model only
 <W>:Taiwanese model only
 <T>:Asian model only
 <A>:Australian model only
 :Black model only
 <S>:Silver model only

REF. NO.	PART NO.	DESCRIPTION	REF. NO.	PART NO.	DESCRIPTION
3	27160375	Heatsink	Q1512	2202843 or	25C5242-O or
4	801433	3SM58W SW+14B(BC),Special screw	Q523,Q524	2202842	25C5242-R,Transistor
5	838130088	3TTB+8B,Self-tapping screw	Q1513	2202833 or	25A1962-O or
8	27141671	Retainer	Q525,Q526	2202832	25A1962-R,Transistor
11	27160376	Heatsink S	Q823,Q824	2202923 or	25C5196-O or
17	27191044	KGFS-8RF Holder	Q823,Q824	2202922	25C5196-R,Transistor
18	27100320B	Chassis	Q825,Q826	2202913 or	25A1939-O or
19	27190503A	KGLS-8RF Holder	Q825,Q826	2202912	25A1939-R,Transistor
20	27190286	KGLS-12RF Holder	T901	2301323	NPT-1337D,Power transformer <D>
24	28175225	Isolated plate		2301324	NPT-1337P,Power transformer <P/T/A>
26	27111068	Front bracket <S>	U1	2301325	NPT-1337DC,Power transformer <W>
32	27190896	Front bracket 		IA771533-1A	NAAR-6233-1A,Main circuit pc board assy <D>
36	830440089	KGLS-10S Holder		IA771533-1B	NAAR-6233-1B,Main circuit pc board assy <P>
38	27300750	4TTT+8C(BC),Self-tapping screw	U2	IA771533-1C	NAAR-6233-1C,Main circuit pc board assy <T/W/A>
42	27175319A	#2771,Steinrelief		IA771534-1A	NAETC-6234-1A,Secondary circuit pc board assy <D>
43	28141332	Cushion	U3	IA771534-1B	NAETC-6234-1B,Secondary circuit pc board assy <D>
45	831430088	3TTW+8B(BC),Self-tapping screw		IA771534-1C	NAETC-6234-1C,Secondary circuit pc board assy <T/W/A>
51	28325457	Knob, Volume <S>	U4	IA771535-1A	NAETC-6235-1A,Tone volume pc board assy <D>
53	28325456	Knob, Volume 		IA771535-1B	NAETC-6235-1B,Tone volume pc board assy <P>
55	28325454	Knob, Tone <S>		IA771535-1C	NAETC-6235-1C,Tone volume pc board assy <T/W/A>
56	28184663	Knob, Tone 		IA771536-1A	NADIS-6236-1A,Display circuit pc board assy <D>
57	28325455	Knob, Tone <S>		IA771536-1B	NADIS-6236-1B,Display circuit pc board assy <P>
58	28184666	Knob, Tone 		IA771536-1C	NADIS-6236-1C,Display circuit pc board assy <T>
60	28184663	Top cover 		IA771536-1D	NADIS-6236-1D,Display circuit pc board assy <W>
61	838230088	3TTB+8B(ND),Nickel screw <S>	U5	IA771536-1E	NADIS-6236-1E,Display circuit pc board assy <A>
62	838430088	3TTB+8B(BC),Self-tapping screw 		IA771537-1A	NARF-6237-1A,Tuner circuit pc board assy <D>
71	27122450	Rear panel <D>		IA771537-1B	NARF-6237-1B,Tuner circuit pc board assy <P>
72	27122451	Rear panel <P>		IA771537-1C	NARF-6237-1C,Tuner circuit pc board assy <T>
73	27122454	Rear panel <T>		IA771537-1D	NARF-6237-1D,Tuner circuit pc board assy <W>
74	27122452	Rear panel <W>		IA771538-1A	NARF-6237-1E,Tuner circuit pc board assy <A>
75	27122453	Rear panel <A>	U6	IA771538-1B	NARF-6237-1E,Tuner circuit pc board assy <A>
76	87643010	W3*10F(BC),Washer		IA771538-1C	NAPS-6238-1A,Primary circuit pc board assy <D>
77	838230088	3TTB+8B(ND),Nickel screw		IA771538-1B	NAPS-6238-1B,Primary circuit pc board assy <P>
78	27212001	Front panel <S>		IA771538-1C	NAPS-6238-1C,Primary circuit pc board assy <T>
79	27211994	Front panel <D>		IA771538-1D	NAPS-6238-1D,Primary circuit pc board assy <W>
80	27211995	Front panel <P/A>	U7	IA771538-1E	NAPS-6238-1E,Primary circuit pc board assy <A>
81	27211996	Front panel <T/W>		IA771539-1A	NAETC-6239-1A,Video terminal pc board assy <D>
82	28325451	Badge <S>		IA771539-1B	NAETC-6239-1B,Video terminal pc board assy <P>
83	28135244	Decorative frame <S>		IA771539-1C	NAETC-6239-1C,Video terminal pc board assy <T>
84	27215302	Decorative frame 		IA771539-1D	NAETC-6239-1D,Video terminal pc board assy <W>
85	28191778	Clear plate <S>	U8	IA771539-1E	NAETC-6239-1E,Video terminal pc board assy <A>
86	28191752A	Clear plate 		IA771540-1A	NAETC-6240-1A,Headphone terminal pc board assy <D>
87	28325458	Knob, Power <S>		IA771540-1B	NAETC-6240-1B,Headphone terminal pc board assy <P>
88	28325451	Knob, Power 		IA771540-1C	NAETC-6240-1C,Headphone terminal pc board assy <T>
89	28325451	Knob, Power <P/T/W/A>		IA771540-1D	NAETC-6240-1D,Headphone terminal pc board assy <W>
90	27267956	Guide, Power <S>	U9	IA771540-1E	NAETC-6240-1E,Headphone terminal pc board assy <A>
91	27267955	Guide, Power <P/T/W/A>		IA771541-1A	NAETC-6241-1A,Terminal pc board assy <D>
92	27267955	Guide, Power <P/T/W/A>		IA771541-1B	NAETC-6241-1B,Terminal pc board assy <P>
93	27267955	Guide, Power <P/T/W/A>		IA771541-1C	NAETC-6241-1C,Terminal pc board assy <T>
94	27267955	Guide, Power <P/T/W/A>		IA771541-1D	NAETC-6241-1D,Terminal pc board assy <W>
95	27267955	Guide, Power <P/T/W/A>	U10	IA771541-1E	NAETC-6241-1E,Terminal pc board assy <A>
96	27267955	Guide, Power <P/T/W/A>		IA771542-1A	NAETC-6242-1A,Transformer pc board assy <D>
97	27267955	Guide, Power <P/T/W/A>		IA771542-1B	NAETC-6242-1B,Transformer pc board assy <P>
98	27267955	Guide, Power <P/T/W/A>		IA771542-1C	NAETC-6242-1C,Transformer pc board assy <T>
99	27267955	Guide, Power <P/T/W/A>		IA771542-1D	NAETC-6242-1D,Transformer pc board assy <W>
100	27267955	Guide, Power <P/T/W/A>	U11	IA771542-1E	NAETC-6242-1E,Transformer pc board assy <A>
101	27267955	Guide, Power <P/T/W/A>		IA771594-4A	NAAF-5894-4A,Dolby circuit pc board assy <D>
102	27267955	Guide, Power <P/T/W/A>		IA771594-4B	NAAF-5894-4B,Dolby circuit pc board assy <P>
103	27267955	Guide, Power <P/T/W/A>		IA771594-4C	NAAF-5894-4C,Dolby circuit pc board assy <T>
104	27267955	Guide, Power <P/T/W/A>		IA771594-4D	NAAF-5894-4D,Dolby circuit pc board assy <W>
105	27267955	Guide, Power <P/T/W/A>	U12	IA771595-4A	NAAF-5895-4A,Rear Amplifier pc board assy <D>
106	27267955	Guide, Power <P/T/W/A>		IA771595-4B	NAAF-5895-4B,Rear Amplifier pc board assy <P>
107	27267955	Guide, Power <P/T/W/A>		IA771595-4C	NAAF-5895-4C,Rear Amplifier pc board assy <T>
108	27267955	Guide, Power <P/T/W/A>	U13	IA771595-4D	NAAF-5895-4D,Rear Amplifier pc board assy <W>
109	27267955	Guide, Power <P/T/W/A>		25136243	NAETC-6243,Holder for lead wire


**BLOCK DIAGRAM
TUNER SECTION
120V MODEL**



OTHER MODELS



MICROPROCESSOR CONNECTION DIAGRAM



MICROPROCESSOR TERMINAL DESCRIPTION

Pin No.	Function	Descriptions
1-7	7G-1G	Grid output terminals
8	VDD	Positive power supply terminal (+5V)
9	CL	Clock output terminal.
10	DATA	Data output terminal.
11	PLL	Chip enable output terminal for PLL IC
12	VOLC	Clock output terminal for electro volume of center channel.
13	VOLS	Clock output terminal for electro volume of surround channels.
14	STB	Strobe output terminal
15	VOLUP	Volume control output terminal
16	VOLDOWN	Volume control output terminal
17	RESET	System reset input terminal
18	REQ	Request terminal for Digital delay and Dolby ICs
19	VIDEO-1V	Video signal selector terminal
20	AVSS	Ground terminal for A/D converter
21	MODE2	Initializing input terminal
22	AREA	Initializing input terminal for region of frequency range
23	MODE1	Initializing input terminal
24	K4-K0	Key input terminals
29	AVDD	Analog power supply terminal (+5V)
30	AVREF	Reference voltage input terminal for A/D converter
31	XT1	Crystal connection terminals for subsystem clock
32	XT2	Not used.
33	VSS	Ground terminal
34	X1	Crystal connection terminals for main system clock
35	X2	Connect the 4.19MHz ceramic oscillator.
36	TUMUT	Muting output terminal for tuner section
37	FRONTMUT	Muting output terminal for amplifier of front channels.
38	SPBRL	Speaker relay B control output terminal
39	SPARL	Speaker relay A control output terminal
40	POWER	Power source control output terminal
41	SYSOUT	System code output terminal
42	RDSSIG	Detection input terminal for RDS broadcast
43	RDSDATA	Data input terminal for RDS broadcast
44	RDSSCK	Clock input terminal from RDS demodulator
42	DSPSCK	Clock output terminal for KARAOKE IC.
43	DSPDATA	Data output terminal for KARAOKE IC.

Pin No.	Function	Descriptions
44	DSPCS	Chip select output terminal for KARAOKE IC.
45	POFF	Power failure detection input terminal
46	SYSIN	system code input terminal
47	REMIN	Remote control signal input terminal
48	IC	Internal connection terminal
49	RE-EQ	RE-EQ control output terminal
50	STBY/RECV	STANDBY/RECEIVED indication output terminal
51	3DB	3-D bass control output terminal
52	VDD	Power supply terminal (+5V)
53	STEREO	Stereo broadcast detection input terminal
54	SD	Broadcast detection input terminal
55,56	NC	Not used.
57	IPM	Audio IPM operation input terminal
58	PROTECT	Detection input terminal for protection circuit
59	P16-P5	Segment output terminals
71	VLOAD	Pull-down resistor connection terminal for FIP controller and driver
72	P4-P1	Segment output terminals
76-80	I2G-8G	Grid output terminals

Volume control output

	15	16
Stop	H	H
Up	H	L
Down	L	H

FM band

BAND1	BAND0	Region	Frequency Range	Channel space
0	0	Europe	87.50~108.00MHz	50kHz
0	1	Saudi	87.50~108.00MHz	50kHz
1	0	Japan	76.0~90.0MHz	100kHz
1	1	U.S.A	87.5~108MHz	100kHz

AM band

BAND1	BAND0	AM10K	Region	Frequency Range	Channel space
0	0	0	Europe	522~1611kHz	9 kHz
0	1	0	Saudi	531~1602kHz	9 kHz
1	0	0	Japan	522~1629kHz	9 kHz
1	1	0	U.S.A	522~1629kHz	9 kHz
1	1	1	U.S.A	530~1710kHz	10 kHz

PRINTED CIRCUIT BOARD PARTS LIST

MAIN CIRCUIT PC BOARD(NAAR-6233-1A/1B/1C)

CIRCUIT NO.	PART NO.	DESCRIPTION	CIRCUIT NO.	PART NO.	DESCRIPTION
					Transistors
Q281,Q401	22240293 or	NJM4558L-D or	Q583	2211792 or	2SA992-F or
Q402,Q405	22240247	BA15218N		2211793	2SA992-E
Q301	222502	NJM4558D-X	Q591,Q592	2215830 or	KRC105M or
Q302	22240881	TC9273N-010		2213640	DTC123JS
Q407,Q409	222502	NJM4558D-X	Q924	2214905 or	2PA1015-GR or
Q410	222502	NJM4558D-X		2211455	2SA1015-GR
Q411,Q412	22240025	LC4966			Diodes
Q481	22240239	TA7291S	D281,D282	223260 or	1N4148 or
Q921	222780125NEC	MPC78M12HF	D401~D403	223163	1SS133
Q922	222790125	79M12HF	D501~D504	22380260,	RL1N4003,
Q923	222780565JRC	NJM78M56FA	D915~D921	22380032	1SR139-100 or
				22380035	GP104003E
					Transistors
Q1501-Q1503	2215116 or	2SC1775-F or	D591,D592	223260 or	1N4148 or
	2211732	2SC1845-F	D912	223163	1SS133
Q1504,Q1505	2215843 or	KTA1024-O or	D911	22380021	RS403L
Q1507	2211353	2SA949-O	D922	224473304	MTZJ33D
Q1506,Q1508	2215853 or	KTC3206-O or	D923,D924	223260 or	1N4148 or
Q1509	2211633	2SC2229-O		223163	1SS133
Q1510	2203010	2SC5171			Capacitors
Q1511	2203000	2SA1930	C1501	354742209	22 μ F,16V,Elect.
Q1512	2202843 or	* 2SC5242-O or	C1502	374721015	100pF \pm 10%,50V,Plastic
	2202842	* 2SC5242-R	C1503	354741019	100 μ F,16V,Elect.
Q1513	2202833 or	* 2SA1962-O or	C1504,C1505	354781009	10 μ F,50V,Elect.
	2202832	* 2SA1962-R	C1511	374721044	0.1 μ F \pm 5%,50V,Plastic
Q1514	2211733 or	2SC1845-E or	C1512	354744709	47 μ F,16V,Elect.
	2211732	2SC1845-F	C1513~C1517	354781009	10 μ F,50V,Elect.
Q1515	2215864 or	KTC3199-GR or	C281~C283	354741009	10 μ F,16V,Elect.
	2213284	2SC1740S-R	C284	354780229	2.2 μ F,50V,Elect.
Q282	2215780 or	KRA103M or	C285,C286	354741009	10 μ F,16V,Elect.
	2212600	DTA124ES	C303,C304	354741009	10 μ F,16V,Elect.
Q283	2213816,	2SD1450-T,	C307,C308	354721019	100 μ F,6.3V,Elect.
	2212356 or	2SD1302-T or	C309,C310	374726224	6200pF \pm 5%,50V,Plastic
	2213815	2SD1450-S	C311,C312	374721824	1800pF \pm 5%,50V,Plastic
Q284	2215810 or	KRC103M or	C313~C316	354741009	10 μ F,16V,Elect.
	2213160	DTC124ES	C391~C393	374721015	100pF \pm 10%,50V,Plastic
Q285	2215800 or	KRA111M or	C401,C402	354741009	10 μ F,16V,Elect.
	2215240	DTA114TS	C407~C410	374721044	0.1 μ F \pm 5%,50V,Plastic
Q403,Q404	2211945	2SK246-GR	C413,C414	354741009	10 μ F,16V,Elect.
Q406	2211945	2SK246-GR	C415,C416	374721534	0.015 μ F \pm 5%,50V,Plastic
Q413,Q426	2215790 or	KRA107M or	C417,C418	374721015	100pF \pm 10%,50V,Plastic
	2213090	DTA114YS	C427,C454	374721044	0.1 μ F \pm 5%,50V,Plastic
Q423~Q425	2213631	RN1241-A	C431,C432	354741009	10 μ F,16V,Elect.
Q427	2215770 or	KRA102M or	C433~C436	374721224	1200pF \pm 5%,50V,Plastic
	2213510	DTA114ES	C437,C438	354741009	10 μ F,16V,Elect.
Q501~Q506	2215116 or	2SC1775-F or	C439,C440	374722224	2200pF \pm 5%,50V,Plastic
	2211732	2SC1845-F	C451,C457	354741009	10 μ F,16V,Elect.
Q507~Q510	2215843 or	KTA1024-O or	C456,C462	374721044	0.1 μ F \pm 5%,50V,Plastic
	2211353	2SA949-O	C458,C459	374721224	1200pF \pm 5%,50V,Plastic
Q511,Q512	2215853 or	KTC3206-O or	C460,C463	354741009	10 μ F,16V,Elect.
Q515~Q518	2211633	2SC2229-O	C461	374722224	2200pF \pm 5%,50V,Plastic
Q513,Q514	2215843 or	KTA1024-O or	C465~C467	354741009	10 μ F,16V,Elect.
	2211353	2SA949-O	C501,C502	354741009	10 μ F,16V,Elect.
Q519,Q520	2203010	2SC5171	C503,C504	374721015	100pF \pm 10%,50V,Plastic
Q521,Q522	2203000	2SA1930	C505,C506	354742219	220 μ F,16V,Elect.
Q523,Q524	2202843 or	* 2SC5242-O or	C507~C510	354781009	10 μ F,50V,Elect.
	2202842	* 2SC5242-R	C519,C520	374721044	0.1 μ F \pm 5%,50V,Plastic
Q525,Q526	2202833 or	* 2SA1962-O or	C521,C522	354744709	47 μ F,16V,Elect.
	2202832	* 2SA1962-R	C525~C528	354774719	470 μ F,6.3V,Elect.
Q527,Q528	2211733 or	2SC1845-E or	C581	354721015	100 μ F,6.3V,Elect.
	2211732	2SC1845-F	C910	354732219	220 μ F,10V,Elect.
Q529,Q530	2215864 or	KTC3199-GR or	C915,C916	3504339,	8200 μ F,56V,Elect.,
	2213284	2SC1740S-R		3504280 or	8200 μ F,56V,Elect. or
Q581,Q582	2215116 or	2SC1775-F or		3504298	8200 μ F,56V,Elect. <D>
	2211732	2SC1845-F			

CAUTION: Replacement of the transistor of mark *, if necessary, must be made from the same beta group (HFE) as the original type.

CIRCUIT NO.	PART NO.	DESCRIPTION
Capacitors		
C915,C916	3504340, 3504285 or 3504299	1000 μ F,56V,Elect., 10000 μ F,56V,Elect. or 10000 μ F,56V,Elect.<P/T/W/A>
C917	354753329	3300 μ F,25V,Elect.
C918	354761029	1000 μ F,35V,Elect.
C922,C923	354781009	10 μ F,50V,Elect.
C924,C925	3504314 or 3504310	4700 μ F,35V,Elect. or 4700 μ F,35V,Elect.
C926	354781009	10 μ F,50V,Elect.
C928,C929	354781019	100 μ F,50V,Elect.
C932	354741009	10 μ F,16V,Elect.
Resistors		
R1512,R1513	443526804	68 Ω \pm 5%,1/2W,Metal oxide
R1515	443525604	56 Ω \pm 5%,1/2W,Metal oxide
R1516	443526804	68 Ω \pm 5%,1/2W,Metal oxide
R1519	4500197 or 4500107	330 Ω \pm 5%,1/4W or 330 Ω \pm 5%,1/4W,Metal
R1522,R1523	4500171 or 4500055	2.2 Ω \pm 5%,1/4W,Metal or 2.2 Ω \pm 5%,1/4W,Metal
R1524	4000132	RGC55 0.22,Special
R1529	453630824	8.2 Ω \pm 5%,1W,Metal
R1532	5210259	N06HR2KBC,Trimming
R521~R524	443526804	68 Ω \pm 5%,1/2W,Metal oxide
R525,R526	443525604	56 Ω \pm 5%,1/2W,Metal oxide
R527,R528	443526804	68 Ω \pm 5%,1/2W,Metal oxide
R539~R542	4500171 or	2.2 Ω \pm 5%,1/4W or
R567~R570	4500055	2.2 Ω \pm 5%,1/4W,Metal
R543,R544	4500197 or 4500107	330 Ω \pm 5%,1/4W or 330 Ω \pm 5%,1/4W,Metal
R547,R548	4000132	RGC55 0.22,Special
R555,R556	453630824	8.2 Ω \pm 5%,1W,Metal
R557,R558	443623914	390 Ω \pm 5%,1/2W,Metal oxide
R573,R574	5210259	N06HR2KBC,Trimming
R933	443524704	47 Ω \pm 5%,1/2W,Metal oxide
Relays		
RL501,RL502	25065517	NRL-2P5A-DC24-098
Terminals		
P301,P302	25045538, 25045300 or 25045458	NPJ-6PDWR362, NPJ-6PDBL159 or NPJ-6PDBL279
P303	25045537, 25045303 or 25045460	NPJ-4PDWR361, NPJ-4PDBL162 or NPJ-4PDBL281
P501	25060147	NTM-4PDMN075
P502	25060273 or 25060161	NTM-4PDML204 or NTM-4PDML087
Plugs		
P1511	25055038	NPLG-2P29
P211a	25055709	NPLG-13P665
P511,P512	25055038	NPLG-2P29
P612a	25055706	NPLG-10P662
Sockets		
P611a	25051752	NSCT-12P1539
P701b	25052044, 25050975 or 25051842	NSCT-35P1831, NSCT-35P762 or NSCT-35P1629
JL261a	25051088	NSCT-4P875
JL401a	25051093	NSCT-9P880
JL911a,JL912a	25051111	NSCT-7P898
JL914a	25051108	NSCT-4P895

NOTE: THE COMPONENTS IDENTIFIED BY MARK Δ ARE CRITICAL FOR RISK OF FIRE AND ELECTRIC SHOCK. REPLACE ONLY WITH PART NUMBER SPECIFIED.

SECONDARY CIRCUIT PC BOARD(NAETC-6234-1A/1B/1C)

CIRCUIT NO.	PART NO.	DESCRIPTION
Fuseholders		
F991a,F992a	25052087 or 25050065	Δ HTF-015 or Δ YSH403T
Fuses		
F991,F992	252077	Δ 4A-SE-EAK,Fuse <P/T/W/A>
F991,F992	252163	Δ 4A-UL/T-237,Fuse <D>
Socket		
JL911b	25051111	NSCT-7P898
Capacitors		
C992,C993	374721044	0.1 μ F \pm 5%,50V,Plastic
C995,C996	374731044	0.1 μ F \pm 5%,50V,Plastic
C997,C998	374721044	0.1 μ F \pm 5%,50V,Plastic
Resistors		
R991,R992	453530224	2.2 Ω \pm 5%,1/2W,Metal

TONE VOLUME PC BOARD(NAETC-6235-1A/1B/1C)

CIRCUIT NO.	PART NO.	DESCRIPTION
C411,C412	374721534	0.015 μ F \pm 5%,50V,Plastic
R400	5131434 or 5104288	N12RLC250KWT20Z or N11RLC250KWT20Z,Variable
R419,R421	5132435 or 5104356	N14RGLC100KWT20Z or N14RLC100KWT20Z,Variable
JL401b	25051093	NSCT-9P880,Socket

DISPLAY CIRCUIT PC BOARD(NADIS-6236-1A/1B/1C/1D/1E)

CIRCUIT NO.	PART NO.	DESCRIPTION
FL tube		
Q702	212156	12-BT-101GK
Remote sensor		
U701	241305	GPIU281X
ICs		
Q701	22241059	MPD78043FGF-018
Q751	22241124	BU1922 <P>
Transistors		
Q703	2215820 or 221282	KRC104M or DTC144ES
Q705,Q706	2215864 or 2213284	KTC3199-GR or 2SC1740S-R
Q707	2215770 or 2213510	KRA102M or DTA114ES
Q752	2215820 or 221282	KRC104M or DTC144ES <P>
Diodes		
D701~D705	223260 or	1N4148 or
D708	223163	1SS133
D706,D707	224470562	MTZJ5.6B
D709	225290	SEL4110R
D710~D712	223260 or 223163	1N4148 or 1SS133
D751	223260 or 223163	1N4148 or 1SS133 <P>
Coils		
L701~L703	233454K220 or 233526K220	NCH-1452 220K or NCH-1561 220K
Oscillators		
X701	3010163	CST4.19MGW
X751	3010203	AF6146CG <P>
Capacitors		
C701	3000075	ECC55R5T473,Super
C702	375524744	0.47 μ F \pm 5%,50V,Plastic
C703,C709	355721019	100 μ F,6.3V,Elect.
C704	355780109	1 μ F,50V,Elect.
C706,C707	355780109	1 μ F,50V,Elect.
C711	355721019	100 μ F,6.3V,Elect.

CIRCUIT NO.	PART NO.	DESCRIPTION	CIRCUIT NO.	PART NO.	DESCRIPTION
	Capacitors			Capacitors	
C751	354721019	100 μ F, 6.3V, Elect. <P>	C001	354741019	100 μ F, 16V, Elect.
C753	354780229	2.2 μ F, 50V, Elect. <P>	C109, C110	374722724	2700pF \pm 5%, 50V, Plastic <P/T/W/A>
C754	374725614	560pF \pm 5%, 50V, Plastic <P>	C127	354721019	100 μ F, 6.3V, Elect.
	Push switches		C130, C159	354780229	2.2 μ F, 50V, Elect.
S701~S704	25035652	NPS-111-S604	C131	374722234	0.022 μ F \pm 5%, 50V, Plastic
	25035652	NPS-111-S604	C132, C153	354783399	0.33 μ F, 50V, Elect.
	25035652	NPS-111-S604	C133, C142	354741019	100 μ F, 16V, Elect.
S707~S738	25035652	NPS-111-S604	C145, C154	354741009	10 μ F, 16V, Elect.
S739	25035653	NPS-122-L605 <P/T/W/A>	C146	374723324	3300pF \pm 5%, 50V, Plastic
	Sockets		C147	374721234	0.012 μ F \pm 5%, 50V, Plastic <P/T/W/A>
JL711a	25051090	NSCT-6P877	C147	374721834	0.018 μ F \pm 5%, 50V, Plastic <D>
P701a	25052081	NSCT-35P1868,	C149	354780479	4.7 μ F, 50V, Elect.
P701aor	25051879 or	NSCT-35P1666 or	C151, C152	354780109	1 μ F, 50V, Elect.
P701aor	25050941	NSCT-35P728	C155, C156	374721034	0.01 μ F \pm 5%, 50V, Plastic <D>
	Holder		C155, C156	374724724	4700pF \pm 5%, 50V, Plastic <P/T/A>
Q702a	27190989	(FL)	C155, C156	374725624	5600pF \pm 5%, 50V, Plastic <W>
	TUNER CIRCUIT PC BOARD(NARF-6237-1A/1B/1C/1D/1E)		C160	354784799	0.47 μ F, 50V, Elect.
	CIRCUIT NO. PART NO. DESCRIPTION		C162, C166	354741009	10 μ F, 16V, Elect.
	Front end		C171, C172	354741009	10 μ F, 16V, Elect.
TU001	240098	ENV172DIG1 <D>	C173, C174	374721024	1000pF \pm 5%, 50V, Plastic <D>
	240099	ENV172A0G1 <P/T/W/A>	C177	354780229	2.2 μ F, 50V, Elect.
	ICs		C178	354741009	10 μ F, 16V, Elect.
Q121	22241076 or	LM7001J or		Resistors	
	22240090	LM7001	R150	5210261	N06HR5KBC, Trimming
Q141	22240983	LA1851N-F	R158	5210264	N06HR30KBC, Trimming
	Transistors			Terminals	
Q101	2210746	2SC945A-P <P/T/W/A>	P101	25060117,	NTM-2PDML051,
Q102	2211723	2SC1923-O		25060222 or	NTM-2PDML144 or
Q122, Q142	2215770,	KRA102M,	P101	25060270	NTM-2PDML201 <P/T/W/A>
Q175	2213510 or	DTA114ES or		25060195,	NTM-4PDML117,
	2214350	RN2202		25060239 or	NTM-4PDML161 or
Q123	2212445	2SK365-GR		25060272	NTM-4PDML203 <D>
Q124, Q171	2215864,	KTC3199-GR,		Socket	
Q172	2212115 or	2SC2458-GR or	P211b	25051238	NSCT-13P1028
	2213284	2SC1740S-R		Plug	
Q143	2215820 or	KRC104M or	TP101	25055038	NPLG-2P29
	221282	DTC144ES		Shield plate	
Q144	2215830 or	KRC105M or	E856	27150397	<P/T/W/A>
	2213640	DTC123JS		PRIMARY CIRCUIT PC BOARD(NAPS-6238-1A/1B/1C/1D/1E)	
Q173, Q174	2215024	2SD1468S-R		CIRCUIT NO. PART NO. DESCRIPTION	
Q182	2215864,	KTC3199-GR,	Q951	Transistor	
	2212115 or	2SC2458-GR or		2213640 or	DTC123JS or
	2213284	2SC1740S-R <P>		2215830	KRC105M
	Diode			Diodes	
D165	224470512	MTZJ5.1B	D951	22380260,	RL1N4003,
	Transformers and coils		D953, D954	22380032 or	1SR139-100 or
L101	233457	NFIF-4081		22380035	GP104003E <P/T/W/A>
L102	233458	NFIF-4082	D952	22380260,	RL1N4003,
L103	233471	NMC-6084 <P/T/W/A>		22380032 or	1SR139-100 or
L104	233526K220 or	NCH-1561 220K or		22380035	GP104003E
	233454K220	NCH-1452 220K	D955	223260 or	1N4148 or
L105	232174	NMRF-5077		223163	1SS133
L106	232176	NMIF-6094		Power transformer	
L107, L108	233484	NMC-4085 <P/T/W/A>	T902	2300670A or Δ	NPT-1111D or
L109, L110	231092	NCH-2140 <D>		Δ 2301258	NPT-1294D <D>
	Ceramic filters			Δ 2300671A	NPT-1111P <P/T/A>
X101, X103	3010071	SFE-10.7MA5 RED		Δ 2300672A	NPT-1111DG <W>
X102	3010130	SFE10.7M22K <P/T/W/A>		Fuses	
X104	3010268	CSB456F23	F901	252164	Δ 5A-UL/T-237, Fuse <D/W>
	Oscillator		F902	252076	Δ 3.15A-SE-EAK, Fuse <P/T/W/A>
X121	3010141	XTL-7.2M	F903	252075	Δ 2.5A-SE-EAK, Fuse <P/T>

CAUTION: Replacement of the transistor of mark *, if necessary, must be made from the same beta group (HFE) as the original type.

NOTE: THE COMPONENTS IDENTIFIED BY MARK Δ ARE CRITICAL FOR RISK OF FIRE AND ELECTRIC SHOCK. REPLACE ONLY WITH PART NUMBER SPECIFIED.

CIRCUIT NO.	PART NO.	DESCRIPTION
Fuseholders		
F901a	25052087 or Δ	HTF-015 or
	25050065 Δ	YSH403T <D/W>
F902a	25052087 or Δ	HTF-015 or
	25050065 Δ	YSH403T <P/T/W/A>
F903a	25052087 or Δ	HTF-015 or
	25050065 Δ	YSH403T <P/T>
Sockets		
JL961a	25051088	NSCT-4P875
P903	25051125 Δ	NSCT-4P912 <P/T/W>
	25051126 Δ	NSCT-4P913 <D>
Plug		
P901a	25055675 Δ	NPLG-2P631
Switch		
S901	25065437 Δ	NSS-22157P <W>
Relay		
RL901	25065515 or Δ	NRL-1P5A-DC12-096 or
	25065561 Δ	NRL-1P5A-DC12-127
Capacitors		
C901	3500191 Δ	DE7150F-103M,IS
C952	354743319	330 μ F, 16V, Elect.
Resistors		
R901	431533355 Δ	3.3M Ω , 1/2W, Solid <D>
R951	453530824	8.2 Ω \pm 5%, 1/2W, Metal <P/T/W/A>

VIDEO TERMINAL PC BOARD(NAETC-6239-1A/1B/1C/1D/1E)

CIRCUIT NO.	PART NO.	DESCRIPTION
IC		
Q253	222840661	4066B
Transistors		
Q251, Q252	2215864 or	KTC3199-GR or
	2213284	2SC1740S-R
Diode		
D251	223260 or	1N4148 or
	223163	1SS133
Capacitors		
C251, C252	354721019	100 μ F, 6.3V, Elect.
C255, C256	354724719	470 μ F, 6.3V, Elect.
C257	354721019	100 μ F, 6.3V, Elect.
C259	354741019	100 μ F, 16V, Elect.
Terminal		
P251	25045339 or	NPJ-4PDYE190 or
	25045539	NPJ-4PDYE363
Plug		
JL261b	25055625	NPLG-4P587

TERMINAL PC BOARD(NAETC-6241-1A/1B/1C/1D/1E)

CIRCUIT NO.	PART NO.	DESCRIPTION
Terminals		
P150i	25060271 or	NTM-2PDML202 or
	25060114	NTM-2PDML048
P805	25045537,	NPJ-4PDWR361,
	25045303 or	NPJ-4PDBL162 or
	25045460	NPJ-4PDBL281
Terminals		
P806	25045536,	NPJ-2PDBL360,
	25045298 or	NPJ-2PDBL157 or
	25045456	NPJ-2PDBL277
P807	25045535,	NPJ-1PDBL359,
	25045302 or	NPJ-1PDBL161 or
	25045459	NPJ-1PDBL280
Socket		
JL914b	25050281	NSCT-4P109
Plug		
JL622b	25055631	NPLG-10P593

HEADPHONE TERMINAL PC BOARD(NAETC-6240-1A/1B/1C/1D/1E)

CIRCUIT NO.	PART NO.	DESCRIPTION
P503	25045255 or	YKB26-5009 or
	25045540	HTJ-064-11D, Terminal

DOLBY CIRCUIT PC BOARD(NAAF-5894-4A/4B/4C)

CIRCUIT NO.	PART NO.	DESCRIPTION
ICs		
Q601, Q603	222502	NJM4558D-X
Q602	22241053	NJW1102AF
Q605	22240800	TC9164AN
Q651	22240995 or	NJU9702 or
	22240686	M65830P
Q671, Q672	222502	NJM4558D-X
Q673, Q674	22241054	M62429FP
Transistors		
Q652	2215163	2SD667A-C
Q675	2213631	RN1241-A
Q677, Q678	2213631	RN1241-A
Diodes		
D651	224470682	MTZJ6.8B
D652~D657	223260 or	1N4148 or
D659	223163	1SS133
Oscillator		
X651	3010217	CST2.04MC040
Capacitors		
C601, C602	354780229	2.2 μ F, 50V, Elect.
C605, C606	354781009	10 μ F, 50V, Elect.
C607~C610	374721044	0.1 μ F \pm 5%, 50V, Plastic
C611, C612	374726814	680pF \pm 5%, 50V, Plastic
C613, C614	354741009	10 μ F, 16V, Elect.
C616, C619	354742209	22 μ F, 16V, Elect.
C617	374724724	4700pF \pm 5%, 50V, Plastic
C618, C657	354744709	47 μ F, 16V, Elect.
C620~C622	354741009	10 μ F, 16V, Elect.
C623, C638	354781099	0.1 μ F, 50V, Elect.
C624, C663	354741009	10 μ F, 16V, Elect.
C625	354722219	220 μ F, 6.3V, Elect.
C627	374725614	560pF \pm 5%, 50V, Plastic
C628	374721024	1000pF \pm 5%, 50V, Plastic
C629, C656	374725624	5600pF \pm 5%, 50V, Plastic
C630	374724734	0.047 μ F \pm 5%, 50V, Plastic
C631	354786899	0.68 μ F, 50V, Elect.
C632, C633	354782299	0.22 μ F, 50V, Elect.
C634, C635	354780479	4.7 μ F, 50V, Elect.
C636, C637	354782299	0.22 μ F, 50V, Elect.
C639, C640	374724734	0.047 μ F \pm 5%, 50V, Plastic
C641, C642	354781099	0.1 μ F, 50V, Elect.
C643, C644	374722234	0.022 μ F \pm 5%, 50V, Plastic
C645	354781099	0.1 μ F, 50V, Elect.
C647~C649	354741009	10 μ F, 16V, Elect.
C650	354780479	4.7 μ F, 50V, Elect.
C651	374722224	2200pF \pm 5%, 50V, Plastic
C652, C653	374725614	560pF \pm 5%, 50V, Plastic
C654, C655	374721044	0.1 μ F \pm 5%, 50V, Plastic
C658, C659	374724734	0.047 μ F \pm 5%, 50V, Plastic
C660	354781009	10 μ F, 50V, Elect.
C661, C662	354721019	100 μ F, 6.3V, Elect.
C664	354741019	100 μ F, 16V, Elect.
C667, C668	354741009	10 μ F, 16V, Elect.
C669, C670	354780229	2.2 μ F, 50V, Elect.
C671~C673	354741009	10 μ F, 16V, Elect.
C674	354780229	2.2 μ F, 50V, Elect.
C676, C677	354741009	10 μ F, 16V, Elect.
C685, C686	354721019	100 μ F, 6.3V, Elect.
C687	354741009	10 μ F, 16V, Elect.
C689~C691	354741009	10 μ F, 16V, Elect.

CIRCUIT NO.	PART NO.	DESCRIPTION			
R696	5104392A	N16RFL50KA25F, Variable			
JL621a	25051087	NSCT-3P874			
JL622a	25051094	NSCT-10P881			
P612b	25051235	NSCT-10P1025			
P611b	25055885	NPLG-12P841			
REAR AMPLIFIER PC BOARD(NAAF-5895-4A/4B/4C)					
CIRCUIT NO.	PART NO.	DESCRIPTION			
Q801, Q802	2215116 or	2SC1775-F or			
Q809	2211732	2SC1845-F			
Q803~Q806	2215843 or	KTA1024-O or			
Q813, Q814	2211353	2SA949-O			
Q807, Q808	2215853 or	KTC3206-O or			
Q817, Q818	2211633	2SC2229-O			
Q810	2215116 or	2SC1775-F or			
Q827~Q830	2211732	2SC1845-F			
Q811, Q812	2215864 or	KTC3199-GR or			
Q815, Q816	2213284	2SC1740S-R			
Q819, Q820	2215163	2SD667A-C			
Q821, Q822	2215173	2SB647A-C			
Q823, Q824	2202923 or	* 2SC5196-O or			
	2202922	* 2SC5196-R			
Q825, Q826	2202913 or	* 2SA1939-O or			
	2202912	* 2SA1939-R			
D801, D802	22380260,	RL1N4003,			
	22380032	1SR139-100 or			
	22380035	GP104003E			
			R847, R848	4000131	RGC22-0.22 OHMK, Special
			R823~R826	443526804	68Ω ± 5%, 1/2W, Metal oxide
			R833, R834	443525604	56Ω ± 5%, 1/2W, Metal oxide
			R835, R836	443526804	68Ω ± 5%, 1/2W, Metal oxide
			R841, R842	443521014	100Ω ± 5%, 1/2W, Metal oxide
			R843~R846	453530224	2.2Ω ± 5%, 1/2W, Metal
			R855, R856	453630824	8.2Ω ± 5%, 1W, Metal
			R859, R860	453530224	2.2Ω ± 5%, 1/2W, Metal
			S961	25065286	NSS-22112 <W>
			P801	25060161 or	NTM-4PDML087 or
				25060273	NTM-4PDML204
			P961	25045439	NPJ-1PDBL263
			JL912b	25050271	NSCT-7P99
			JL621b	25055624	NPLG-3P586
			JL961b	25055625	NPLG-4P587
			JL711b	25055627	NPLG-6P589

NOTES: <D>:120V Model only
 <P>:European Model only
 <T>:Asian Model only
 <W>:Taiwanese Model only
 <A>:Australian Model only

ADJUSTMENT PROCEDURES

Preparation

1. Input

FM mono: 1kHz, 75kHz devi., 60dB/μV

FM stereo: 1kHz, 67.5kHz devi., 60dB/μV

Pilot signal 19kHz 7.5kHz devi.

AM: 400Hz, 30% mod.

2. Outputs

Connect the non-inductive type resistor of 8 ohms to the all speaker terminals unless otherwise noted.

1.IDLING CURRENT ADJUSTMENT

Before Idling adjustment, turn the trimming resistors R573, R574 and R1532 to counter clockwise.

Connect the DC voltmeter to sockets P511, P512 and P1511.

After turn POWER to ON, adjust the trimming resistors R573, R574 and R1532 so that the reading of voltmeter becomes 1.5±0.2mV.

After adjustment, attach the top cover.

Confirm the voltage of above points after five minutes.

When the voltage is less than 5mV, adjust the above resistors so that the voltage becomes 5.5±0.2mV.

When the voltage is 5mV to 7mV, adjust the above resistors so that the voltage becomes 5.7±0.2mV.

When the voltage is more than 7mV, adjust the above resistors so that the voltage becomes 5.9±0.2mV.

2.FM ADJUSTMENT

Item	Step	Connection of instrument	FM SG output	Stereo modulator output	Tuning frequency	Output indicator	Adjustment point	Adjust for	Remarks
FM IF/RF	1	Fig.1	99.0MHz 1kHz 75kHz devi. 65dB(60dB)	—	99.0MHz	DC voltmeter	L101	0±20mV	FM MUTE/MODE switch:ON/AUTO Repeat the steps 1 and 3 until no further adjustment is necessary.
	AC voltmeter					IFT on the front end	Maximum		
	Distortion analyzer					L102	Minimum		
Stereo Distortion		Fig.2	99.0MHz Ext. mod.65dB(60dB)	Channel L or R 1kHz	99.0MHz	Distortion analyzer	IFT on the front end	Minimum	FM MUTE/MODE switch:ON/AUTO Don't turn more than ± 180°
		Fig.2	99.0MHz Ext. mod.65dB(60dB)	Channel L or R 1kHz	99.0MHz	Oscilloscope	R150	Maximum separation	
Stereo Separation		Fig.1	99.0MHz	—	99.0MHz	Oscilloscope	R158	Signal output	

3.AM ADJUSTMENT

120V model





Step	AM SG output	Tuning Frequency	Output Indicator	Adjustment point	Adjust for
1		530kHz	Digital DC voltmeter	OSC coil on RF block L105	1.3±0.2V
2	600kHz 30% mod. 60dB/m	600kHz	AC voltmeter	RF coil on RF block L105	Maximum
3	990kHz 30% mod. 60dB/m	990kHz	AC voltmeter	L106	Maximum

Reference Specification
 FM tuned voltage:87.50MHz~108.00MHz
 More than 1.2V~Less than 10V
 AM tuned voltage:530kHz~1710kHz
 1.3±0.2~Less than 9.0V

230V and Worldwide models


Step	AM SG output	Tuning Frequency	Output Indicator	Adjustment point	Adjust for
1		522kHz or 531kHz	Digital DC voltmeter	OSC coil on RF block L105	1.3±0.2V
2	603kHz 30% mod. 60dB/m	603kHz	AC voltmeter	RF coil on RF block L105	Maximum
3	999kHz 30% mod. 60dB/m	999kHz	AC voltmeter	L106	Maximum

Reference Specification
 FM tuned voltage:87.50MHz~108.00MHz
 More than 1.2V~Less than 10V
 AM tuned voltage:522kHz~1611kHz
 1.3±0.2~Less than 9.0V
 (230V model)
 AM tuned voltage:531kHz~1602kHz
 1.3±0.2~Less than 9.0V
 (Worldwide model)




SCHEMATIC DIAGRAM

A B C D E F G H




BLOCK DIAGRAM



TA-01434 TA-01434

PACKING VIEW



REF. NO.	PART NO.	DESCRIPTION
1	29100034-1A	850*650,Styren bag
2	29053280	Carton box <S>
2	29053266	Carton box <D>
2	29053268	Carton box <P>
2	29053267	Carton box <W/T/A>
3	282301	Staple
4	29091763A	Pad ass'y
6	261504	Paper tape
7	29110071	PP tape
8	29362276	Label EAN <P/T/W/A>
8	29362294	Label EAN <S>
8	29362275	Label UPC <D>
	Accessory bag ass'y	
	232140	NMA-3057,AM loop antenna
	24140371	RC-371M,Remote control
	25055018	CV-K-1,Conversion plug <W>
	25065462	YAE21-0237,FM antenna adaptor <T/W/A>
	29100097-1A	350*250,Styren bag
	292111	FM antenna <D>
	292112	FM antenna <P/T/W/A>
	29342556	Instruction manual E
	29342557	Instruction manual U3FSI <P>
	29342558	Instruction manual U3GSWD <P>
	29342559	Instruction manual T <T/W>
	29358002K	Servie station list <D>
	29365019B	Warranty card <D>
	3010124	UM-4,Two batteries

NOTE: <D>:120V model only
 <P>:230V model only
 <W>:Taiwanese model only
 <T>:Asian model only
 <A>:Australian model only
 :Black model only
 <S>:Silver model only

ONKYO CORPORATION

International Sales Div. : 31 Sankyo-bld. 3-8-5, Asakusabashi, Taito-ku, TOKYO 111, JAPAN
TEL : 03-5820-5865 FAX : 03-5820-5869

ONKYO U.S.A. CORPORATION
200 Williams Drive, Ramsey, N.J. 07446, U.S.A.
TEL : 201-825-7950 FAX : 201-825-8150

ONKYO EUROPE ELECTRONICS GmbH
Industriestrasse 18-20, 82110 Germering, GERMANY
TEL : 089 84 93 20 FAX : 089 84 93 226

ONKYO FRANCE
Immeuble Le Diamant, Domaine Technologique de Saclay, 4 Rue Rene Razel, 91892 SACLAY, FRANCE
TEL : (1) 69 33 14 00 FAX : (1) 69 41 35 84