




OPTONICA

SERVICE MANUAL

RP-7100H
RP-7100HB



STEREO TURNTABLE

MODEL
RP-7100H
(Silver Panel)

RP-7100HB
(Brown Panel)

In the interests of user-safety the set should be restored to its original condition and only parts identical to those specified be used.

INDEX TO CONTENTS

SPECIFICATIONS	2
DESIGNATION OF PARTS	2
DISASSEMBLY	3
VOLTAGE SELECTION	3
TONEARM LIFTER	3
CARTRIDGE MOUNTING	4
DUST COVER MOUNTING	4
TRACKING FORCE ADJUSTMENT	5
ADJUSTMENT OF AUTOMATIC LEAD-IN	6
MECHANISM	
CLEANING THE STYLUS TIP	6
CIRCUIT DESCRIPTION	
SCHEMATIC DIAGRAM OF LOGIC CIRCUIT	7, 8
OUTLINE	9 ~ 11
BEHAVIORS OF LOGIC CIRCUIT	12
SIGNAL FLOW CHART	13, 14
BEHAVIORS OF CONTROL CIRCUIT	15 ~ 18
ALIGNMENT POINTS	19, 20

ADJUSTMENT	
STYLUS HEIGHT ADJUSTMENT	21
(LEAD-IN HEIGHT)	
AUTO RETURN ADJUSTMENT	21
SENSITIVITY ADJUSTMENT	21
CHECKING OF APLD SENSOR HEIGHT	22
QUARTS LOCK TIMING ADJUSTMENT	22
TONEARM RETURN DETECTOR ADJUSTMENT	22
DETECTED SENSITIVITY ADJUSTMENT	22
ADJUSTMENT OF MOTOR DRIVE CIRCUIT	23
PITCH FINE ADJUSTMENT	23
FREQUENCY ADJUSTMENT	23
TOP VIEW OF LOGICAL IC	24
EQUIVALENT OF INTEGRATED CIRCUIT	25, 26
SCHEMATIC DIAGRAM	27 ~ 30
WIRING SIDE OF P.W. BOARD	31 ~ 34
CABINET EXPLODED VIEW	35, 36
PARTS LIST	37 ~ 42
AC SUPPLY CORD WIRING CONNECTION	43

SHARP CORPORATION OSAKA, JAPAN

SPECIFICATIONS

Power source: AC 110/220/240V, 50/60 Hz
 Power consumption: 10W
 Semiconductors: 22-IC
 47-transistor
 33-diode
 2-hall elements
 1 quartz-crystal oscillator

Dimensions: Width: 480 mm (18-29/32")
 (with dust cover) Height: 108 mm (4-1/4")
 Depth: 384 mm (15-1/8")
 Weight: 9 kg (20 lbs)

TURNTABLE

Motor: Core-less DC servo mono-torque motor
 Speed stabilization: 160-pole frequency generator, PLL with quartz-crystal oscillator, sample hold phase detector.
 Drive system: Direct-drive

Speed: 33-1/3 and 45 rpm
 Speed control range: Within $\pm 4\%$
 Wow & Flutter: $\pm 0.045\%$ (DIN 45 507)
 Rumble: Better than 68 dB (DIN-B)
 Turntable platter: 30 cm (12 in.) aluminum die-cast with stroboscope marks.

ONEARM

Type: Statically balanced pipe arm with APLD sensor.
 Effective length: 210 mm (18-1/4")
 Overhang: 11 mm (7/16")
 Off-set angle: 19°
 Cartridge weight range: 4 to 12 grams

Specifications are subject to change without prior notice.

DESIGNATION OF PARTS




Figure 1

DISASSEMBLY

Disconnect all leads connected to the back of the unit.
Remove fourteen (14) screws retaining the bottom plate.




Figure 2

VOLTAGE SELECTION

Check the preset AC supply voltage before plugging the AC supply cord into an AC wall outlet. If the setting is different from your local supply voltage, the voltage selector (located on the base board, under the turntable platter) must be reset as follows:

Rotate the voltage selector switch with a screwdriver, so that your local voltage number can be seen in the window.

Note:

Since this unit uses DD motor, operation is regardless of whether the frequency of AC supply is 50 Hz or 60 Hz.




Figure 3




Figure 4

ONEARM LIFTER

When operating the turntable after it has been stored for long periods, tonearm may not move in initial action because of the property of oil.

In this case, move the tonearm lifter 2 to 3 times up and down with your fingers. The lifter will be able to function normally.




Figure 5

CARTRIDGE MOUNTING

A cartridge is not furnished with the unit.

Important Note:

- * Any cartridge of which the dimension "A" shown in figure 7 is greater than 19 mm, cannot be applied to this set.
 - * The weight of the cartridge should be 4 to 12 grams.
1. Before attempting to mount the cartridge read the instructions supplied by the cartridge manufacturer. The cartridge you have selected may require some special mounting hardware or need to be insulated from the headshell. The cartridge can be mounted to the headshell with the hardware supplied by the cartridge manufacturer or with the hardware included with the turntable.
 2. The headshell has been pre-wired to facilitate connection to the cartridge. Attach the wires to the cartridge by sliding the connector over the proper terminal on the cartridge.
 3. The cartridge must be positioned in the headshell so that there is a distance of 50 mm between the tip of the stylus and the rubber grommet at the plug end of the headshell. Without this adjustment the APLD won't function normally.




Figure 6




Figure 7

DUST COVER MOUNTING

Join the plate hinges and hinge brackets on the cabinet with a downward motion as indicated by the arrow in the illustration.




Figure 8

TRACKING FORCE ADJUSTMENT

1. Adjust the antiskating control to the "0" position (See Figure 9).
2. Move the tonearm to over the platter surface. The tonearm must be supported with your hand to prevent the stylus from hitting the motor board or the platter (See Figure 10).
3. Rotate the tracking force adjustment knob till perfect balance is achieved. When the tonearm is perfectly balanced it will keep its horizontal position when you remove your hand (See Figure 11).
4. Replace the tonearm on the rest with your hand (See Figure 12).
5. Rotate the tracking force gauge with your fingers till "0" graduation aligns with a mark on the counterweight (See Figure 13).
6. Consult the cartridge instructions to find the tracking force recommended by the cartridge manufacturer. Rotate the tracking force adjustment knob in the direction of the arrow as shown in the figure 14, till the desired force aligns to a mark on the counterweight.
7. Adjust the anti-skating control to the same number as the tracking force that you have chosen in the above step 6 (See Figure 15).




Figure 9




Figure 10




Figure 11




Figure 12




Figure 13




Figure 14




Figure 15

ADJUSTMENT OF AUTOMATIC LEAD-IN MECHANISM

If the stylus, APLD sensor and tonearm bearing are not positionally arranged at the same center line, this results in both the APLD and autoplay-start mechanism working abnormally. This is proved by the fact that the APLD cannot search for the desired program's spaces in a normal way. In this case, take the following procedures to solve the problem.

1. Keep two discs in hand, a 30 cm (12") and 17 cm (7") one.
2. After adjusting the tracking force of cartridge, plug the AC supply cord into a wall outlet, then set the power switch to "on" position.
3. Place a 30 cm (12") disc on the rubber mat of turntable.
4. Press the "play" button. The tonearm will leave the rest and descend on the disc.
5. If the stylus descends outside the disc periphery, rotate the screw (as shown in the illustration) anticlockwise. While, if it descends inside the starting groove of the disc, rotate the screw clockwise.
6. Next, place a 17 cm (7") disc, instead of the 30 cm (12") one, on the platter and do the same as above.




Figure 16

CLEANING THE STYLUS TIP

To clean the stylus use a soft brush (not supplied). Wipe it in the direction of arrow shown in the illustration. Never touch the stylus with your fingers, or the stylus tip may break.




Figure 17

CIRCUIT DESCRIPTION




Figure 18 SCHEMATIC DIAGRAM OF LOGIC CIRCUIT

■ OUTLINE




Figure 19 BLOCK DIAGRAM OF LOGIC CIRCUIT

1 REPEAT GATE/MEMORY CIRCUIT

Circuit which memorizes the unit is put in the repeat mode, and sends forth the signal to the repeat selector circuit. The signal is also used to turn the repeat indicator LED (LED2) on.

2 PLAY GATE/MEMORY CIRCUIT

Does not permit the unit to accept the play signal except when the tonearm is settled on its rest. This circuit also memorizes the unit is put in the play mode, and feeds the signal to the lead-in/return selector circuit. The signal is also used to turn the play indicator LED (LED1) on.

3 CUE GATE/MEMORY CIRCUIT

Does not let the unit accept the cue signal except while the cuing operation is performed. This circuit also memorizes the unit is put in the cue mode, and sends the signal to the lead-in/return selector circuit. The signal is also used to turn the cue indicator LED (LED3) on.

4 REPEAT SELECTOR CIRCUIT

Circuit which leads in the tonearm when it returns to its tonearm rest.

5 LEAD-IN/RETURN SELECTOR CIRCUIT

Selects which mode the unit is to be put in, among the lead-in, return and cue modes.

6 PLAY TIMER CIRCUIT

In the case of leading in, when the tonearm is lifted up there is required an interval during which the sub motor changes its rotational direction from the normal to the reverse; for that reason, this circuit works to delay an attraction of the solenoid by 90msec.

7 CUT TIMER CIRCUIT

When the tonearm returns to its tonearmrest, this circuit delays putting in the solenoid in action by 0.9 sec, even if the rest switch (SW15) is open (off).

8 POWER-FAILURE-TIME PLAY INDICATOR CIRCUIT

Turns the play indicator LED (LED1) on when power failes or temporarily becomes off during playing.

9 PLAY IDENTIFY CIRCUIT

Identifies the unit is playing.

10 TONEARM REST IDENTIFY CIRCUIT

Identifies the tonearm is on its tonearm rest. The circuit also generates the signal for putting the play and repeat indicators off when the tonearm is manually put back to its tonearmrest.

11 SOLENOID DRIVE CIRCUIT

Drives the solenoid in response to the solenoid actuating signal.

12 SUB MOTOR MEMORY CIRCUIT

Memorizes the motor actuating signal specifying the normal or reverse direction rotation, and keeps it till the normal or reverse rotation stop signal is received.

13 SUB MOTOR DRIVE CIRCUIT

Drives the motor.

14 UP SIGNAL GENERATOR CIRCUIT

Circuit which generates the up signal of tonearm rest.

15 DOWN-RESET SIGNAL GENERATOR CIRCUIT

Comprises the following circuits:

- (1) Circuit which generates the up and reset signals.
- (2) Rest switch (SW15) chattering prevention circuit and DD motor on/off circuit.
- (3) Circuit which generates the down and reset signals, motor when the tonearm is on its rest; and it generates the signal which actuates the DD motor when the tonearm leaves its rest.

16 APLD CIRCUIT

Puts the APLD (Auto Program Locate Device) in action.

17 GROOVE SPACE DETECTOR CIRCUIT

Detects a program void groove between programs.

18 CUT GATE/MEMORY CIRCUIT

Let the unit accept the motor actuating signal the normal or tonearm is settled on it rest.

This circuit also memorizes the unit is put in the cut mode, and sends the signal to the lead-in/return selector circuit.

19 SOLENOID MEMORY CIRCUIT

Memorizes the solenoid actuating signal and keep it till the solenoid stop signal received.

GROOVE SPACE DETECTOR CIRCUIT

GROOVE SPACE DETECTOR CIRCUIT

(1) Program-to-program space detector

By the difference in reflection factor of infrared rays between no-sound-groove and sound-groove, this detector detects spaces between programs; when the sensor arm reaches a no-sound-groove the collector voltage of the APLD SENSOR Q304 becomes as shown by the waveform (A). The longer the no-sound-groove is, the wider this waveform width becomes.

(2) Output amplifier circuit

The waveform (A) is here amplified in terms of A.C. so that the waveform (B) is obtained.

(3) Waveform shaping circuit

Shapes the waveform (B) into a square wave; the result is as shown by the waveform (C).

(4) Groove pulse generator circuit

Differentiates (D), the waveform (C) once, and generates the program-to-program pulse with constant width. The pulse takes on a waveform as shown by (E).




Figure 20




Figure 21




Figure 22 TIME CHART




Figure 23 TIME MODE CHART

BEHAVIORS OF LOGIC CIRCUIT (See Figure 24)

- ① When the play start button is depressed with the power switch SW12 set at "on", the play indicator LED (LED1) lights up, and the tonearm moves away its rest, then it ascends. --- at the time, the sub-motor is rotating in clockwise direction. When the tonearm reaches its "up" position thoroughly, the sub motor now changes its rotating direction: say, it rotates in counterclockwise direction to get action of the solenoid, so that the tonearm will slide towards the surface of a record.
A signal flow corresponding to the abovementioned is revealed in Section ① of the separate Signal Flow Chart. In Section ① of the Chart, the non-shaded zone shows a signal flow up to the process where the tonearm "up" motion stops: while the shaded zone up to the process where the tonearm begins to slide towards the record surface.
In the following descriptions ② thru ⑩, it is preferred for you to refer to this Chart now and then for better understanding.
- ② As the tonearm slides towards the record surface, the APLD sensor Q304 finds out the 1st groove of a record (or the pre-designated groove in the case of APLD operation), and with this, the sub motor changes the rotation from counterclockwise to clockwise direction and simultaneously the solenoid stops to function. As a result, the tonearm begins to descend onto the record, the sub motor stops to rotate, and the unit gets in play mode. The abovementioned is illustrated in Section ② of the Chart. The non-shaded zone shows a signal flow up to the process where the solenoid stops to function while the shaded zone, the process thereafter.
The term "APLD" in the Chart means the process where the unit is under APLD operation.
- ③ When the cueing control button is pushed during play mode, signals are caused, as shown in the non-shaded zone in Section ③ of the Chart, so as to have the cue indicator LED (LED3) light up and also to let the sub motor change the rotation from counterclockwise to clockwise direction --- with this, the tonearm comes off the record surface and it will ascend to the full extent. Next, signals are caused as shown in the shaded zone of the Chart, to stop the rotation of the sub motor eventually.
- ④ If the cueing control button is pushed once again, signals are caused as shown in the non-shaded zone in Section ④ of the Chart, to have the sub motor rotate in clockwise direction, then the tonearm will thus descend onto the record surface. Next, signals are caused as shown in the shaded zone of the Chart, to stop the rotation of the sub motor with the cue indicator LED (LED3) going off.
- ⑤ When a play is finished (say, the tonearm reaches the end groove of record), or when the cut-out button is pushed during play mode, signals are caused as shown in the non-shaded zone in Section ⑤ of the Chart, resulting in that: the play indicator LED (LED1) is put off; the sub motor rotates in clockwise direction; the tonearm comes off the record surface and ascends. Next, signals are caused as shown in the shaded zone of the Chart, so the solenoid functions and the tonearm comes back to its rest.
- ⑥ The moment the tonearm reaches its rest, signals are caused as shown in the non-shaded zone in Section ⑥ of the Chart, so the solenoid stops to function and the tonearm enters the inside of its rest. Next, signals are caused as shown in the shaded zone, to stop the rotation of the sub motor and to reset the memory (of play mode).
- ⑦ If the cueing control button is pushed when the tonearm is inside its rest, the tonearm comes off its rest and ascends. In this state, if the cut-out button is further pushed, signal are caused as shown in the non-shaded zone in Section ⑦ of the Chart, so the sub motor rotates in clockwise direction to have the tonearm again descend onto its rest. Thereafter, signals are caused as shown in the shaded zone of the Chart, resulting in that the sub motor stops to rotate and the memory (of play mode) is reset.
- ⑧ If the play start button is pushed when the tonearm is inside its rest, the play start LED lights up, and the tonearm comes off its rest and ascend while moving towards the record surface. Under this state, if the cut-out button is further pushed, signals are caused as shown in the non-shaded zone in Section ⑧ of the Chart, so the sub motor changes the rotation from counterclockwise to clockwise direction, the play start LED is put off and the tonearm comes back to its rest. Thereafter, signals are caused as shown in the shaded zone of the Chart, resulting in that the solenoid stops to function, the tonearm enters the inside of its rest and the sub motor stops to rotate.
- ⑨ Pushing the repeat play button will enable the unit to perform auto-return operation of the tonearm. Here is shown what the auto-return operation is referring to Section ⑨ of the Chart.
If the repeat play button is pushed, signals are caused as shown in the non-shaded zone in Section ⑨ of the Chart, so the repeat indicator LED (LED2) lights up and the repeat signal is memorized in the unit: with this, it is in play mode that when the tonearm reaches the end groove of record, it, in turn, comes back automatically to its rest. Thereafter, signals are caused as shown in the shaded zone of the Chart, resulting in that the sub motor changes the rotation from clockwise to counterclockwise direction and the unit again starts play from the beginning.
- ⑩ If any one of the APLD number buttons (1 to 7) is pushed during play mode, signals are caused as shown in Section ⑩ of the Chart, so the sub motor rotates in clockwise direction, and the tonearm comes off the record surface and ascends. Thereafter, signals are caused as shown in the shaded zone and as a result, the sub motor changes the rotation from clockwise to counterclockwise direction and the solenoid functions. With the solenoid operation, the tonearm shifts above a record to find out a program-to-program space (groove) of it --- now, the sub motor keeps the counterclockwise rotation. Next with such groove detected, signals are caused as shown in the non shaded zone in Section ⑪ of the Chart, resulting in that the sub motor changes the rotation from counterclockwise to clockwise direction, the solenoid stops to function and the tonearm finally descends onto the detected groove. Thereafter, signals are caused in the shaded zone of the Chart, so the sub motor stops to rotate and the unit starts to play.

SIGNAL FLOW CHART



Figure 24

■ BEHAVIORS OF CONTROL CIRCUIT

The control circuit consists of a frequency generator servo circuit and sync circuit; the frequency generator servo circuit produces the signal according the speeds of the turntable which rotates coaxially with the motor.

and the sync circuit provides a phase control with a quartz oscillator signal as a reference. Described below are details of each part with the block diagram referred.




Figure 25 BLACK DIAGRAM

(1) Frequency generator, amplifier and flip-flop circuit

The frequency generator comprises a 160-pole magnet, a multigap head having 80-pair-pole teeth and coils. The frequency generator produces the 44.44 Hz sine-wave signal when playing the LP (33-1/3 rpm) record, and the 60 Hz sine-wave signal in the case of the EP

(45 rpm) record; the signal is amplified by the operational amplifier IC1 (1/2) and the 24 V peak-to-peak waveform (A) is obtained; then the waveform (A) is sent to the flip-flop circuit so that the rectangular waveform of 50% duty cycle is obtained.




Figure 26

(2) Operation control timing generator circuit and F/V sample hold circuit




Figure 27 BLACK DIAGRAM OF PLL IC (IC3)

The timing generator circuit is actuated by a pulse gained by dividing the quartz oscillator frequency to quarter.

When the starting part of the frequency generator's (FG) flip-flop reaction output enters the (FV) sample hold circuit, it is held by means of the sample pulse of the timing generator circuit so that the hold output voltage (FV) is obtained.

Thereafter, the reset pulse (FR) from the timing generator circuit discharges the load from C1, and the saw tooth wave (FVS) is obtained.




Figure 28 SIGNAL FLOW CHART

(3) Quartz oscillator and 10-bit program counter

This is a C-MOS inverter oscillator and the oscillation frequency can be adjusted by using the trimmer capacitor VC1 which is connected in parallel with the load of the quartz.

Quartz is of 9.3312 MHz type.

The programming is so designed that the frequency is divided by 972 for both LP and EP records to be played.




Figure 29 FREQUENCY DIVIDER

(4) Phase comparator circuit (P/D sample hold)

By the strobo signal output pulse, this circuit generates the saw tooth wave.

Besides, the circuit is appended with a bootstrap circuit so that the resultant saw tooth wave will have an excellent linearity.

This saw tooth wave is sample-hold by the flip-flop (FG) inversion of frequency generator.

Moreover, the phase comparator circuit is designed to be kept off by a switch when the quartz lock is off.




Figure 30 PHASE COMPARATOR

(5) Strobo signal output circuit

At pin (12) of IC3 this circuit, the output from the frequency divider circuit is more divided by 27 in the case of the LP record, and by 20 in the case of the EP one; then it is divided further by 2. And the reset pulse generator takes a timing pulse out of it to create a strobo signal.

- This timing pulse is also used as a reference signal for the P/D sample hold circuit.

(6) Reference voltage circuit (Voltage comparator)

Circuit which sets rpm of the DD motor; the constant voltage for it is obtained by making the output of the constant voltage circuit subject to a resistance-type voltage division.

This circuit compares the added output of the phase comparator and (FV) sample hold circuit with the reference voltage.

(7) Reversing rotation detector circuit (FET voltage switch)(See Figure 50)

When the output from the voltage comparator becomes below 0 V (in the case of reversing rotation), the transistor at the lower side of this circuit is turned off.

At that time, the voltage at the source-to-gate junction of the FET (Q3) becomes lower than the pinch-off voltage, and the resistance at its drain-to-source junction becomes higher so that the signal stops being fed to the Hall element (HE). Until the capacitor in the gate is charged up, the

voltage at the source-to-gate junction is higher than the pinch-off voltage and the reversing rotation brake is therefore applied.

The FET voltage switch puts the FET in conduction or cutoff by means of the motor start or stop signal. It also puts the FET in conduction or cutoff by means of the signal from the reversing rotation detector circuit (in the case of reverse rotation of the motor).




Figure 31 DD MOTOR DRIVE CIRCUIT

(8) DD motor drive circuit (See Figure 31)

This circuit detects a position of the rotor magnet by means of the Hall element (HE) and determines an order of the currents to feed to the two-phase drive coil. Besides, the voltage applied to the Hall element is controlled by the servo phase control circuit; the output voltage from the Hall element is varied according to variation of the rotation phase; then that output voltage is amplified by the operational amplifier IC2 to feed the current into the drive coil.

(9) Rectifier circuit (Constant voltage circuit)

This circuit rectifies the AC input by 4 diodes D11 ~ D14. The voltage by the zener diode ZD1 is 5.6 V; the 5.6 V constant voltage is taken out by the emitter-follower type transistor Q14.

The +12 V voltage is stabilized by the way that: the voltage subjected to a voltage division by the R50, R51 and VR4 is compared with the reference voltage provided by the ZD1, by means of the Q15.

When the +12 V voltage is thus stabilized, base current of the control transistor is governed by the transistor Q18 with the aid of voltage division by R54, R55 and R56 so that -12 V voltage is also stabilized.

The 12 V voltage can be adjusted externally by the variable resistor VR4.

- ① Allowable range for entry of the APLD Button at the control section.
- ② Except when the motor rotates in the normal direction.
- ③ Only during the time of playing.

(10) Tonearm moving speed detector circuit

When the tonearm comes near the end groove of the record, the shutter installed beneath the arm enters between the LED and the photo transistor so that the voltage at the collector of the photo-transistor varies as shown by (A) in the figure. And the voltage (A) runs through C301 and takes on an output waveform as shown by (B). This voltage increases when the tonearm moving speed becomes faster.

Voltage comparator

Applies the reference voltage (C) to pin ② of IC301 (the operational amplifier), and the voltage (B) to pin ③

Return pulse generator

Divides the output of IC301 by R308 and R303; and the divided output becomes the output pulse (E).

Reference voltage switch

Since the required output voltage (C) is different between 33 rpm and 45 rpm records, the reference voltage is changed by this switch; in the case of 33 rpm, the transistor Q301 is ON to make VR302 and R315 a parallel connection so that the voltage (C) becomes low.

(11) Strobe light-up circuit

To pin ⑬ of IC3, the 44.44 Hz pulse is fed when playing the LP record, and the 60 Hz pulse when playing the EP record; and this circuit turns on the transistor Q104 by means of the abovementioned pulses to trigger the monostable multivibrator. Q102 of this monostable multivibrator is in conduction and Q103 of it in cut-off in the stable state; but when the trigger pulse is fed into it, Q102 is turned off and Q103, on to light up the LED just during a period which is determined by R104 and C105.




Figure 32 RECTIFIER CIRCUIT




Figure 33 TIME CHART




Figure 34 STROBO LIGHT-UP CIRCUIT

ALIGNMENT POINTS




Figure 35

ADJUSTMENT

STYLUS HEIGHT ADJUSTMENT (LEAD-IN HEIGHT)

1. Put the power supply cord of the unit into a wall outlet; Set the power switch in "on" position; then press the cueing control button to send the tonearm up.
2. Manually hold the headshell grip; bring it over the record; then put the tonearm onto the tonearm lifter.
3. Turn the adjustment screw of the tonearm lifter using a screwdriver having a form as shown in the figure in order to adjust the stylus height.




Figure 36

AUTO RETURN ADJUSTMENT

1. Set the speed selector switch to "33 rpm" position.
2. Play the test record (SSR-4001), and adjustment screw so that the return count becomes 14 ± 1 .
3. Change the selector switch to "45 rpm" position, and make sure of the proper function.




Figure 37

SENSITIVITY ADJUSTMENT

1. Put the test record (TOSHIBA LF1003 or equivalent) on the turntable.
2. Set the power switch to "on" position.
3. Lift up the tonearm by pressing the Cueing control button.
4. Set the power switch to "off" position.
5. Move the headshell on the lead out groove of the test record by finger.
6. In this condition, unplug the connector socket CNS208 from the connector plug CNP208 mounted on the logic P.W.Board.
7. Connect the DC VTVM to the pin terminals of the connector plug CPN208 [Pin 5 (positive), Pin 4 (negative)], and adjust the variable resistor VR201 so that the VTVM reads 30 mV (30 ± 2 mV).
8. Next, set the tonearm on the tonearm rest.
9. Change the connection of the DC VTVM to the pin terminals of the connector plug CPN208 [Pin 2 (positive), Pin 3 (negative)], and adjust the variable resistor VR202 so that the DC VTVM reads 0.2V (0.2 ± 0.01 V).




Figure 38

CHECKING OF THE APLD SENSOR HEIGHT

Check the height and horizontal of the APLD sensor against the record surface on the turntable.

1. Set the power switch to "on", press the cueing control button, move the headshell over the record, and set the power switch to "off".
2. Make sure the height of sensor bottom from the record surface to be within 4.5 ± 1 mm, and at the same time to be parallel with record surface.
3. If, not correct, loosen the two screws fixing the sensor arm pipe at it's root, and modify the height and horizontal of the sensor by rotating the sensor arm pipe. Never forget the screws fixing.




Figure 39

QUARTZ LOCK TIMING ADJUSTMENT

1. Connect one end of a dual-beam synchroscope, on the control PWB, between pin 33 (GND) and pin 14 and another between pin 33 (GND) and pin 16.
2. Setting the speed selector at "33 rpm" position, adjust the variable resistor VR5 so that strobo signal pulse and frequency generator's signal pulse will be shown in Figure 40.
3. Next with the speed selector set at "45 rpm" position, further adjust the variable resistor VR6 so that strobo signal pulse and frequency generator's signal pulse will be shown in Figure 41.




Figure 40

TOEARM RETURN DETECTOR ADJUSTMENT

1. Put the tonearm onto its tonearm rest.
2. Connect a VTVM between TP1-14 and TP1-13 (GND).
3. Adjust the variable resistor VR301 so that the VTVM reads 0.2 V.




Figure 41

DETECTED SENSITIVITY ADJUSTMENT

1. Put the tonearm onto its tonearm rest.
2. Set the speed selector to "33 rpm" position.
3. Connect a VTVM between TP1-11 and TP1-13 (GND).
4. Adjust the variable resistor VR302 so that the VTVM reads 0.4 V.
5. Set the speed selector to "45 rpm" position, and make sure the VTVM shows 0.44 V.

ADJUSTMENT OF MOTOR DRIVE ADJUSTMENT

1. Connect one end of a dual-beam synchroscope, on the control PWB, between pin (13) (GND) and pin (8) and another between pin (13) (GND) and pin (7).
2. Turn the variable resistors VR2 and VR3 to generate two waveforms and adjust so that these two will have symmetry verticalit, as shown in Figure 42.
3. Adjust the variable resistor VR1 so that the two waveforms will be the same in their peaks.




Figure 42

PITCH FINE ADJUSTMENT

1. Set the pitch adjust controls VR33 and VR45 to their respective mechanical center position.
2. Setting the speed selector at "33 rpm" position, adjust the variable resistor VR32 so that stripe patterns of the

stroboscope will be motionless.

3. Next with the speed selector set at "45 rpm" position, further adjust the variable resistor VR44 so that stripe patterns of the stroboscope will be motionless.




Figure 43

FREQUENCY ADJUSTMENT

1. Connect a frequency counter between pin (33) (GND) and pin (14), respectively of the control PWB.
2. Adjust the variable capacitor VC1 so that the frequency counter will read 44.44 Hz with the speed selector set at "33 rpm" position.
3. Next with the speed selector set at "45 rpm" position, see that the frequency counter will indicate 60.00 Hz.











Figure 44 TOP VIEW OF LOGICAL IC




Figure 45 EQUIVALENT OF INTEGRATED CIRCUIT (IC201)




Figure 46 EQUIVALENT OF INTEGRATED CIRCUIT (IC1, 2, 202)




Figure 47 EQUIVALENT OF INTEGRATED CIRCUIT (IC301)





Figure 48 BLOCK DIAGRAM OF INTEGRATED CIRCUIT (IC3)



-29-




Figure 52 WIRING SIDE OF P.W.BOARD




Figure 53 CABINET EXPLODED VIEW

REPLACEMENT PARTS LIST

"HOW TO ORDER REPLACEMENT PARTS"

To have your order filled promptly and correctly, please furnish the following informations.

1. MODEL NUMBER
2. REF. NO.
3. PART NO.
4. DESCRIPTION

REF. NO.	PART NO.	DESCRIPTION	CODE	REF. NO.	PART NO.	DESCRIPTION	CODE		
INTEGRATED CIRCUITS									
IC1	VHINJM4558D-1	Operation Amplifier	AH	Q6	91Z2SA733Q	Drive (2SA733Q, 2SA733P, 2SA844B, 2SA844C)	AE		
	91ZRC4558P	(NJM4558D, RC4558P, 91ZPC4558C, 91ZPC1458C)			91Z2SA733P				
	91ZPC4558C				91Z2SA844B				
	91ZPC1458C				91Z2SA844C				
IC2	VHINJM4558D-1	Operation Amplifier	AH	Q7	91Z2SC945P	Reverse Rotation Detector (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD		
	91ZRC4558P	(NJM4558D, RC4558P, 91ZPC4558C, 91ZPC1458C)			91Z2SC945K				
	91ZPC4558C				91Z2SC2308C				
	91ZPC1458C				91Z2SC2308B				
IC3	91ZSM6415A-4S	PLL IC (SM-6415A-4S)	AQ	Q8	91Z2SC945P	Reverse Rotation Detector (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD		
IC201	RH-IX1123AFZZ	Shift Register (M54832P)	AT		91Z2SA733Q				
IC202	VHINJM4558D-1	Operation Amplifier (NJM4558D)	AH		Q9	91Z2SA733P		Reverse Rotation Detector (2SA733Q, 2SA733P, 2SA844B, 2SA844C)	AE
						91Z2SA844B			
IC203	RH-IX1141AFZZ	3 AND (SN74LS11)	AE		91Z2SA844C				
IC204	RH-IX1138AFZZ	Hex Inverter (SN74LS04)	AE	Q10	91Z2SC945P	Reverse Rotation Detector (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD		
IC205	RH-IX1135AFZZ	4 NAND (SN74LS00)	AE		91Z2SC945K				
IC206	RH-IX1136AFZZ	4 NOR (SN74LS02)	AE		91Z2SC2308C				
IC207	RH-IX1134AFZZ	S-R Latches (SN74279)	AH		91Z2SC2308B				
IC208	RH-IX1135AFZZ	4 NAND (SN74LS00)	AE	Q11	91Z2SC945P	Driver (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD		
IC209	RH-IX1134AFZZ	S-R Latches (SN74279)	AH		91Z2SC945K				
IC210	RH-IX1141AFZZ	3 AND (SN74LS11)	AE		91Z2SC2308C				
IC211	RH-IX1137AFZZ	4 NAND (SN74LS03)	AE		91Z2SC2308B				
IC212	RH-IX1138AFZZ	Hex Inverter (SN74LS04)	AE	Q12	91Z2SC945P	Driver (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD		
IC213	RH-IX1135AFZZ	4 NAND (SN74LS00)	AE		91Z2SC945K				
IC214	RH-IX1137AFZZ	4 NAND (SN74LS03)	AE		91Z2SC2308C				
IC215	RH-IX1136AFZZ	4 NOR (SN74LS02)	AE		91Z2SC2308B				
IC216	RH-IX1141AFZZ	3 AND (SN74LS11)	AE	Q13	91Z2SC945P	Constant Voltage (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD		
IC218	RH-IX1139AFZZ	4 AND (SN74LS08)	AE		91Z2SC945K				
IC301	91ZPC741C	Operation Amplifier (PC741C)	AQ		Q13	91Z2SC2308C			
						91Z2SC2308B			
IC401	RH-IX1140AFZZ	3 NAND (SN74LS10)	AE	Q14	91Z2SC945P	Constant Voltage (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD		
					91Z2SC945K				
					91Z2SC2308C				
					91Z2SC2308B				
TRANSISTORS									
Q1	91Z2SC945P	Flip-Flop (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD	Q15	91Z2SC945P	Constant Voltage (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD		
	91Z2SC945K								
	91Z2SC2308C								
	91Z2SC2308B								
Q2	91Z2SC945P	Flip-Flop (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD	Q16	91Z2SC945P	Constant Voltage (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)	AD		
	91Z2SC945K								
	91Z2SC2308C								
	91Z2SC2308B								
Q3	91Z2SK68K	FET, Voltage Switching (2SK68K, 2SK68L)	AF	Q17	91Z2SC1419B	Constant Voltage (2SC1419B, 2SC1419C)	AG		
	91Z2SK68L								
	91Z2SC945P	Position Detect (2SC945P, 2SC945K, 2SC2308C, 2SC2308B)			Q18	91Z2SA733Q		Constant Voltage (2SA733Q, 2SA733P, 2SA844B, 2SA844C)	AE
	91Z2SC945K								
91Z2SC2308C									
91Z2SC2308B									
Q4	91Z2SC2308B		AE	Q19	91Z2SA733Q	Constant Voltage (2SA733Q, 2SA733P, 2SA844B, 2SA844C)	AE		
	91Z2SA733Q								
	91Z2SA733P								
	91Z2SA844B								
Q5	91Z2SA844B		AE	Q20	91Z2SA844C		AF		
	91Z2SA844C								
		91Z2SA755B			Constant Voltage (2SA755B, 2SA755C)				
		91Z2SA755C							

TRANSISTORS

PARTS LIST

REF. NO.	PART NO.	DESCRIPTION	CODE	REF. NO.	PART NO.	DESCRIPTION	CODE	
Q21	91Z2SC1162B	Motor Drive (2SC1162B,	AG	D9	91Z1S953	Starter (1S953, 1SS53)	AC	
	91Z2SC1162C	2SC1162C, 2SD794R,		D10	91Z1SS53	Reverse Detector (1S953,	AC	
	91Z2SD794R	2SD794Q)			91Z1S953	1SS53)		
	91Z2SD794Q				91Z1SS53			
Q22	91Z2SA715B	Motor Drive (2SA715B,	AG	D11	91ZW03B	Rectifier (W03B, W03C,	AE	
	91Z2SA715C	2SA715C, 2SB744R,			91ZW03C	F14A, F14C)		
	91Z2SB744R	2SB744Q)			91ZF14A			
	91Z2SB744Q				91ZF14C			
Q23	91Z2SC1162B	Motor Drive (2SC1162B,	AG	D12	91ZW03B	Rectifier (W03B, W03C,	AE	
	91Z2SC1162C	2SC1162C, 2SD794R,			91ZW03C	F14A, F14C)		
	91Z2SD794R	2SD794Q)			91ZF14A			
	91Z2SD794Q				91ZF14C			
Q24	91Z2SA715B	Motor Drive (2SA715B,	AG	D13	91ZW03B	Rectifier (W03B, W03C,	AE	
	91Z2SA715C	2SA715C, 2SB744R,			91ZW03C	F14A, F14C)		
	91Z2SB744R	2SB744Q)			91ZF14A			
	91Z2SB744Q				91ZF14C			
Q101	91Z2SD793	Regulator (2SD793, 2SC1847)	AG	D14	91ZW03B	Rectifier (W03B, W03C,	AE	
	91Z2SC1847		AD		91ZW03C	F14A, F14C)		
Q102	91Z2SC945	Flip-Flop (2SC945)	AD		91ZF14A			
Q103	91Z2SC945	Flip-Flop (2SC945)	AD		91ZF14C			
Q104	91Z2SC945	Switching (2SC945)	AD	D101	91ZRB-150	Rectifier (RB-150)	AG	
Q201	91Z2SC945AP	Switching (Play Indicator) (2SC945AP)	AD	D102	91Z1S953	Level Shift (1S953)	AC	
				D202	91Z1S2076	Protector (1S2076)	AC	
Q202	91Z2SC945AP	Flip-Flop (2SC945AP)	AD	D203	91Z1S2076	Timer (1S2076)	AC	
Q203	91Z2SC945AP	Flip-Flop (2SC945AP)	AD	D204	91Z10E1	Protector (10E1)	AC	
Q204	91Z2SC945AP	Timer (2SC945AP)	AD	D205	91Z1S2076	Protector (1S2076)	AC	
Q205	91Z2SC1213C	Solenoid Drive (2SC1213C)	AG	D206	91Z1S2076	Discharger (1S2076)	AC	
Q206	91Z2SA673C	Sub Motor Drive (2SA673C)	AG	D207	91Z1S2076	DD Motor Drive (1S2076)	AC	
Q207	91Z2SA673C	Sub Motor Drive (2SA673C)	AG	D210	91Z1S2076	Protector (1S2076)	AC	
Q208	91Z2SC1213C	Sub Motor Drive (2SC1213C)	AG	D211	91Z1S953	Protector (1S953)	AC	
Q209	91Z2SC1213C	Sub Motor Drive (2SC1213C)	AG	D301	91Z1S953	Level Shift (1S953)	AC	
Q210	91Z2SC945AP	Flip-Flop Reset (2SC945AP)	AD	D302	91Z1S953	Protector (1S953)	AC	
Q211	91Z2SA733P	D.D. Motor Drive (2SA733P)	AE	ZENER DIODES				
Q212	91Z2SC945AP	Switching (2SC945AP)	AD	ZD1	91ZRD5.6EB	Regulator (RD5.6EB)	AG	
Q213	91Z2SC945AP	Switching (2SC945AP)	AD	ZD101	91ZRD5.6EB	Regulator (RD5.6EB)	AG	
Q214	91Z2SC945AP	Switching (2SC945AP)	AD	ZD201	91ZWZ-090	Regulator (WZ-090)	AG	
Q215	91Z2SC945AP	Flip-Flop (2SC945AP)	AD	ZD202	91ZRD2.4F	Level Shift (RD2.4F)	AF	
Q216	91Z2SC945AP	Flip-Flop (2SC945AP)	AD	ZD301	91ZWZ-056	Regulator (WZ-056, RD5.6EB)	AG	
Q301	91Z2SC945	Speed Selector (2SC945,	AD	ZD302	91ZRD5.6EB		AG	
	91Z2SC2308	2SC2308)				91ZRD12E		Regulator (RD12E, HZ12L)
Q302	91Z2SC945	Speed Selector (2SC945,				91ZHZ12L		
	91Z2SC2308	2SC2308)		ZD303	91ZRD13EC	Regulator (RD13EC, WZ-140)	AG	
Q303	VHPPT-501A/-1	Photo Transistor (PT-501A)	AR		91ZWZ-140			
Q304	RH-PX1014AFZZ	APLD Sensor (GP-453)	AR	LED (Light Emitting Diode)				
Q401	91Z2SA733P	Switching (2SA733P)	AE	LED1	VHPGL-9NG12-1	Play Indicator (GL-9NG12)	AD	
DIODES				LED2	RH-PX1008AFZZ	Repeat Indicator (GL-9PR2)	AE	
D1	91Z1S953	Regulator (1S953, 1SS53)	AC	LED3	RH-PX1008AFZZ	Cue Indicator (GL-9PR2)	AE	
D2	91Z1SS53	Regulator (1S953, 1SS53)	AC	LED4	VHPGL-9NG12-1	APLD Number Indicator (GL-9NG12)	AD	
D3	91Z1S953	Starter (1S953, 1SS53)	AC	LED5	VHPGL-9NG12-1	APLD Number Indicator (GL-9NG12)	AD	
D4	91Z1S953	Reverse Detector (1S953, 1SS53)	AC	LED6	VHPGL-9NG12-1	APLD Number Indicator (GL-9NG12)	AD	
D5	91Z1S953	Reverse Detector (1S953, 1SS53)	AC	LED7	VHPGL-9NG12-1	APLD Number Indicator (GL-9NG12)	AD	
D6	91Z1S953	Reverse Detector (1S953, 1SS53)	AC	LED8	VHPGL-9NG12-1	APLD Number Indicator (GL-9NG12)	AD	
D7	91Z1S953	Starter (1S953, 1SS53)	AC	LED9	VHPGL-9NG12-1	APLD Number Indicator (GL-9NG12)	AD	
D8	91Z1S953	Reverse Detector (1S953, 1SS53)	AC					

PARTS LIST

REF. NO.	PART NO.	DESCRIPTION	CODE	REF. NO.	PART NO.	DESCRIPTION	CODE
LED10	VHPGL-9NG12-1	APLD Number Indicator (GL-9NG12)	AD	C15	VCEAAU1EW226Y	22MFD, 25V	AC
LED11	RH-PX1008AFZZ	Quartz Indicator (GL-9PR2)	AE	C16	VCEAAU1EW226Y	22MFD, 25V	AC
LED12	91ZEB-5505	Strobo (EB-5505)	AF	C17	VCEAAU1CW476Y	47MFD, 16V	AC
LED13	91ZEB-5505	Strobo (EB-5505)	AF	C18	VCEAAU1VW108Y	1000MFD, 35V	AG
LED14	91ZEB-5505	Strobo (EB-5505)	AF	C19	VCEAAU1VW108Y	1000MFD, 35V	AG
LED15	VHPGL5PR6//1	Return Sensor (GL-5PR6)	AH	C20	VCEAAU1EW106Y	10MFD, 25V	AB
				C103	VCEAAU1CW108Y	1000MFD, 16V	AE
				C104	VCEAAU1CW106Y	10MFD, 16V	AB
				C106	VCEAAU1AW476Y	47MFD, 10V	AB
				C203	VCEAAU1HW105A	1MFD, 50V, +75 -10%	AB
				C204	VCEAAU1HW105A	1MFD, 50V, +75 -10%	AB
				C207	VCEAAU1CW476Y	47MFD, 16V	AC
				C208	VCEAAU1HW225M	2.2MFD, 50V, ±20%	**
				C209	VCEAAU1HW105A	1MFD, 50V, +75 -10%	AB
				C211	VCEAAU1CW107Y	100MFD, 16V	AC
				C212	VCEAAU1HW105A	1MFD, 50V, +75 -10%	AB
				C213	VCEAAU1HW105A	1MFD, 50V, +75 -10%	AB
				C214	VCEAAU1CW106Y	10MFD, 16V	AB
				C220	VCEAAU1HW335M	3.3MFD, 50V, ±20%	AB
				C222	VCEAAU1HW225M	2.2MFD, 50V, ±20%	**
				C224	VCEAAU1CW106Y	10MFD, 16V	AB
				C225	VCEAAU1CW476Y	47MFD, 16V	AC
				C226	VCEAAU1HW105A	1MFD, 50V, +75 -10%	AB
				C227	VCEAAU1CW106Y	10MFD, 16V	AB
				C228	VCEAAU1CW106Y	10MFD, 16V	AB
				C229	VCEAAU1CW106Y	10MFD, 16V	AB
				C230	VCEAAU1CW106Y	10MFD, 16V	AB
				C231	VCEAAU1CW106Y	10MFD, 16V	AB
				C239	VCEAAU1HW105A	1MFD, 50V, +75 -10%	AB
				C269	VCEAAU1HW474M	47MFD, 50V, ±20%	**
				C301	VCEAAU1HW336Y	33MFD, 50V	AC
				C302	VCEAAU1HW105A	1MFD, 50V, +75 -10%	AB
				C303	VCEAAU1CW106Y	10MFD, 16V	AB
				C401	VCEAAU1HW105M	1MFD, 50V, ±20%	**
				CAPACITORS			
				(Unless otherwise specified capacitors are 50V, +80 -20%, Ceramic type.)			
				C2	VCQYKU1HM473K	.047MFD, 50V, ±10%, Mylar	AC
				C3	VCCSPU1HL300K	30PF, 50V, ±10%, Ceramic	AA
				C4	VCCSPU1HL9R0K	9PF, 50V, ±10%, Ceramic	**
				C5	VCQYKU1HM104K	.1MFD, 50V, ±10%, Mylar	AC
				C6	VCQYKU1HM332K	.0033MFD, 50V, ±10%, Mylar	AB
				C7	VCQYKU1HM332K	.0033MFD, 50V, ±10%, Mylar	AB
				C9	VCQYKU1HM104K	.1MFD, 50V, ±10%, Mylar	AC
				C10	VCQYKU1HM103K	.01MFD, 50V, ±10%, Mylar	AB
				C13	VCQYKU1HM104K	.1MFD, 50V, ±10%, Mylar	AC
				C14	VCQYKU1HM104K	.1MFD, 50V, ±10%, Mylar	AC
				C101	91ZPME271Y	.022MFD, 250V	AE
				C105	VCQYKU1HM104K	.1MFD, 50V, ±10%, Mylar	AC
				C201	VCQYKU1HM223K	.022MFD, 50V, ±10%, Mylar	AB
				C202	VCQYKU1HM223K	.022MFD, 50V, ±10%, Mylar	AB
				C205	VCQYKU1HM103K	.01MFD, 50V, ±10%, Mylar	AB
				C206	VCQYKU1HM223K	.022MFD, 50V, ±10%, Mylar	AB
				C210	VCQYKU1HM103K	.01MFD, 50V, ±10%, Mylar	AB
				C216	VCCSPU1HL103Z	.01MFD	**
				C217	VCQYKU1HM103K	.01MFD, 50V, ±10%, Mylar	AB
				C218	VCQYKU1HM473K	.047MFD, 50V, ±10%, Mylar	AC
				C219	VCCSPU1HL471Z	470PF	**
				C221	VCQYKU1HM103K	.01MFD, 50V, ±10%, Mylar	AB
				C223	VCQYKU1HM103K	.01MFD, 50V, ±10%, Mylar	AB
				C232	VCKZPU1HF223Z	.022MFD	AA
				C233	VCKZPU1HF223Z	.022MFD	AA

PARTS LIST

REF. NO.	PART NO.	DESCRIPTION	CODE	REF. NO.	PART NO.	DESCRIPTION	CODE
R242	VRD-SU2EE473J	47K ohm	AA	6	91Z897907	Brake Arm	AD
R243	VRD-SU2EE103J	10K ohm	AA	7	91Z871956	Rubber Mat	AQ
R244	VRD-SU2EE103J	10K ohm	AA	8	91Z896598-2	Eccentric Pin	AC
R245	VRD-SU2EE471J	470 ohm	AA	9	91Z897672	Drum, Join Motor	AH
R246	VRD-SU2EE103J	10K ohm	AA	10	91Z851698-1	Dust Cover	BF
R247	VRD-SU2EE103J	10K ohm	AA	11	91Z897673	Metal Plate, Drum	AE
R248	VRD-SU2EE151J	150 ohm	AA	12	91Z897667	Spring, Tray	AC
R250	VRD-SU2EE103J	10K ohm	AA	13	91Z871972	Hinge	AN
R251	VRD-SU2EE103J	10K ohm	AA	14	91Z897664	Gear	AE
R252	VRD-SU2EE102J	1K ohm	AA	15	91Z897876	Spring, Gear	AC
R254	VRD-SU2EE473J	47K ohm	AA	16	91Z897668	Washer, Stainless Steel	AC
R255	VRD-SU2EE121J	120 ohm	AA	17	91Z851671	Control Panel (RP-7100H)	AX
R256	VRD-SU2EE103J	10K ohm	AA	17	91Z851671-4	Control Panel (RP-7100HB)	**
R257	VRD-SU2EE103J	10K ohm	AA	18	91Z897666	Gear, Tonearm	AF
R258	VRD-SU2EE103J	10K ohm	AA	19	91Z897665	Gear, Tonearm	AD
R259	VRD-SU2EE222J	2.2K ohm	AA	21	91Z705259	Sub Motor	AW
R260	VRD-SU2EE332J	3.3K ohm	AA	22	91Z897813	Pulley, Motor	AH
R261	VRD-SU2EE563J	56K ohm	AA	24	QACCB0054AF09	AC Supply Cord (SUK)	**
R262	VRD-SU2EE563J	56K ohm	AA	24	QACCV0001AGZZ	AC Supply Cord (SEEG)	AP
R263	VRD-SU2EE332J	3.3K ohm	AA	24	QACCZ0053AF00	AC Supply Cord (EX)	AK
R264	VRD-SU2EE473J	47K ohm	AA	24	QACCZ0002TA0F	AC Supply Cord (EX)	AF
R266	VRD-SU2EE101J	100 ohm	AA	24	91Z897322	AC Supply Cord (SCA)	**
R267	VRD-SU2EE225J	2.2 Meg ohm	AA	26	LBSHC0004AGZZ	Bushing, AC Supply Cord (SEEG)	AB
R268	VRD-SU2EE473J	47K ohm	AA	26	LBSHC0003AFZZ	Bushing, AC Supply Cord (SCA-EX)	AA
R269	VRD-SU2EE103J	10K ohm	AA	26	LBSHC0002AFZZ	Bushing, AC Supply Cord (SUK)	AB
R271	VRD-SU2EE103J	10K ohm	AA	27	91Z897682	Rubber, Solenoid	AB
R272	VRD-SU2EE683J	68K ohm	AA	29	91Z871958	Bracket, Motor	AG
R273	VRD-SU2EE224J	220K ohm	AA	30	91Z897894	Shaft, Motor	AD
R274	VRD-SU2EE104J	100K ohm	AA	31	91Z897677	Pulley, Motor	AD
R275	VRD-SU2EE332J	3.3K ohm	AA	32	91Z897692	Belt, Motor	AD
R276	VRD-SU2EE222J	2.2K ohm	AA	33	91Z892227	Leg	AE
R277	VRD-SU2EE472J	4.7K ohm	AA	34	91Z891215	Washer, Leg	AB
R278	VRD-SU2EE472J	4.7K ohm	AA	35	91Z890432-3	Cushion, Leg	AB
R279	VRD-SU2EE223J	22K ohm	AA	36	91ZE-825187	Spring, Leg	AE
R280	VRD-ST2EE102J	10K ohm	AA	37	91Z890755	Wire Holder	AD
R281	VRD-ST2EE224J	220K ohm	AA	38	91Z871965	Cam, Arm lifter	AF
R301	VRD-SU2EY102J	1K ohm	AA	39	91Z897669	Gear (Double Type)	AF
R302	VRD-SU2EY102J	1K ohm	AA	40	91Z897671	Lever, Micro-Switch	AD
R303	VRD-SU2EE471J	470 ohm	AA	41	91Z898284	Spring, Solenoid Operation	AC
R305	VRD-SU2EY332J	3.3K ohm	AA	42	91Z872035	Lever	AX
R306	VRD-SU2EY393J	39K ohm	AA	43	91Z897814	Main Chassis	AD
R307	VRD-SU2EY103J	10K ohm	AA	44	91Z897663	Shaft, Solenoid Operation	AG
R308	VRD-SU2EY222J	2.2K ohm	AA	45	—	Lever, Solenoid Operation	—
R311	VRD-SU2EY333J	33K ohm	AA	46	91Z851670	P.W. Board, Auto Return (Board only not available)	BP
R312	VRS-PT3DB331J	330 ohm, 2W, ±5%, Oxide Film	AB	47	91Z897681	Tonearm Assembly	AC
R313	VRD-SU2EY102J	1K ohm	AA	48	—	Shield Plate, Main P.W. Board	—
R315	VRD-SU2EY222J	2.2K ohm	AA	50	91Z897744-1	P.W. Board, Logic (Board only not available)	AD
R316	VRD-SU2EY103J	10K ohm	AA	51	91Z847109	Mirror, Stroboscope	AV
R317	VRD-SU2EY122J	1.2K ohm	AA	52	91Z872039	Bottom Plate	AZ
R401	VRD-ST2EE103J	10K ohm	AA	53	91Z893037-3	Power Transformer	AD
R402	VRD-ST2EE223J	22K ohm	AA	53	91Z892624-3	Bracket, AC Supply Cord (SEEG-SUK)	AD
R403	VRD-ST2EE103J	10K ohm	AA	54	—	Bracket, AC Supply Cord (SCA-EX)	AD
R404	VRD-ST2EE103J	10K ohm	AA	55	91Z242020	Spacer, Power Transformer	—
R405	VRD-ST2EE273J	27K ohm	AA	56	91Z898146	Cushion, Power Transformer	**
MISCELLANEOUS				57	91Z897734	Screw, Power Transformer	**
1	91Z897689	Shield Plate	AD	58	91Z897683	Cushion, Dust Cover	AC
2	—	P.W. Board, Transport Ass'y (With Output Leads) (Board only not available)	—	58	91Z897683-2	Button (RP-7100H)	AG
3	91Z897691	Sensor Holder	**			Button (RP-7100HB)	**
4	91Z898142	Sub Chassis	AL				
5	91Z620049-1	Turntable	BF				

PARTS LIST

REF. NO.	PART NO.	DESCRIPTION	CODE	REF. NO.	PART NO.	DESCRIPTION	CODE
59	91Z897685	Bracket, Controls	AD	SW12	91Z872069	Switch, Power	AR
	JKNBM0297AFSA	Knob, Power Switch (RP-7100H)	AD	SW13	91Z894614	Switch, Tonearmrest Up	AK
60	JKNBM0297AFSB	Knob, Power Switch (RP-7100HB)	**	SW14	91Z894614	Switch, Tonearmrest Down	AK
				SW15	91Z871418	Switch, Rest	AH
61	91Z631758-6	DC Servo Mono-torque Motor (DD Motor)	BK	SW16	91Z872001	Switch, Speed Selector/Quarts-crystal PLL ON-OFF	AQ
		(With Control P.W. Board)		(A, B)			
62	—	P.W. Board, Power Ass'y (Board only not available)	—		91Z897904	Tonearm Lifter	AG
63	91Z847110-1	Cabinet	BD		91ZH-SHELL5100	Head Shell	AZ
64	91Z897841	Spacer, Controls Bracket	AC		91ZMW5100	Counter Weight	AX
	91Z892618-4	Knob, Pitch Controls (RP-7100H)	AL	CNS201	91Z897911	Socket, 9 pin	**
65	91Z892618-6	Knob, Pitch Controls (RP-7100HB)	**	CNS202	91Z897908	Socket, 4 pin	**
				CNS203	91Z897913	Socket, 2 pin	**
	91Z897684	Knob, Speed Selector/Quarts-crystal PLL (RP-7100H)	AG	CNS204	91Z897908	Socket, 4 pin	**
66	91Z897684-2	Knob, Speed Selector/Quarts-crystal PLL (RP-7100HB)	**	CNS205	91Z897912	Socket, 9 pin	**
67	—	P.W. Board, Switch Ass'y (Board only not available)	—	CNS206	91Z897915	Socket, 9 pin	**
68	—	P.W. Board, Stroboscope Ass'y (Board only not available)	—	CNS207	91Z897914	Socket, 3 pin	**
69	91Z898165	Reflect Plate	AD	CNS208	91Z895382	Socket, 6 pin	**
70	91Z898145	Frosted Plate	AD	CNS301	91Z897918	Socket, 9 pin	**
71	91ZE-825182	Spring, Leg	AC	CNS401	91Z898316	Socket, 6 pin	**
72	91Z897688-1	Transparent Plate	AD	CNP201	With in Logic P.W. B.Ass'y	Plug, 9 pin	—
73	91Z700749	Spacer, Sub Motor	AC	CNP202	With in Logic P.W. B.Ass'y	Plug, 4 pin	—
74	91ZE-288760	Cushion, Sub Motor	AC	CNP203	With in Logic P.W. B.Ass'y	Plug, 2 pin	—
	PSPAS0080AFSA	Spacer, Power Switch (RP-7100H)	AB	CNP204	With in Logic P.W. B.Ass'y	Plug, 4 pin	—
75	PSPAS0080AFSB	Spacer, Power Switch (RP-7100HB)	**	CNP205	With in Logic P.W. B.Ass'y	Plug, 9 pin	—
				CNP206	With in Logic P.W. B.Ass'y	Plug, 9 pin	—
76	91Z897675	Stopper, Motor Shaft	**	CNP207	With in Logic P.W. B.Ass'y	Plug, 3 pin	—
77	91Z897736	Spacer, Button (RP-7100H)	**	CNP208	With in Logic P.W. B.Ass'y	Plug, 5 pin	—
78	91Z897736-2	Spacer, Button (RP-7100HB)	**	CNP401	With in Logic P.W. B.Ass'y	Plug, 6 pin	—
79	91Z897735	Cover, LED	**	CNP301	91Z399253-7	Plug, 9 pin	**
	91Z897686	Transparent Plate, Stroboscope	**	TP1	91Z399253-1	Test Point, 4 pin	**
F1	With in Control P.W.B. Ass'y	Fuse, T 800mA	—	SO1	QSOCE0551AFZZ	Switch, Voltage Selector	AG
F2	With in Control P.W.B. Ass'y	Fuse, T 800mA	—	SO101, SO102	91Z894205-1	Output Leads	**
F101	With in Power P.W.B. Ass'y	Fuse, T 200mA	—	SOL201	91Z897896	Solenoid	AN
F102	With in Power P.W.B. Ass'y	Fuse, T 200mA	—		91Z897904	Tonearm Rest	AG
SW1, SW2, SW3, SW4, SW5, SW6, SW7, SW8, SW9, SW10, SW11	QSW-Z0051AFZZ	Switch, Play/Repeat Play/Cueing Control/Cut Out/APLD Number	AD				




AC supply cord	Bushing	Connection		Photograph of figure
		(L)	(N)	
QACCB0054AF09	LBSHC0002AGZZ	Brown	Blue	
QACCV0001AGZZ	LBSHC0004AGZZ	Brown	Blue	
QAC CZ0053AF00	LBSHC0003AGZZ	Black	Black	
QAC CZ0002TA0F	LBSHC0003AGZZ	Brown	Brown	
91Z897322	LBSHC0003AGZZ	Black	Black	

Figure 54 AC SUPPLY CORD WIRING CONNECTION