

Service Manual

Compact Disc Changer


SL-PD988

Simplified

COMPACT
disc
DIGITAL AUDIOMASH*
multi-stage noise shaping

Colour

(K) Black Type



Area

Suffix for Model No.	Area	Colour
(PP)	U.S.A and Canada	(K)

* MASH is a trademark of NTT.

Please file and use this Service Manual together with the Service Manual for Model No. SL-PD987 (P, PC) Order No. AD9501004C1

Note : This Simplified Service Manual is provided to indicate the main difference between the original Model No. SL-PD687 (P, PC) and the subsequent Model No. SL-PD688 (P, PC).

Change In Replacement Parts List

- Notes : * Mentioned in this parts list is the complete replacement parts list for Model No. **SL-PD988 (PP)** with reference to model no. SL-PD987 (PP).
 * Important safety notice:
 Components identified by mark have special characteristics important for safety.
 Furthermore, special parts which have purposes of fire-retardant (resistors), high-quality sound (capacitors), low noise (resistors), etc are used.
 When replacing any of these components, be sure to use only manufacturer's specified parts shown in the parts list .
 * [M] Indicates in the Remarks columns indicates parts supplied by **MESA**.

Ref No.	Part No.	Part Name & Description	Remarks	Ref No.	Part No.	Part Name & Description	Remarks	Ref No.	Part No.	Part Name & Description	Remarks
		CABINET AND CHASSIS		8	RFKPLPD667PA	TRAY MOTOR ASS'Y	[M]	14	RGT0019	ROTARY TRAY	[M]
				9.	RMN0254	LED HOLDER	[M]	15	RHW81001-1	WASHER	[M]
1	RKM0339-K1	TOP CABINET	[M]	10	RMN0255	SENSOR HOLDER	[M]	16	RMB0365	TRAY SPRING	[M]
2	SNE2129-3	SCREW	[M]	11	RMN0263	MOTOR HOLDER	[M]	17	RME0152-3	LOCK GEAR SPRING	[M]
3	XTBS3+8JFZ1	SCREW	[M]	12	REZ0648	14P FFC	[M]	18	RMS0123-1	RIVET	[M]
4	RDG0267	TRAY REDUCTION GEAR	[M]	13	RFKNLPD1000E	TRAY ASS'Y	[M]	19	XTB3+10G	SCREW	[M]
5	RDG0268	LOCK GEAR	[M]	13-1	RMF0182	TRAY FELT	[M]	20	XTWS3+10T	SCREW	[M]
6	RDG0269-3	OPEN/CLOSE GEAR	[M]	13-2	RMG0200	SHUTTER RUBBER	[M]	21	XWE3D13	WASHER	[M]
7	RDV0031	BELT	[M]	13-3	RMR0546-W	ROLLER	[M]	23	REE0635	23P FFC	[M]

WARNING

This service information is designed for experienced repair technicians only and is not designed for use by the general public. It does not contain warnings or cautions to advise non-technical individuals of potential dangers in attempting to service a product. Products powered by electricity should be serviced or repaired only by experienced professional technicians. Any attempt to service or repair the product or products dealt with in this service information by anyone else could result in serious injury or death.

Technics®

© 1997 Matsushita Electronics (S) Pte. Ltd.
 All rights reserved. Unauthorized copying and distribution is a violation of law.

Ref No.	Part No.	Part Name & Description	Remarks	Ref No.	Part No.	Part Name & Description	Remarks	Ref No.	Part No.	Part Name & Description	Remarks
24	REE0636-1	FFC WIRE	[M]	116-2	SNSD38	TRV MOTOR ASS'Y SCRE	[M]			DIODES	
25	REE0637-1	FFC WIRE	[M]	117	RME0109	FLOATING SPRING B	[M]	D11	RL1N4003N02	DIODE	[M]
26	RGR0246A-V	REAR PANEL	[M]	118	RME0142	FLOATING SPRING A	[M]	D12	RL1N4003N02	DIODE	[M]
27	RFKJLPD688PK	BOTTOM CHASSIS ASS'Y	[M]	119	RMR0698-K	TRY CHASSIS	[M]	D13	RL1N4003N02	DIODE	[M]
28	RMR0749-W	CABLE HOLDER	[M]	120	RMS0123-1	FIXED PIN B	[M]	D14	RL1N4003N02	DIODE	[M]
29	RMR0742-K	BASE GUIDE (L)	[M]	121	RMS0350	FIXED PIN A	[M]	D15	MTZJ9R1CTA	DIODE	[M]
30	RMR0743-K	BASE GUIDE (R)	[M]	123	RMX0094	TRAY GUIDE	[M]	D16	RL1N4003N02	DIODE	[M]
31	RMR0765-W1	TRANSFORMER BASE	[M]	124	XTN2+6G	PCB SCREW	[M]	D21	RL1N4003N02	DIODE	[M]
32	RHM245ZA	MAGNET	[M]					D22	RL1N4003N02	DIODE	[M]
33	RMR0334	FIXED PLATE	[M]			INTEGRATED CIRCUITS		D23	MTZJ8R2CTA	DIODE	[M]
34	RMR0744-W	CLAMP PLATE	[M]	IC11	LM2940T5M	IC, REGULATOR	[M]	D24	MTZJ8R2CTA	DIODE	[M]
35	RMR0624-W	CLAMPER	[M]	IC351	UPD6376GSE1	IC, D/A CONVERTER	[M]	D31	RL1N4003N02	DIODE	[M]
36	RMN0185	FL HOLDER	[M]	IC352	BA4558FDXE2	IC, OP AMP	[M]	D32	RL1N4003N02	DIODE	[M]
37	RFKGLPD988PK	FRONT PANEL ASS'Y	[M]	IC353	BU4052BCF-E2	IC, ANALOG SW	[M]	D33	MA4270MTA	DIODE	[M]
37-1	RGK0611C-K	FRONT ORNAMENT PLATE	[M]	IC401	UPD78044A180	IC, MICROCOMPUTER	[M]	D34	MTZJ9R1CTA	DIODE	[M]
38	RGU1043-K	MAIN BUTTON	[M]	IC501	BA6247N	IC, MOTOR DRIVER	[M]	D41	MTZJ6R2CTA	DIODE	[M]
39	RGU1019-K	10-KEY BUTTON	[M]	IC601	RCDHC-278N	IC, REMO-CON SENSOR	[M]	D42	1SS254TA	DIODE	[M]
40	RGU1015-K	POWER BUTTON	[M]	IC602	NJU3713D	IC, LED DRIVE	[M]	D43	1SS291TA	DIODE	[M]
41	RGU1017-K	SUB BUTTON	[M]	IC701	AN8837SBE1	IC, HEAD AMP	[M]	D51	1SS254TA	DIODE	[M]
42	RMG0200	SHUTTER RUBBER	[M]	IC702	MN662741RPA	IC, DIGITAL LSI	[M]	D52	1SS254TA	DIODE	[M]
43	XTBS26+8J	SCREW	[M]	IC703	AN8780NSBE2	IC, MOTOR DRIVE	[M]	D53	MTZJ5R1BTA	DIODE	[M]
44	XTB3+10JFZ	SCREW	[M]	IC801	BA4558FDXE2	IC, OP AMP	[M]	D54	1SS254TA	DIODE	[M]
45	XTB3+20J	SCREW	[M]					D401	1SS254TA	DIODE	[M]
46	XTB3+8JFZ	SCREW	[M]			TRANSISTORS		D402	1SS254TA	DIODE	[M]
47	RGL0098	PANEL LIGHT	[M]	Q11	BA1A4PTA	TRANSISTOR	[M]	D403	1SS254TA	DIODE	[M]
48	RGU0878-K	PITCH CONTROL BUTTON	[M]	Q12	BN1A4PTA	TRANSISTOR	[M]	D404	1SS254TA	DIODE	[M]
49	RGU1044-Q	DISC BUTTON	[M]	Q13	BN1A4PTA	TRANSISTOR	[M]	D405	1SS254TA	DIODE	[M]
50	RGW0043	PITCH CONTROL KNOB	[M]	Q15	2SD2037ETA	TRANSISTOR	[M]	D406	1SS254TA	DIODE	[M]
51	RMC0245	TR FIXTURE	[M]	Q21	2SC2785FETA	TRANSISTOR	[M]	D461	MTZJ6R8CTA	DIODE	[M]
				Q22	2SA1175FETA	TRANSISTOR	[M]	D462	MTZJ5R6BTA	DIODE	[M]
		TRAVERSE DECK		Q31	2SB1238Q	TRANSISTOR	[M]	D501	GL380	DIODE	[M]
101	RDG0270	SPEED REDUCTION GEAR	[M]	Q32	2SD1302STA	TRANSISTOR	[M]	D502	RSQGP1S53V	DIODE	[M]
102	RDG0271	DRIVE GEAR A	[M]	Q33	2SD1302STA	TRANSISTOR	[M]	D551	SG-206S	DIODE	[M]
103	RDG0272	DRIVE GEAR B	[M]	Q41	2SD1862QTV2	TRANSISTOR	[M]	D601	REK0033	DIODE	[M]
104	RDK0025	DRIVE CAM	[M]	Q42	2SD1862QTV2	TRANSISTOR	[M]	D671	LN013304P	DIODE	[M]
105	RDP0050	PULLEY GEAR	[M]	Q401	2SC2785FETA	TRANSISTOR	[M]	D801	1SS254TA	DIODE	[M]
106	RFKPLPD667PB	LOADING MOTOR ASS'Y	[M]	Q461	BA1A4ZTA	TRANSISTOR	[M]	D802	1SS254TA	DIODE	[M]
107	RHD26019	SCREW	[M]	Q462	BA1A4ZTA	TRANSISTOR	[M]	D852	1SS254TA	DIODE	[M]
108	RMG0268-K	BELT	[M]	Q501	PT381	TRANSISTOR	[M]				
109	RML0334	CHANGE LEVER	[M]	Q701	2SA1037AKSTX	TRANSISTOR	[M]			SWITCHES	
110	RMM0117	SLIDE PLATE 1	[M]	Q702	DTC114YKA146	TRANSISTOR	[M]	S551	RSH1A005	SW, OPEN/CLOSE	[M]
111	RMM0118	SLIDE PLATE 2	[M]	Q801	2SD1302STA	TRANSISTOR	[M]	S601	EVQ21405R	SW, AUTO CUE	[M]
112	RMR0746-W	STRENGTHENING PLATE	[M]	Q802	2SD1302STA	TRANSISTOR	[M]	S602	EVQ21405R	SW, SPIRAL	[M]
113	RFKNLPD667PB	MECHANISM BASE ASS'Y	[M]	Q851	BN1F4MTA	TRANSISTOR	[M]	S603	EVQ21405R	SW, RANDOM MODE	[M]
114	RXQ0346-1	SLIDER ASS'Y	[M]	Q852	BA1F4MTA	TRANSISTOR	[M]	S604	EVQ21405R	SW, REPEAT	[M]
115	XTB3+10JFZ	SCREW	[M]	Q853	BN1F4MTA	TRANSISTOR	[M]	S605	EVQ21405R	SW, ID SCAN	[M]
116	RAE0150Z	TRAVERSE DECK	[M]	Q854	BA1F4MTA	TRANSISTOR	[M]	S606	EVQ21405R	SW, EDIT GUIDE	[M]
116-1	SHGD113-1	FLOATING CUSHION	[M]					S607	EVQ21405R	SW, STOP	[M]

Ref No.	Part No.	Part Name & Description	Remarks	Ref No.	Part No.	Part Name & Description	Remarks	Ref No.	Part No.	Part Name & Description	Remarks
S608	EVQ21405R	SW, PAUSE	[M]	S672	RSR2A003-A	SW, PITCH CTRL +/-	[M]			OSCILLATORS	
S609	EVQ21405R	SW, PLAY	[M]	S701	RSH1A043-U	SW, REST	[M]	X401	RSXY4M23M01T	CRYSTAL RESONATOR	[M]
S610	EVQ21405R	SW, DISC 1	[M]					X701	RSXZ16M9M01T	CERAMIC OSC	[M]
S611	EVQ21405R	SW, DISC 2	[M]			CONNECTORS					
S612	EVQ21405R	SW, DISC 3	[M]	CN11	RJS1A1101T1	TAPING CONNECTOR	[M]			DISPLAY TUBE	
S613	EVQ21405R	SW, DISC 4	[M]	CN14	RJS1A1101T1	TAPING CONNECTOR	[M]	FL601	RSL0170-F	FL DISPLAY	[M]
S614	EVQ21405R	SW, DISC 5	[M]	CN16	RJS1A1101T1	TAPING CONNECTOR	[M]				
S615	EVQ21405R	SW, DISC SKIP	[M]	CN17	RJS1A1101T1	TAPING CONNECTOR	[M]			JACKS	
S616	EVQ21405R	SW, PROGRAM MODE	[M]	CN18	RJS1A1101T1	TAPING CONNECTOR	[M]	JK11	SJSD16-1	JK, AC INLET	[M] ⚠
S617	EVQ21405R	SW, R.SEARCH	[M]	CN19	RJS1A1101T1	TAPING CONNECTOR	[M]	JK801	RJH3201N	JK, RCA	[M]
S618	EVQ21405R	SW, F.SEARCH	[M]	CN20	RJS1A1101T1	TAPING CONNECTOR	[M]				
S619	EVQ21405R	SW, R.SKIP	[M]	CN21	RJS1A1101T1	TAPING CONNECTOR	[M]			FLAT CABLES	
S620	EVQ21405R	SW, F.SKIP	[M]	CN301	RJS1A9423	FFC CONNECTOR	[M]	FC502	RWJ4406087KK	6 PIN FLAT CABLE	[M]
S621	EVQ21405R	SW, OPEN/CLOSE	[M]	CN401	RJS1A9423	FFC CONNECTOR	[M]	FC503	RWJ4403102KK	3 PIN FLAT CABLE	[M]
S631	EVQ21405R	SW, POWER	[M]	CN402	RJS1A9423	FFC CONNECTOR	[M]				
S651	EVQ21405R	SW, NUMERIC 1	[M]	CN403	RJS1A6814-J	FF CONNECTOR	[M]			PACKING MATERIALS	
S652	EVQ21405R	SW, NUMERIC 2	[M]	CN404	RJS1A6606T1	TAPING CONNECTOR	[M]	P1	RPG3849	PACKING CASE	[M]
S653	EVQ21405R	SW, NUMERIC 3	[M]	CN501	RJS1A6714-Q	14 PIN CONNECTOR	[M]	P2	RPN0781	POLYFOAM	[M]
S654	EVQ21405R	SW, NUMERIC 4	[M]	CN551	RJS2A1506	6 PIN CONNECTOR	[M]	P4	RPF0139	BAG	[M]
S655	EVQ21405R	SW, NUMERIC 5	[M]	CN601	RJS1A6223-1	23P CONNECTOR	[M]	P5	RPF00005	MIRAMAT BAG	[M]
S656	EVQ21405R	SW, NUMERIC 6	[M]	CN602	RJS1A6223-1	23P CONNECTOR	[M]				
S657	EVQ21405R	SW, NUMERIC 7	[M]	CN603	RJP6G18ZA	CONNECTOR	[M]			ACCESSORIES	
S658	EVQ21405R	SW, NUMERIC 8	[M]	CN701	RJS2A6016	16 PIN FFC CONNECTOR	[M]	A1	RFKSPD988PPK	O/I BOOK ASS'Y	[M]
S659	EVQ21405R	SW, NUMERIC 9	[M]	CN702	RJS1A6723-1Q	23 PIN FFC CONNECTOR	[M]	A2	EUR644970	REMOTE TRANSMITTER	[M]
S660	EVQ21405R	SW, NUMERIC 10	[M]					A2-1	UR64EC1371	R/C BATTERY COVER	[M]
S661	EVQ21405R	SW, NUMERIC >10	[M]			POWER TRANSFORMER		A4	SJA172	AC CORD	[M] ⚠
S662	EVQ21405R	SW, NUMERIC 0	[M]	PT11	RTP1K4C019-X	POWER TRANSFORMER	[M] ⚠	A5	RJL2P004B08	STEREO CONNECTOR CAB	[M]
S671	EVQB005R	SW,PITCH CTRL OFF/ON	[M]								

Resistors & Capacitors

Ref No.	Part No.	Values & Remarks	Ref No.	Part No.	Values & Remarks	Ref No.	Part No.	Values & Remarks	Ref No.	Part No.	Values & Remarks
	RESISTORS		R311	ERDS2TJ471T	470 1/4W [M]	R411	ERDS2TJ472T	4.7K 1/4W [M]	R603	ERDS2TJ121T	120 1/4W [M]
			R351	ERDS2TJ272T	2.7K 1/4W [M]	R412	ERDS2TJ223T	22K 1/4W [M]	R604	ERDS2TJ121T	120 1/4W [M]
R11	ERDS2TJ151T	150 1/4W [M]	R352	ERDS2TJ272T	2.7K 1/4W [M]	R413	ERDS2TJ103T	10K 1/4W [M]	R605	ERDS2TJ121T	120 1/4W [M]
R12	ERDS2TJ151T	150 1/4W [M]	R353	ERDS2TJ152T	1.5K 1/4W [M]	R414	ERDS2TJ471T	470 1/4W [M]	R606	ERDS2TJ121T	120 1/4W [M]
R21	ERDS2TJ122T	1.2K 1/4W [M]	R354	ERDS2TJ152T	1.5K 1/4W [M]	R415	ERDS2TJ103T	10K 1/4W [M]	R608	ERDS2TJ122T	1.2K 1/4W [M]
R22	ERDS2TJ122T	1.2K 1/4W [M]	R401	ERDS2TJ472T	4.7K 1/4W [M]	R416	ERDS2TJ102T	1K 1/4W [M]	R701	ERJ6GEYJ4R7A	4.7 1/10W [M]
R31	ERDS2TJ123T	12K 1/4W [M]	R402	ERDS2TJ472T	4.7K 1/4W [M]	R417	ERDS2TJ103T	10K 1/4W [M]	R702	ERJ6GEYJ822A	8.2K 1/10W [M]
R32	ERDS2TJ103T	10K 1/4W [M]	R403	ERDS2TJ472T	4.7K 1/4W [M]	R418	ERDS2TJ821T	820 1/4W [M]	R703	ERJ6GEYJ823A	82K 1/10W [M]
R33	ERDS2TJ103T	10K 1/4W [M]	R404	ERDS2TJ472T	4.7K 1/4W [M]	R419	ERDS2TJ821T	820 1/4W [M]	R704	ERJ6GEYJ102A	1K 1/10W [M]
R41	ERDS2TJ471T	470 1/4W [M]	R405	ERDS2TJ472T	4.7K 1/4W [M]	R421	ERDS2TJ472T	4.7K 1/4W [M]	R705	ERJ6GEYJ124A	120K 1/10W [M]
R42	ERDS2TJ2R2T	2.2 1/4W [M]	R406	ERDS2TJ472T	4.7K 1/4W [M]	R461	ERDS2TJ271T	270 1/4W [M]	R706	ERJ6GEYJ102A	1K 1/10W [M]
R43	ERDS2TJ2R2T	2.2 1/4W [M]	R407	ERDS2TJ472T	4.7K 1/4W [M]	R462	ERDS2TJ221T	220 1/4W [M]	R707	ERJ6GEYJ474A	470K 1/10W [M]
R51	ERDS2TJ122T	1.2K 1/4W [M]	R409	ERDS2TJ102T	1K 1/4W [M]	R601	ERDS2TJ121T	120 1/4W [M]	R708	ERJ6GEYJ154A	150K 1/10W [M]
R52	ERDS2TJ122T	1.2K 1/4W [M]	R410	ERDS2TJ103T	10K 1/4W [M]	R602	ERDS2TJ121T	120 1/4W [M]	R709	ERJ6GEYJ473A	47K 1/10W [M]

Ref No.	Part No.	Values & Remarks	Ref No.	Part No.	Values & Remarks	Ref No.	Part No.	Values & Remarks	Ref No.	Part No.	Values & Remarks
R710	ERJ6GEYJ103A	10K 1/10W [M]		CAPACITORS		C708	ECUZ1H392KBN	3900P 50V [M]	C809	ECEA0JKA470B	47 6.3V [M]
R711	ERJ6GEYJ154A	150K 1/10W [M]				C709	ECUZ1E563KBN	0.056 25V [M]	C810	ECEA0JKA470B	47 6.3V [M]
R712	ERJ6GEYJ221A	220 1/10W [M]	C11	ECBT1E103ZF5	0.01 25V [M]	C710	ECUV1H151KCN	150P 50V [M]	C811	ECBT1H102KB5	1000P 50V [M]
R715	ERJ6GEYJ122A	1.2K 1/10W [M]	C12	ECEA1CM332B	3300 16V [M]	C711	ECUZ1E104ZFN	0.1 25V [M]	C812	ECBT1H102KB5	1000P 50V [M]
R717	ERJ6GEYJ101A	100 1/10W [M]	C15	ECBT1H102KB5	1000P 50V [M]	C712	ECUZ1E104ZFN	0.1 25V [M]			
R718	ERJ6GEYJ101A	100 1/10W [M]	C16	ECA1AM471B	470 10V [M]	C713	ECUZ1E104MBN	0.1 25V [M]		TEST JUMPER	
R721	ERJ6GEYJ101A	100 1/10W [M]	C17	ECEA0JKA101B	100 6.3V [M]	C714	ECEA0JKA101I	100 6.3V [M]			
R722	ERJ6GEYJ563A	56K 1/10W [M]	C20	ECBT1E103ZF5	0.01 25V [M]	C715	ECUZ1H182KBN	1800P 50V [M]	TJ701	EYF8CU	JUMPER [M]
R723	ERJ6GEYJ182A	1.8K 1/10W [M]	C21	RCA1EM101BT	100P 25V [M]	C716	ECUZ1H821KBN	820P 50V [M]			
R724	ERJ6GEYJ333A	33K 1/10W [M]	C22	RCA1EM101BT	100P 25V [M]	C717	ECUZ1E104ZFN	0.1 25V [M]			
R725	ERJ6GEYJ122A	1.2K 1/10W [M]	C25	ECBT1H102KB5	1000P 50V [M]	C718	ECUZ1C224KBN	0.22 16V [M]			
R726	ERJ6GEYJ473A	47K 1/10W [M]	C26	ECBT1H102KB5	1000P 50V [M]	C721	ECUZ1H150JCN	15P 50V [M]			
R727	ERJ6GEYJ682A	6.8K 1/10W [M]	C30	ECBT1E103ZF5	0.01 25V [M]	C722	ECUZ1H150JCN	15P 50V [M]			
R728	ERJ6GEYJ682A	6.8K 1/10W [M]	C31	ECA1HM470B	47P 50V [M]	C723	ECEA1AKA221I	220 10V [M]			
R729	ERJ6GEYJ562A	5.6K 1/10W [M]	C32	ECA1HM470B	47P 50V [M]	C724	ECUZ1E104MBN	0.1 25V [M]			
R731	ERJ6GEYJ822A	8.2K 1/10W [M]	C33	ECBT1H102KB5	1000P 50V [M]	C730	ECUZ1E104ZFN	0.1 25V [M]			
R735	ERJ6GEYJ101A	100 1/10W [M]	C41	ECBT1H102KB5	1000P 50V [M]	C731	ECEA0JKA221I	220 6.3V [M]			
R736	ERJ6GEYJ101A	100 1/10W [M]	C42	ECEA0JKA101B	100 6.3V [M]	C732	ECEA0JKA221I	220 6.3V [M]			
R738	ERJ6GEYJ223A	22K 1/10W [M]	C301	ECBT1C103NS5	0.01 16V [M]	C733	ECUZ1E104MBN	0.1 25V [M]			
R744	ERJ6GEYJ104A	100K 1/10W [M]	C311	ECEA1HKA101B	1 50V [M]	C734	ECEA1AKA221I	220 10V [M]			
R745	ERJ6GEYJ155A	1.5M 1/10W [M]	C312	ECBT1C103NS5	0.01 16V [M]	C735	ECUZ1E104ZFN	0.1 25V [M]			
R748	ERJ6GEYJ182A	1.8K 1/10W [M]	C351	ECEA0JKA221B	220 6.3V [M]	C736	ECUZ1E104ZFN	0.1 25V [M]			
R749	ERJ6GEYJ682A	6.8K 1/10W [M]	C352	ECBT1C103NS5	0.01 16V [M]	C737	ECUZ1E104ZFN	0.1 25V [M]			
R752	ERJ8GEYJ220A	22 1/8W [M]	C353	ECBT1C103NS5	0.01 16V [M]	C738	ECUZ1E104MBN	0.1 25V [M]			
R753	ERJ6GEYJ102A	1K 1/10W [M]	C354	ECBT1C103NS5	0.01 16V [M]	C739	ECUZ1H102KBN	1000P 50V [M]			
R803	ERDS2TJ224T	220K 1/4W [M]	C355	ECBT1C103NS5	0.01 16V [M]	C742	ECUZ1E273KBN	0.027 25V [M]			
R804	ERDS2TJ224T	220K 1/4W [M]	C401	ECBT1C103NS5	0.01 16V [M]	C743	ECUZ1E104ZFN	0.1 25V [M]			
R805	ERDS2TJ822T	8.2K 1/4W [M]	C402	ECA0JM471B	470P 6.3V [M]	C744	ECUZ1E123KBN	0.012 25V [M]			
R806	ERDS2TJ822T	8.2K 1/4W [M]	C403	ECEA1HKA101B	1 50V [M]	C745	ECUZ1H102KBN	1000P 50V [M]			
R807	ERDS2TJ123T	12K 1/4W [M]	C404	ECEA1EKA4R7B	4.7 25V [M]	C747	ECUV1H221KBN	220P 50V [M]			
R808	ERDS2TJ123T	12K 1/4W [M]	C405	ECBT1C103NS5	0.01 16V [M]	C749	ECUZ1H222KBN	2200P 50V [M]			
R809	ERDS2TJ333T	33K 1/4W [M]	C406	ECEA1HKA101B	1 50V [M]	C750	ECUZ1E104MBN	0.1 25V [M]			
R810	ERDS2TJ333T	33K 1/4W [M]	C421	ECBT1C103NS5	0.01 16V [M]	C751	ECUZ1E104MBN	0.1 25V [M]			
R811	ERDS2TJ333T	33K 1/4W [M]	C461	ECEA1AU470B	47 10V [M]	C753	ECUZ1H471KBM	470P 50V [M]			
R812	ERDS2TJ333T	33K 1/4W [M]	C462	ECBT1C103NS5	0.01 16V [M]	C755	ECUZ1H102KBN	1000P 50V [M]			
R813	ERDS2TJ102T	1K 1/4W [M]	C601	ECFR1E104ZF5	0.1 25V [M]	C756	ECUZ1H102KBN	1000P 50V [M]			
R814	ERDS2TJ102T	1K 1/4W [M]	C602	ECBT1C103NS5	0.01 16V [M]	C757	ECUZ1H102KBN	1000P 50V [M]			
R815	ERDS2TJ102T	1K 1/4W [M]	C603	ECBT1H331KB5	330P 50V [M]	C762	ECUZ1H471KBN	470P 50V [M]			
R816	ERDS2TJ102T	1K 1/4W [M]	C604	ECBT1H102KB5	1000P 50V [M]	C801	ECEA1AKA470B	47 10V [M]			
R817	ERDS2TJ473T	47K 1/4W [M]	C605	ECBT1C103NS5	0.01 16V [M]	C802	ECEA1AKA470B	47 10V [M]			
R818	ERDS2TJ473T	47K 1/4W [M]	C701	ECEA0JKA330I	33 6.3V [M]	C803	ECEA1CKA100B	10 16V [M]			
R819	ERDS2TJ100T	10 1/4W [M]	C702	ECUZ1E104MBN	0.1 25V [M]	C804	ECEA1CKA100B	10 16V [M]			
R820	ERDS2TJ100T	10 1/4W [M]	C703	ECEA0JKA101I	100 6.3V [M]	C805	ECCR1H391J5	390P 50V [M]			
R851	ERDS2TJ122T	1.2K 1/4W [M]	C704	ECUZ1E104MBN	0.1 25V [M]	C806	ECCR1H391J5	390P 50V [M]			
R852	ERDS2TJ102T	1K 1/4W [M]	C706	ECUZ1H272KBN	2700P 50V [M]	C807	ECCR1H391J5	390P 50V [M]			
R853	ERDS2TJ103T	10K 1/4W [M]	C707	ECUZ1E273KBN	0.027 25V [M]	C808	ECCR1H391J5	390P 50V [M]			