


SERVICE MANUAL

STEREO CASSETTE DECK

SANSUI D-290

(Silver & Black Model)



CAUTION

1. Parts identified by the \triangle symbol on the schematic diagram and the parts list are critical for safety. Use only replacement parts that have critical characteristics recommended by the manufacturer.
2. Make leakage-current or resistance measurements to determine that exposed parts are acceptably insulated from the supply circuit before returning the appliance to the customer.

•SPECIFICATIONS

Track format.....	4-track/2-channel system
Tape speed.....	4.8 cm/sec.
Heads (2-head configuration)	
Rec/pb head.....	HIGH-Bs hard permalloy
Erase head.....	Double-gap HIGH-Bs ferrite
Motor	Capstan: Electronically Controlled DC Motor Reels: DC Motor
Wow/flutter	0.05% max (WRMS)
Fast forwarding (rewinding) time	
.....	Approx. 85 sec. (for C-60 tape)
Frequency response (—20 VU recording/playback)	
Normal tape (LH)	20 to 15,000 Hz (30 to 14,000 Hz \pm 3 dB)
Chrome tape	20 to 16,000 Hz (30 to 15,000 Hz \pm 3 dB)
Metal tape.....	20 to 17,000 Hz (30 to 16,000 Hz \pm 3 dB)
Signal-to-noise ratio (recording/playback with metal tape)	
DOLBY NR OFF	Better than 57 dB
DOLBY-B NR ON.....	Better than 67 dB (above 5 kHz)
DOLBY-C NR ON.....	Better than 77 dB (above 1 kHz)
Erase rate (metal tape)	
.....	70 dB min (1 kHz)
Recording bias frequency	
.....	85 kHz
Input sensitivity/Impedance	
LINE IN (REC).....	70 mV/100 kohms
MIC	0.5 mV/200 ~ 5,000 ohms
Power requiremets	120/220/240V 50/60 Hz
For U.S.A. and Canada	
.....	120V (60 Hz)
Power consumption	14W
Dimensions	430 mm (16-15/16") W 111 mm (4-3/8") H 234 mm (9-1/4") D
Weight	3.6 kg (7.9 lbs) net 4.6 kg (10.1 lbs) packed


- * Design and specifications subject to changes without notice for improvements.
- * Noise reduction system manufactured under license from Dolby Laboratories Licensing Corporation.
"Dolby" and the double D symbol are trade marks of Dolby Laboratories Licensing Corporation.




SANSUI ELECTRIC CO., LTD.

1. BLOCK DIAGRAM


1-1. Logic Control Section



1-2. Playback Section <L-ch>



1-3. Recording Section <L-ch>



2. MODE OPERATION & TIMING CHART OF IC TC9310N-046


•Mode Operation of IC TC9310N-046

PRESENT MODE \ INPUT KEY	STOP	PLAY	F.F	REW	REC	PAUSE	AUTO STOP	AMPS SIG.OFF
STOP	—	PLAY	F.F	REW	REC (-)	PAUSE	/	/
PLAY	STOP	—	CUE	REVIEW	—	PLAY.PAUSE	STOP	/
F.F	STOP	PLAY	—	REW	—	—	STOP	/
REW	STOP	PLAY	F.F	—	—	—	STOP	/
CUE	STOP	PLAY	—	REW	—	—	STOP	PLAY
REVIEW	STOP	PLAY	F.F	—	—	—	STOP	PLAY
REC	STOP	—	F.F	REW	—	REC.PAUSE	STOP	/
PAUSE	STOP	PLAY.PAUSE	F.F	REW	REC.PAUSE (-)	STOP	/	/
PLAY.PAUSE	STOP	—	F.F	REW	REC.PAUSE (-)	PLAY	/	/
REC.PAUSE	STOP	—	F.F	REW	—	REC	/	/


- Note: 1. This table shows operation when one input key is depressed on present mode.
 2. CUE is in the state of PLAY mode under FF operation.
 Review is in the state of PLAY mode under REW operation.

— mark means continuing present mode.
 / mark means non relation with other input ports.

•Pin-connection




•Microcomputer Timing Chart (REC, REW→FF→STOP, FF→PLAY)




3. OPERATIONS OF PINCH ROLLER

3-1. Torque Transportation Flowchart




• The pinch roller is brought into pressure contact with the capstan shaft.


3-2. Rear View of Mechanism Chassis



3-3. Front View of Mechanism Chassis




3-4. Cam Positions in the Modes of PLAY, FF, REW & STOP




4. INTERIOR BLOCK DIAGRAM OF IC


•HA12058NT (Dolby Noise Reduction IC)



•BA6208 (Motor Drive IC)





•M5218P (OP AMP. IC)



5. ADJUSTMENTS

5-1. Tape Speed Adjustment



- Note:** 1. Use Sansui Test Tape, SCT-S3K (3 kHz signal is recorded on the tape).
 2. Connections are shown in Fig. 5-1.
 3. Remove the cassette lid. (See Fig.10-2 on page 15)



STEP	SUBJECT	MEASURE OUTPUT	SETTING	ADJUSTMENT	ADJUST FOR	REMARKS
1.	Tape Speed Adj.	LINE OUT Frequency counter	Playback the Test Tape SCT-S3K.	Turn semi-variable resistor as Fig. 5-2	3000Hz ± 45Hz	Use small screw driver

5-2. Playback Adjustment

- Note:** 1. Before this adjustment, clean REC/P.B. head surface.
 2. For this adjustment, use Sansui Test Tape, SCT-F10K, and SCT-L400N.
 3. Connections are shown in Fig. 5-3.
 4. DOLBY NR..... OFF
 5. Remove the cassette lid. (See Fig. 10-2 on page 15)




STEP	SUBJECT	MEASURE OUTPUT	SETTING	ADJUSTMENT	ADJUST FOR	REMARKS
1.	REC/P.B. Head Adj.	LINE OUT VTVM and Scope	Set TAPE SELECTOR to NORMAL Playback the TEST TAPE SCT-F10K	Adjust the azimuth adjusting screw in Fig. 5-4.	Maximum output from L and R-ch	After this adjustment, lock the screw with paint.
2.	Playback Level Pre Adj.	Between Point (A)/(B) (vC14) & GND VTVM and Scope	Set TAPE SELECTOR to NORMAL Playback the TEST TAPE SCT-L400N	Adjust each vVR101 (F-4430) of L-CH and R-CH	10mV ± 2dB	See Top View on page 12.
3.	Playback Level Adj.	LINE OUT VTVM and Scope	Same as above	Adjust each vVR2 (F-4440) of L-CH and R-CH	500mV ± 2dB	See Top View on page 12.

5-3. Recording Adjustment

1) Bias Frequency Adjustment

- * Perform this adjustment when bias pot or REC/P.B. head replaced.
Note: 1. For this adjustment, use Sansui Test Tape, SCT-MA.
 2. Connections are shown in Fig. 5-5.
 3. DOLBY NR..... OFF




STEP	SUBJECT	MEASURE OUTPUT	SETTING	ADJUSTMENT	ADJUST FOR	REMARKS
1.	Bias Frequency Adj.	Between Point (C) (vC207) & GND Frequency counter	Load Test Tape SCT-MA and set TAPE SELECTOR to METAL. Depress REC button.	Adjust vL202 (F-4431)	85kHz ± 5kHz	See Top View on page 12.

2) REC Level & Frequency Response Adjustment

- Note:** 1. Connections are shown in Fig. 5-6.
 2. DOLBY NR..... OFF
 3. REC LEVEL..... Maximum

Fig. 5-6



STEP	SUBJECT	INPUT SIGNAL	MEASURE OUTPUT	SETTING	ADJUSTMENT	REMARKS
1.	REC Level Adj.	Feed 1kHz, 150mV from S.G. into LINE IN.	LINE OUT, VTVM and Scope	Load the Test Tape SCT-SA and set TAPE SELECTOR to HIGH. 1. Depress PAUSE and REC button. 2. Adjust the Audio S.G. output level for obtaining 230mV on VTVM. 3. Push off the PAUSE button, then record the 1kHz signal. 4. Play back the 1kHz signal. 5. Confirm that the output levels on both channels are 230mV ± 2dB on VTVM.	1. If not, turn each vVR202 (F-4431) of L-CH and R-CH until output level 230mV ± 2dB on both channels are obtained.	See Top View on page 12.
2.	Frequency Response (BIAS) Adj.	Feed 1kHz 15mV (-20dB) and 10kHz 15mV (-20dB) from S.G. into LINE IN.	Seme as above	Load the Test Tape SCT-SA and set TAPE SELECTOR to HIGH. 1. Record the 1kHz and 10kHz signals from S.G. 2. Play back the 1kHz and 10kHz signals, then confirm that both output levels equal.	1. If not, adjust each vVR203 (F-4431) of L-CH and R-CH slightly until the output levels will be equal.	See Top View on page 12.
3.	Metal REC Level Adj.	Feed 1kHz 150mV from S.G. into LINE IN.	LINE OUT VTVM and Scope	Load the Test Tape SCT-MA and set TAPE SELECTOR to METAL. 1. Depress PAUSE and REC button. 2. Adjust the Audio S.G. output level for obtaining 230mV on VTVM. 3. Push off the PAUSE button, then record the 1kHz signal. 4. Play back the 1kHz signal. 5. Confirm that the output levels on both channels are 230mV ± 2dB on VTVM.	1. If not, adjust each vVR201 (F-4431) of L-CH and R-CH until output level 230mV ± 2dB on both channels are obtained.	See Top View on page 12.

◆ List of Sansui Test Tape

Name of TEST TAPE	Recorded Frequency	Description	Equivalent To
SCT-F40	40 Hz	Playback Frequency Response Check	—
SCT-F1K	1 kHz	High Frequency Equalization Check	—
SCT-F10K	10 kHz	REC/PB Head Adjustment	—
SCT-L400N	400 Hz	Playback Level and Indicator Level Adjustment	—
SCT-S3K	3 kHz	Speed Check and Wow & Flutter Check	—
*SCT-AD NORMAL	—	Recording Bias Adjustment	TDK AD
*SCT-SA HIGH	—	REC/PB Level Adjustment	TDK SA
*SCT-MA (METAL)	—	Frequency Response Check	TDK MA

•Note: Some reference tapes marked * are not supplied. As these are equivalent to ones indicated above, please obtain these blank tapes on your side as possible.

◆ TAPE SELECTOR Position

NORMAL	
FUJI	FL, FX I
MAXELL	UL, UD, XL I, XL I-S
TDK	D, AD, OD
SCOTCH	TARTAN CRYSTAL MASTER 120
SONY	AHF, BHF, CHF Low-Noise
AGFA	SUPER SUPER COLOR SUPER FERRO DYNAMIC.
BASF	LN Super LH I


HIGH	
FUJI	FX II
MAXELL	XL II, XL II-S
TDK	SA, SA-X
SCOTCH	MASTER 70
SONY	JHF
AGFA	STEREO CHROM
BASF	SCR

METAL	
MAXELL	MX
TDK	MA-R, MA
SCOTCH	Metafine
SONY	METALLIC


6. PARTS LOCATION & PARTS LIST

6-1. F-4422 Noise Reduction Circuit Board (Stock No. 00777801)

Top View (Component Side) with Bottom Side Pattern



Chip Parts View with Bottom Side Pattern




Parts List

Parts No.	Stock No.	Description
•IC		
xIC1	46671900	HA12058NT
xJW1	46741100	Cross Conductor (Chip)
xJW2	46741100	Cross Conductor (Chip)
xJW3	46741100	Cross Conductor (Chip)
xJW4	46741100	Cross Conductor (Chip)
xJW5	46741100	Cross Conductor (Chip)
xR1	46754000	470kΩ 1/8W Chip R.
xR2	46749400	5.6kΩ 1/8W Chip R.
xR4	46749800	8.2kΩ 1/8W Chip R.
xR5	46748800	3.3kΩ 1/8W Chip R.
xR6	46750900	24kΩ 1/8W Chip R.
xR7	46749500	6.2kΩ 1/8W Chip R.
xR8	46752200	82kΩ 1/8W Chip R.

Parts No.	Stock No.	Description
xR9	46754800	1MΩ 1/8W Chip R.
xR10	46752200	82kΩ 1/8W Chip R.
xR11	46752200	82kΩ 1/8W Chip R.
xR12	46748800	3.3kΩ 1/8W Chip R.
xR13	46747600	1kΩ 1/8W Chip R.
xR14	46752200	82kΩ 1/8W Chip R.
xR15	46749500	6.2kΩ 1/8W Chip R.
xR16	46752200	82kΩ 1/8W Chip R.
xR17	46746800	470Ω 1/8W Chip R.
xR18	46749200	4.7kΩ 1/8W Chip R.
xR19	46750000	10kΩ 1/8W Chip R.
xR20	46752000	68kΩ 1/8W Chip R.
xR21	46754800	1MΩ 1/8W Chip R.
xFL1	46177600	TRAP FILTER, 19.8kHz

6-2. F-4431 Rec Amp Circuit Board (Stock No. 00779001)

Component Side




•Note: On this circuit board, the left channel is specified by "●" mark on top of the parts No.

Parts List


Parts No.	Stock No.	Description
•Transistor		
vQ201	46367101	2SC2603
	or 46391901	2SC2785
vQ202	46367101	2SC2603
	or 46391901	2SC2785
vQ203	46725801	2SC1627A
vQ204	03086101	2SD357
vQ205	46367101	2SC2603
	or 46391901	2SC2785
vQ206	46367101	2SC2603
	or 46391901	2SC2785
•Zener Diode		
vDZ201	46109400	05Z3.0-Y
vC208	46657000	3900pF 100V F.C.
vFL201	42904400	Peaking Coil
vL201	46313900	Inductor 2.7mH
vL202	46362200	Bias OSC Coil
vVR201	07262200	100kΩ(B) S.V.R., Metal Rec Level Adj.
vVR202	07262100	50kΩ(B) S.V.R., Rec Level Adj.
vVR203	07262200	100kΩ(B) S.V.R., Bias Adj.

6-3. F-4430 Playback Amp Circuit Board (Stock No. 00778901)

Top View (Component Side) with Bottom Side Pattern



Chip Parts View with Bottom Side Pattern




Parts List

Parts No.	Stock No.	Description
•Transistor		
vQ101	46359801	2SC2001
vQ102	46577801	2SC2320L
vQ103	46577801	2SC2320L
vQ104	46367101 or 46391901	2SC2603 2SC2785
•Diode		
vD101	46852000	RLS-73
vR101	46742800	10Ω 1/8W Chip R.
vR102	46749200	4.7kΩ 1/8W Chip R.
vR103	46753200	220kΩ 1/8W Chip R.
vR104	46751600	47kΩ 1/8W Chip R.
vR105	46750400	15kΩ 1/8W Chip R.

Parts No.	Stock No.	Description
vR106	46753200	220kΩ 1/8W Chip R.
vR107	46744000	33Ω 1/8W Chip R.
vR108	46747800	1.2kΩ 1/8W Chip R.
vR109	46746800	470Ω 1/8W Chip R.
vR110	46752800	150kΩ 1/8W Chip R.
vR111	46748600	2.7kΩ 1/8W Chip R.
vR112	46748400	2.2kΩ 1/8W Chip R.
vR113	46750000	10kΩ 1/8W Chip R.
vR114	46753200	220kΩ 1/8W Chip R.
vVR101	46839300	1kΩ S.V.R., P.B Level Adj.
vRL101	11504700 or 11504701	Relay Relay

6-4. F-4463 Mic Amp Circuit Board (Stock No. 00783701)

Component Side




Parts List

Parts No.	Stock No.	Description
•Transistor		
gQ1	46367101 or 46391901	2SC2603 2SC2785
gQ2	46367101 or 46391901	2SC2603 2SC2785
gVR1	07106701	20kΩ(A) V.R., MIC
oJ3	46502200	JACK, MIC

6-5. F-4439 Rec, Play & Pause Indi. Circuit Board

Component Side




Parts List

Parts No.	Stock No.	Description
•LED		
nLD1	46176900	TLS-123
nLD2	07251000	TLY-123
nLD3	07250900	TLG-123A

6-6. F-4438 Control SW. Circuit Board

Component Side




Parts List

Parts No.	Stock No.	Description
oPS1	46133300	Push SW., REW
oPS2	46133300	Push SW., F.FWD
oPS3	46133300	Push SW., PLAY
oPS4	46133300	Push SW., REC
oPS5	46133300	Push SW., STOP
oPS6	46133300	Push SW., PAUSE

Parts No.	Stock No.	Description
oS1	46917200	Push SW., TAPE SELECTOR
oS2	46916900	Push SW., DOLBY NR SYSTEM
oS3	46178400	Silde SW., TIMER
vVR1	46917400	50kΩ V.R., REC LEVEL

6-7. F-4461 Indicator Circuit Board

Component Side




Parts List

Parts No.	Stock No.	Description
•LED		
nLD5	46921900	LD-702GG

6-8. F-4464 Phones Jack Circuit Board

Component Side




Parts List

Parts No.	Stock No.	Description
oJ2	46265700	JACK, PHONES

6-9. F-4433 Power SW. Circuit Board

Component Side




Parts List

Parts No.	Stock No.	Description
Δ pC1	46425800	0.01μF 400V C.C.
Δ pS1	46360300	Push SW., POWER

6-10. F-4440 Main Circuit Board (Stock No. 00779201)

Component Side



Parts List


Parts No.	Stock No.	Description
•Transistor		
△ mQ2	03085201	2SD438
△ mQ3	03083901	2SD313AL
mQ4	46367101	2SC2603
	or 46391901	2SC2785
•Diode		
△ mD1	46273600	DBB10-B
△ mD2	46273600	DBB10-B
△ mD3	03117600	1S2473T77
△ mD4	or 46086000	1S1588TP-3
△	03117600	1S2473T77
△	or 46086000	1S1588TP-3
•Zener Diode		
mDZ2	46111500	05Z5.6-Y
△ mR7	00135300	47Ω 1/2W N.I.R.
oJ1	46371500	4P TERMINAL BOARD, LINE IN/ LINE OUT
•Transistor		
vQ1	46367101	2SC2603
	or 46391901	2SC2785
vQ2	46367101	2SC2603
	or 46391901	2SC2785
vQ3	46367101	2SC2603
	or 46391901	2SC2785
vQ4	46367101	2SC2603
	or 46391901	2SC2785
vQ5	46367101	2SC2603
	or 46391901	2SC2785
vQ6	46367101	2SC2603
	or 46391901	2SC2785
vQ7	46367101	2SC2603
	or 46391901	2SC2785
vQ8	46367101	2SC2603
	or 46391901	2SC2785

Parts No.	Stock No.	Description
vQ9	46367001	2SA1115
	or 46392001	2SA1175
vQ11	46367101	2SC2603
	or 46391901	2SC2785
vQ12	46367101	2SC2603
	or 46391901	2SC2785
vQ13	46367101	2SC2603
	or 46391901	2SC2785
vQ14	46367101	2SC2603
	or 46391901	2SC2785
vQ15	46367101	2SC2603
	or 46391901	2SC2785
vQ16	46367101	2SC2603
	or 46391901	2SC2785
•IC		
vic1	46580100	M5218P
•Diode		
vd1	03117600	1S2473T77
	or 46086000	1S1588TP-3
vd4	03117600	1S2473T77
	or 46086000	1S1588TP-3
△ vR18	46681300	10Ω 1/4W F.R.
vFL1	46177500	Dolby Filter
vVR2	46839200	470Ω S.V.R., P.B Level Adj.
•Transistor		
wQ1	46367101	2SC2603
	or 46391901	2SC2785
wQ2	46719800	DTA124
wQ3	46719800	DTA124
wQ4	46359801	2SC2001
wQ5	03085201	2SD438
wQ6	46367101	2SC2603
	or 46391901	2SC2785

Parts No.	Stock No.	Description
wQ7	46367101	2SC2603
	or 46391901	2SC2785
wQ8	46359701	2SA952
wQ9	46367101	2SC2603
	or 46391901	2SC2785
wQ10	46367101	2SC2603
	or 46391901	2SC2785
wQ11	46367101	2SC2603
	or 46391901	2SC2785
•IC		
wIC1	46916800	TC9310N-046
wIC2	46149600	BA6208
•Diode		
wD1	03117600	1S2473T77
	or 46086000	1S1588TP-3
wD2	03117600	1S2473T77
	or 46086000	1S1588TP-3
wD4	03117600	1S2473T77
	or 46086000	1S1588TP-3
wD5	03117600	1S2473T77
	or 46086000	1S1588TP-3
△ wR5	46242000	47Ω 1W N.I.R.
△ wR12	00191900	82Ω 2W N.I.R.

7. OTHER PARTS


7-1. Front View



Parts List

Parts No.	Stock No.	Description
<Common Parts>		
2	46899300	Tape Counter
3	46917500	LED LEVEL METER (LT-1115)
4	47484200	Meter Window Cover
5-1	47350900	Knob, EJECT
6	46133300	Push SW., REW, F.FWD, PLAY, REC, STOP, PAUSE
8	47257100	Knob, POWER
9	46360300	Push SW., POWER
10	47353000	Slide Knob, TIMER
11	46178400	Slide SW., TIMER
13	07106701	20kΩ(A) V.R., MIC
14	46502200	Jack, MIC
15	46265700	Jack, PHONES
18	46917400	50kΩ V.R., REC LEVEL
19	47353200	Knob, TAPE SELECTOR
20	46917200	Push SW., TAPE SELECTOR
21	47353100	Knob, DOLBY NR SYSTEM
22	46916900	Push SW., DOLBY NR SYSTEM
23	47352100	Spring, EJECT
<Silver Model>		
1	47379000	Cassette Lid Ass'y
5	47427600	Front Panel Ass'y
7	47338600	Bonnet
12	47496000	Knob, MIC
16	47256610	Knob, REC LEVEL (L)
17	47502400	Knob, REC LEVEL (R)
<Black Model>		
1	47379100	Cassette Lid Ass'y
5	47427700	Front Panel Ass'y
7	47352300	Bonnet
12	07680600	Knob, MIC
16	47427400	Knob, REC LEVEL (L)
17	47502500	Knob, REC LEVEL (R)

7-2. Top View




Parts List


Parts No.	Stock No.	Description
1	46371500	4P Terminal Board, LINE IN/LINE OUT
2	47103100	Tention Wire
3	15015201	Power Transformer (XX)
3	15015202	Power Transformer (UL, CSA)
3	15015205	Power Transformer (EU, BS, AS)
4	38005700	Power Supply Cord (XX, UL, CSA)
4	38004500	Power Supply Cord (EU)
4	38004300	Power Supply Cord (BS)
4	07204200	Power Supply Cord (AS)
5	47157300	AC Cord Cover
6	47174920	Right Side Panel Ass'y
	47491000	Right Side Panel Ass'y
		<Silver Model>
		<Black Model>
7	47351100	Joint Shaft
8	46370300	Eject Damper Ass'y
9	47375700	Damper Holder
10	47378200	Counter Belt
11	47174810	Left Side Panel Ass'y
		<Silver Model>
		<Black Model>
12	07204700	Slide SW., Voltage Selector (EU, BS)
13	47292700	Leaf Switch, harf

8. EXPLODED VIEW OF MECHANISM ASS'Y & PARTS LIST


8-1. Front View of Mechanism Chassis



8-2. Rear View of Mechanism Chassis



•Shapes of standard mechanical parts



① ~ ⑩
⑪ ~ ⑳
㉑ ~ ㉳

Parts No.	Stock No.	Description
1	46731200	Tapping Screw, M2.6 x 8
2	47406000	Spring, eject
3	47420900	Plastic Tack
4	47281800	Pinchroller Ass'y
5	47405500	Spring, pinchroller
6	47406200	Spring, head base
7	47405600	Spring, head slider
8	47405900	Spring, plunger solenoid
9	47404700	Washer, φ2.5


Parts No.	Stock No.	Description
10	47293500	Spring, half
11	47405700	Spring, reel
12	00420900	Binding Head Screw, M2 x 12
13	47404900	Steel Ball, φ2
14	47405000	Arm Ass'y
15	47404800	Washer, 1.6 x 3.5
16	47497100	Washer, d=2.0
17	47281000	Sprocket
18	47281100	Reel Damper

Parts No.	Stock No.	Description
19	47283300	Reel Gear
20	47283400	Reel Gear A
21	47155700	REC/PB Head
22	07997400	Erase Head
23	47406100	Spring, azimuth
24	46268900	Pan Head Deltite Screw, M2.6 x 6
25	47282900	Flywheel Ass'y
26	47281200	Capstan Gear
27	47405100	Belt
28	47283200	Pulley

Parts No.	Stock No.	Description
29	46737400	Capstan Motor
30	47281600	Lock Arm
31	46737500	Reel Motor
32	47293100	Gear, reel motor
33	47293800	Arm (B)
34	47283800	Assist Gear
35	47292600	Plunger Solenoid
36	47404600	Washer, 2.5 x 0.25
37	47284100	Head Base
38	47292400	Sensor Arm (A)

9. SCHEMATIC DIAGRAM

*Design and specifications subject to change without notice for improvement.
 *La présentation et les spécifications sont susceptibles d'être modifiées sans préavis par suites d'améliorations éventuelles.
 *Änderungen, die dem technischen Fortschritt dienen, bleiben vorbehalten.



SYMBOL
 Δ Ceramic Capacitor
 ▽ Barrier Layer Capacitor
 ⊖ Mylar Capacitor
 ⊕ Low-Leak Electrolytic
 □ Non-Inflammable Resistor

RESISTORS
 Are in ohms, 1/4 Watts, ±5% Tolerance
 Unless otherwise noted: k: 10, M: 10⁶

CAPACITORS
 Are in μF, Unless otherwise noted: p: pF

Each D.C. Voltage shows the nominal value in volts during recording.

⚡ is Safety Part.
 Use only replacement parts recommended by the manufacturer.

- 2SA952
- 2SA1115
- 2SC1627
- 2SC2603
- 2SC2001
- 2SC230L
- 2SD438
- 2SD313AL
- 2SD357
- 2SA1175
- 2SC2785
- DTA124
- BA6208
- HA1205BNT
- TC9310N-046
- Det. or SHI of Line
- DBB10-B
- 05Z3.0
- 05Z5.6
- 1SS1588TP-3
- 1S2473T77

— REC Signal Line
 - - - PLAY Signal Line

1
 2
 3
 4
 5

10. MAIN PARTS REPLACEMENT (See Exploded View on page 13)

A. Bonnet (See Fig. 10-1)

- 1) Remove two screws (S_A).
- 2) Push the rear side of the bonnet to remove the hooks and then remove bonnet.

B. Bottom Plate

- 1) Remove two screws (S_B). (Fig. 10-1)
 - 2) Push the rear side of the bottom plate to remove the hooks and then remove bottom plate.
- * Install the bottom plate after matching eject spring with Point (A) of bottom plate. (Fig. 10-4)

C. Side Panel L (R) (See Fig. 10-5)

- 1) Remove bonnet and bottom plate.
- 2) Shift the position of the side panel L (R) 1.5 cm in the arrow direction.
- 3) Remove the hooks (2) of the side panel from front panel and then pull it to the arrow direction (3) to remove the side panel L (R).

D. F-4430 and F-4431 Circuit Board

- 1) Remove the bonnet and bottom plate.
- 2) Extract four connectors from circuit boards at mechanism ass'y.
- 3) Remove the protection cover on F-4430 circuit board.
- 4) Loosen two screws fastening F-4430 circuit board.

E. Mechanism Ass'y

- 1) Take off the lid ass'y.
- 2) Remove the bonnet and bottom plate.
- 3) Extract five connectors from circuit boards at mechanism ass'y.
- 4) Remove F-4430 and F-4431 circuit board.
- 5) Remove the side panel L.
- 6) Loosen four screws (S_C) fixing mechanism ass'y. (See Top View on page 12)
- 7) Loosen the screw (S_D) fixing channel to remove the mechanism ass'y. (Fig. 10-1)
- 8) Take off counter belt.

F. Rec/PB Head (21)

- 1) Remove the mechanism ass'y from set.
- 2) Unsolder head read wires.
- 3) Loosen two screws.

G. Pinch roller Ass'y (4)


- 1) Remove the mechanism ass'y from set.
- 2) Pull out the lock pin (3).
- 3) Take out the pinchroller ass'y.

H. Reel Gear (19), (20)

- 1) Remove the mechanism ass'y from set.
- 2) Take off two washer (15), (16) to pull out reel gear.

I. Capstan Motor (29), Reel Motor (31), Capstan Belt (27), Flywheel (25), Plunger Solenoid (35)


- 1) Remove the F-4430 and F-4431 circuit board.
- 2) Remove the mechanism ass'y from set.
- 3) Loosen five screws (1), (24) fastening sub chassis (36).



J. Lid Ass'y

Depress the EJECT switch to open the cassette holder, and pull the cover up and then toward you to remove it as shown in the figure.

Fig. 10-2



Re-attach the cover to the cassette holder by following the procedure for its removal in reverse.

Fig. 10-3




Fig. 10-4






Fig. 10-5



11. PACKING LIST

Parts No.	Stock No.	Description
1	91263810	Vinyl Cover
2	47379700	Styrofoam Packing
3	47378400	Carton Case <Silver Model>
	47378500	Carton Case <Black Model>



12. ACCESSORY LIST

Stock No.	Description
07193400	PJP Cord x 2
or 38103300	PJP Cord x 2
94300500	Head Cleaner
46797900	Operating Instruction

Sansui

SANSUI ELECTRIC CO., LTD.:

SANSUI ELECTRONICS CORPORATION:

SANSUI ELECTRONICS (U.K.) LTD.:
SANSUI ELECTRONICS G.M.B.H.:

14-1, Izumi 2-chome, Suginami-ku, Tokyo 168 Japan
PHONE: (03) 324-8891/TELEX: 232-2076 (International Division)
1250 Valley Brook Ave. Lyndhurst, N.J. 07071 U.S.A.
17150 South Margay Ave. Carson, California 90746 U.S.A.
3036 Koapaka Street Honolulu, Hawaii 96819 U.S.A.

Unit 10A, Lyon Industrial Estate, Rockware Avenue, Geenford, Middx UB6, OAA, England
Pau Ehrich Strasse 8, 6074 Rödermark 2, West Germany