



### ALIGNMENT AND SENSITIVITY SIGNAL GENERATOR MODULATED 30% AT 400 CY.

STEP	APPLY SIGNAL		THRU SERIES DUMMY	SET GANG AT	ADJUST FOR MAX. OUTPUT	NOMINAL SENSITIVITY FOR 50 MILLIWATTS OUTPUT
	AT KC.	TO				
1	455	12BA6 #1 PIN	.05 $\mu\text{fd}$	—	2 <sup>ND</sup> I.F.	2600 $\mu\text{V}$ .
2	455	12BE6 #7 PIN	.05 $\mu\text{fd}$	MIN. CAP.	1 <sup>ST</sup> I.F. 2 <sup>ND</sup> I.F.	70 $\mu\text{V}$ .
3	1460	ANT.	400 $\Omega$	1460 KC	OSC. TRIM.	—
4	1460	ANT.	400 $\Omega$	1460 KC.	ANT. TRIM.	24 $\mu\text{V}$
5	600	ANT.	400 $\Omega$	600 KC	CHECK ONLY	40 $\mu\text{V}$

## VIKING RM-315