


EAR 8L6

SPECIFICATION

<i>Power Output</i>	50 watts/channel (30Hz-15kHz at 1% THD into rated load)
<i>Power Bandwidth</i>	15Hz-40kHz at less than 3% THD
<i>I.M.D.</i>	less than 1% at any level from 10mW to 50 Watts
<i>Output Damping Factor</i>	12
<i>Signal to Noise Ratio</i>	85dB
<i>Input Sensitivity</i>	200 mV
<i>Input Impedance</i>	47k Ohms
<i>Power Consumption</i>	200 watts total
<i>Weight</i>	20kg
<i>Size</i>	W 16" (405mm) D 16" (405mm) H 6" (150mm)
<i>Valves List</i>	2 x ECC83 2 x ECC85 8 x 6L6 (EL34)



YOSHINO 8L6 Stereo Pre/Main Amplifier

Designed and Drawn by Tim de Paravicini

Reproduction by whatever means and in any style shall

be actionable at law.

Due to continued developments, the circuit may change from time to time.