

PARTS LIST AND DESCRIPTIONS (Continued)

TRANSFORMER (POWER)

ITEM No.	RATING		REPLACEMENT DATA				Triad PART No.	
	PRI.	SEC.	EICO PART No.	Hollidorsen PART No.	Merit PART No.	Ram PART No.		Stancor PART No.
T1	117V @ .9A	750 VCT 5V @ 3V @ .100A	30016 ①					
	SEC. 3 6.3V @ 2.7A	SEC. 4 SEC. 5						

① Used in Model HF-22.

TRANSFORMER (POWER)

ITEM No.	RATING		REPLACEMENT DATA				Triad PART No.	
	PRI.	SEC.	EICO PART No.	Hollidorsen PART No.	Merit PART No.	Ram PART No.		Stancor PART No.
T1	125V @ 1.15A Tap @ 1.45A .005A	780VCT @ 5V @ 1.9A @ 1.75V @ 1.9A	30020 ②	24R38 ③			P-4004 ③	24R38 ③
	SEC. 3 6.3V @ 4.2A	SEC. 4 SEC. 5						

② Model HF-35

③ Parallel and phase 6.3 Volt windings. Tape center tap on 5V and 6.3V windings.

TRANSFORMER (AUDIO OUTPUT)

ITEM No.	IMPEDANCE		REPLACEMENT DATA				NOTES			
	PRI.	SEC.	EICO PART No.	Hollidorsen PART No.	Merit PART No.	Ram PART No.		Stancor PART No.	Thorderson PART No.	Triad PART No.
T2	7500Ω CT	16Ω Tap @ 8Ω, 4Ω	30004							

FUSES

ITEM No.	TYPE	RATING	REPLACEMENT DATA						
			EICO PART No.	Hollidorsen PART No.	Merit PART No.	Ram PART No.	Stancor PART No.	Thorderson PART No.	Triad PART No.
M1	3AG 250V	3A	91005	97800					
			FUSE	HOLDER	FUSE	HOLDER	FUSE	HOLDER	FUSE
				312003 (3AG 3A 250V)	342001	AGC3	HKP		

WIRING DATA

General-use Unshielded Hook-up Wire	Use BELDEN No. 8530 (Solid) Available in Ten Colors
Power Cord	8524 (Stranded) Available in Ten Colors
	1765-B (6 Ft. Length)
	1725-K (7½ Ft. Length)

CHASSIS - BOTTOM VIEW

