



- 1. KNOB SHOULD REMAIN PULLED OUT WHEN USING OPTIONAL PEDAL ASSEMBLY 01934.
- 2. SOME VERSIONS USE .001/25 VAC, PIN 018764 (NO SUBSTITUTE)
- 3. USED IN SOME VERSIONS.
- 4. ALL CAPACITORS 500 V MIN.
- 5. ALL RESISTORS 1/2 WATT ± 10%.
- 6. DENOTES TYPICAL 1W₂ SIGNAL REQUIRED FOR 1 WATT RMS OUTPUT AND 500 MV REVERB LOAD DRIVE IN RHYTHM MODE. ALL CONTROLS MAX. AND BOOSTS OFF.

Fender / Rosen / Rhodes

THE ORIGINAL INSTRUMENTS... A DIVISION OF FENDER INC. FULLERTON, CALIFORNIA 92631

SCHEMATIC, SUPER CHAMP
DOMESTIC, C.S.A., EXPORT & JAPAN
1 WATT REVERB AMP W/ BOOST PEDAL

| | | | |
|----------|-----------------------|----------|------|
| REVISION | DATE | FIG. NO. | REV. |
| 5 IN 87 | D | 01930 | A |
| SCALE | MODEL NO. SUPER CHAMP | | |

FENDER SUPER CHAMP AMPLIFIER (214400 & 214401)

PARTS LIST

019301 Cabinet w/hdw
 019311 Grill frame w/hdw
 019766 Lower cabinet back
 019767 Upper cabinet back
 019170 Handle w/insert
 019279 Handle cap
 024695 Corner - two screws
 019118 Power transformer
 022913 Output transformer
 022921 Reverb output transformer
 023010 10" standard speaker
 019576 10" EV speaker
 019585 Tolex - black
 018252 Grill cloth
 013341 7025/12AX7A tube
 013759 6C10 tube
 023531 12AT7 Tube
 023564 6V6GTA Tube
 018454 Reverb pan
 019419 21" reverb cable

CAPACITORS

010541 .0022mfd 10% 600v
 010992 560pf 10% 3kv
 014700 .047mfd x 125v
 020875 .003mfd 10% 1kv
 069724 .0001mfd 10% 1kv
 004513 .022mfd 10% 600v
 081590 .1mfd 20% 600v
 009512 25mfd x 25v
 010543 .01mfd 10% 600v
 012022 4mfd x 450v
 012754 .047 ± 10% 600v
 014122 70mfd x 100v
 020909 .000047mfd x 500v
 020917 .00025mfd 10% 1kv
 023257 .002mfd 10% 25v
 029320 .0027mfd x 60v 10% mylar
 094953 .001mfd 10% 600v
 019128 80mfd x 40 x 20 x 450v
 010639 .0012mfd 600v

RESISTORS

021394 10 meg ohm 10% 1/2w
 008167 100k 10% 1w
 011302 150 ohm 10% 1/2w
 021162 47 ohm 10% 1/2w
 021204 1k ohm 10% 1/2w
 021212 1.5k ohm 10% 1/2w
 021238 2.7k ohm 10% 1/2w
 021279 10k ohm 10% 1/2w
 021329 56k ohm 10% 1/2w
 021345 100k ohm 10% 1/2w
 021352 470k ohm 10% 1/2w
 021360 1 meg ohm 10% 1/2w
 021386 3.3 meg ohm 10% 1/2w
 021493 220k ohm 10% 1/2w
 031062 4.7k ohm 10% 1/2w
 051136 39k 10% 1/2w
 070128 680 ohm 10% 1/2w
 073593 12k ohm 10% 1/2w
 021519 1k ohm 10% 1w
 019256 390 ohm 10% 2w
 021220 2.2k ohm 10% 1/2w
 073502 270 ohm 10% 1/2w

DIODES

013556 VacTec led/1dr unit
 015003 IN5234B Zener
 026730 1 amp x 800v

CONTROLS

011540 1 meg 30% (volume)
 013404 250k w/switch (treble)
 021857 250k audio (bass)
 021873 100k (reverb, lead level, master)
 028421 100 ohm (hum balance)

SCREWS

011231 Cabinet back mounting
 016188 Reverb mounting
 019277 Speaker mounting
 022160 Glide mounting
 022103 Corner mounting
 022244 Handle mounting
 022152 Logo mounting
 022236 Chassis strap mounting
 084699 Cord clamp

WASHERS

010823 Dress - pilot light
 014567 Red enamel (pedal jack)
 031153 Finish (jack)
 016436 Lock - internal (controls)
 016469 Lock - internal (fuse holder)
 022384 Lock - internal (hum balance pot)
 043760 Neoprene (fuseholder)
 022293 Toggle switch

NUTS

016352 Jack, control mounting
 019282 Pem (chassis)
 022012 Toggle switch mounting
 031625 Pilot light holder mounting
 031666 Fuse holder mounting
 021972 Tee nut (handle mounting)

MISCELLANEOUS

013485 Knob (bass, reverb, lead level, master)
 024604 Knob (volume, treble)
 019163 Control plate
 019165 Rear plate - chassis
 011298 Logo
 010766 Line cord
 013762 Tube socket - 12 pin
 023580 Tube socket — 8 pin
 023606 Tube socket — 9 pin
 023598 Tube shield
 021527 Fuse holder
 021667 1A slo blo fuse
 021642 #47 pilot light
 021741 Pilot light holder
 032219 Pilot light collar
 025718 Pilot light jewel
 007565 Strain relief bushing (AC cord)
 016081 Capacitor clamp
 022491 Cable clamp
 013043 Jack (pedal plain)
 011028 Jack (input)
 021824 Jack (Reverb in & out)
 021956 Jack (line recording)
 023760 Jack - (pedal red)
 037960 Toggle switch
 019308 Glide assembly
 024679 Chassis strap

EXPORT

013002 Line cord
 016520 Voltage selector
 019119 Power transformer
 019167 Rear plate - chassis
 061663 Toggle switch
 036788 1-1/2A slo blo fuse

MODEL ONLY