FENDER "TWIN-AMP" SCHEMATIC

MODEL 6G8

F-FJ

NOTICE

1- VOLTAGES READ TO GROUND WITH ELECTRONIC VOLTMETER. VALUES SHOWN + OR - 20 %
2- ALL RESISTORS ½ WATT, 10% TOLERANCE IF NOT SPECIFIED
3- ALL CONDENSERS AT LEAST 400 VOLT RATING IF NOT SPECIFIED

VIBRATO
2
1
7025
VIBRATO PEDAL
4M-RA SPEED
100K
INTENSITY 1M-RA
BASS 1M-B
TREBLE 350K-TAP AT 70K
VOLUME 500K-L
+170 V.
+150 V.
+165 V.
+330 V.
+310 V.
+350V.
+72 V.
+70 V.
+3.3 V.
+1.3 V.
+1.17 V.
+160 V.
+145 V.
20-600 P.
27 K 1W
(4) 6L6GC
22K
+290 V.
+270 V.
+250 V.
+400 V.
+430 V.
+432 V.
-55 V.
+25 V.
+27 V.
MMF.
1500
56K
10K
4700
820
6800
TR1
TR2
TR3
TR1-6723
TR2-125C
TR3-4554
AC SWITCH
3 AMP. FUSE
GROUND SWITCH
TO ALL HEATERS AND PILOT LIGHT
NORMAL