



MULTIPLEX ADAPTER ALIGNMENT USING FM STEREO SIGNAL GENERATOR & AUDIO OSCILLATOR

	SIGNAL GENERATOR	CONNECT SCOPE	ADJUST	REMARKS
1.	19KC to input jack, low side to chassis.	Vert. amp. to pin 6 of V2, low side to chassis.	A1	Adjust for maximum deflection.
2.	"	Vert. amp. to pin 2 of V1, low side to chassis.	A2	Adjust for maximum deflection. Set scope to lock in 2-cycle waveform.
3.	"	Vert. amp. to point A, low side to chassis.	A3	Adjust for maximum deflection of 4-cycle waveform.
4.	67KC to input jack, low side to chassis.	"	A4	Adjust for MINIMUM deflection.
5.	"	"	A5	Adjust for maximum deflection.
6.	18KC to Pin 8 of V1, low side to chassis.	Vert. amp. to point B, low side to chassis.	A6	"

