

# Service Manual

ORDER NO.  
RRV2764

COMPACT DISC PLAYER

# CDJ-100S

THIS MANUAL IS APPLICABLE TO THE FOLLOWING MODEL(S) AND TYPE(S).

Type	Model	Power Requirement	Remarks
	CDJ-100S		
WAXJ	○	AC220 - 240V	

● This service manual should be used together with the following manual(s):

Model No.	Order No.	Remarks
CDJ-100S/ WY	RRV2027	

# 1. CONTRAST OF MISCELLANEOUS PARTS

NOTES: ● Parts marked by "NSP" are generally unavailable because they are not in our Master Spare Parts List.

● The  $\triangle$  mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.

● Screws adjacent to  $\nabla$  mark on product are used for disassembly.

● Reference Nos. indicate the pages and Nos. in the service manual for the base model.

● When ordering resistors, first convert resistance values into code form as shown in the following examples.

Ex.1 When there are 2 effective digits (any digit apart from 0), such as 560 ohm and 47k ohm (tolerance is shown by J=5%, and K=10%).

560  $\rightarrow$  56 x 10<sup>1</sup>  $\rightarrow$  561 ..... RD1/APU 561J  
 47k  $\rightarrow$  47 x 10<sup>3</sup>  $\rightarrow$  473 ..... RD1/APU 473J  
 0.5  $\rightarrow$  R50 ..... RN2H/R 50K  
 1  $\rightarrow$  1R0 ..... RS1P 1R0K

Ex.2 When there are 3 effective digits (such as in high precision metal film resistors).

5.62k  $\rightarrow$  562 x 10<sup>1</sup>  $\rightarrow$  5621 ..... RN1/4PC 5621F

## ■ CONTRAST TABLE

CDJ-100S/WAXJ and CDJ-100S/WY are constructed the same except for the following :

Ref. No.	Mark	Symbol and Description	Part No.		Remarks
			CDJ-100S/ WY	CDJ-100S/ WAXJ	
<b>PACKING</b>					
P4 - 1		Pad (A)	DHA1411	DHA1480	
P4 - 2		Pad (B)	DHA1412	DHA1481	
P4 - 3		Pad (C)	DHA1413	DHA1482	
P4 - 4		Packing Case	DHG1850	DHG2369	
P4 - 6		Audio Cable (L= 1.5m)	VDE1033	VDE1064	
P4 - 7		Operating Instructions (English, French, German, Italian, Dutch, Spanish)	DRB1227	Not used	
P4 - 7		Operating Instructions (Chinese)	Not used	DRB1343	
P4 - 10		Polyethylene Bag	DHL1106	DHL1121	
P4 - 12	NSP	Caution SG	DRM1199	PRR1001	
		Control Cord	PDE1247	PDE-319	For Packing (Accessories)
	NSP	Assistant Manual	DRH1044	Not used	For Packing (Accessories)
		Mini Catalog	DRY1194	Not used	For Packing (Accessories)
<b>EXTERIOR (1/2)</b>					
P6 - 6		Earth Lead Unit/300V	DDF1010	DDF1022	
P6 - 11	$\triangle$	AC Power Cord	PDG1003	PDG1070	
P6 - 19		Bottom Plate	DNH2338	DNH2563	
P6 - 20	NSP	Chassis	DNK3553	DNK4184	
P6 - 32	NSP	Binder	Z09-061	ZCB-069Z	No.1
		Label	Not used	PRW1499	No.2
	NSP	CCC S&E Label	Not used	VRW1945	
<b>EXTERIOR (2/2)</b>					
P7 - 2		36P FFC/60V	DDD1131	DDD1187	
P7 - 4		Cushion C	DEC2259	DEC2496	
P7 - 13		Jog Washer	DBF1001	DBF1002	
P7 - 26		Caution Label	VRW1094	DRW2153	
P7 - 27	NSP	Caution Label HE	VRW1297	Not used	

Note: The numbers in the remarks column correspond to the numbers on the "EXPLODED VIEWS".

## ■ EXPLODED VIEWS

### • EXTERIOR

