

9. JB-100

SPECIFICATIONS

Matching impedance	4 to 16Ω
Rated input	5V (When used in combination with SE-100)
Maximum input	10V (When used in combination with SE-100)
Output changeover	Switch system (0dB, 6dB, 12dB and speaker)
Connecting cord	3.2 ft/1m
External dimensions	4-1/2 (W) x 3-1/8 (H) x 8-9/16 (D) inch 114(W) x 80(H) x 217(D) mm
Weight	3 lb./1360 g
Accessories	Speaker connecting plug, two each

NOTE:

Specifications and the design subject to possible modification without notice due to improvements.

PARTS LIST

Key No.	Description	Part No.
1	Front Panel	M21-671-0
2	Wooden Case	M32-626-0
3	Rotary Switch	S15-606-0
4	4-P Socket	K72-625-0
5	Knob	A12-631-0
6	Plug	K72-642-0
7	Transformer	STV-001-0
8	Resistor (30Ω, 5W)	C91-628-0
9	Rubber Foot	E31-615-A
10	Connection Cord	D12-639-0
11		
12	Cord Crammer	SNB-007-0
13	Positive Thermistor	SCN-002-A
14	Socket	K72-624-0
	Packing Case	H93-640-0
	Styrol Protector	H92-608-0
	Operating Guide (SE100, JB-100)	SRB-009-0



