



### ALIGNMENT AND SENSITIVITY

SIGNAL GENERATOR MODULATED 30% AT 400 CY.

STEP	APPLY SIGNAL		THRU SERIES DUMMY	SET GANG AT	ADJUST FOR MAX. OUTPUT	NOMINAL SENSITIVITY FOR 50 MILLIWATTS OUTPUT.
	AT KC.	TO				
1	455	12BA6 #1 PIN	.05	MINIMUM CAPACITY	2ND. I.F	2600 $\mu$ K
2	455	12BE6 #7 PIN	.05	MINIMUM CAPACITY	1ST. I.F 2ND. I.F	60 $\mu$ V.
3	1640	ANT.	*	MINIMUM CAPACITY	OSC. TRIM.	—
4	1450	ANT.	*	RESONANCE	ANT. TRIM.	150 $\mu$ V/M.
5	600	ANT.	*	RESONANCE	CHECK ONLY	300 $\mu$ V/M.

### VIKING RM-237, RM-237R

