



ALIGNMENT AND SENSITIVITY						
SIGNAL GENERATOR MODULATED 30% AT 400 CY.						
STEP	APPLY SIGNAL AT KC.	To	THRU SERIES DUMMY	SET GANG AT	ADJUST FOR MAX. OUTPUT	NOMINAL SENSITIVITY FOR 50 MILLIWATTS OUTPUT
1	455	12BA6 1.F. #1 PIN	.05	—	2ND. I.F.	4500
2	455	12BE6 #7 PIN	.05	MINIMUM CAPACITY	1ST. I.F. 2ND. I.F.	175
3	1460	12BA6 #1 PIN	.05	1460 KC	OSC. AND INTERSTAGE TRIMMERS	ADJUST OSC. SLUG AT 600 KC.
4	1460	ANT.	*	1460 KC	ANTENNA & INTERSTAGE TRIMMER	70 μ V./M.
5	600	ANT.	*	600 KC	CHECK ONLY	170 μ V./M.