


STEP	APPLY SIGNAL AT KC.	THRU SERIES DUMMY TO	SET GANG AT	ADJUST FOR MAX. OUTPUT	NOMINAL SENSITIVITY 50 MILLIWATTS OUTPUT AT 400 C/S
1	455	12BA6 #1 PIN	.05	MINIMUM CAPACITY	2ND I.F. 2200 $\mu$ V.
2	455	12BE6 #7 PIN	.05	MINIMUM CAPACITY	1ST I.F. 60 $\mu$ V.
3	1650	ANT.	400 $\Omega$	MINIMUM CAPACITY	OSC. TRIM
4	1460	ANT.	400 $\Omega$	RESONANCE	ANT. TRIM 22 $\mu$ V.
5	600	ANT.	400 $\Omega$	RESONANCE	CHECK ONLY 34 $\mu$ V.
6	530	ANT.	400 $\Omega$	MAXIMUM CAPACITY	CHECK ONLY



GANG COMPLETELY IN MESH.

VIKING RMK-236, RMK-236R, RMK-279