


# VIKING RMK-369



ALIGNMENT AND SENSITIVITY							
SIGNAL GENERATOR MODULATED 30% AT 400 CYCLES							
STEP	APPLY SIGNAL KC	TO	THRU SERIES DUMMY	SET GANG AT	ADJUST FOR MAX OUTPUT	NOMINAL SENSITIVITY FOR 50 mW OUTPUT	NOMINAL SENSITIVITY FOR 100 mW AT 100 OHM LOAD
1	455	12BA6 #1 PIN	.05	-	2nd I.F.	1800 $\mu$ V	3600 $\mu$ V
2	455	12BE6 #7 PIN	.05	MIN. CAP	1st I.F. 2nd I.F.	63 $\mu$ V	150 $\mu$ V
3	1460	ANT.	*	1460 KC	OSC. TRIM ANT. TRIM.	110 $\mu$ V/M	245 $\mu$ V/M
4	600	ANT.	*	600 KC	OSC. SLUG REPEAT STEP 3	220 $\mu$ V/M	450 $\mu$ V/M
5	535	ANT.	*	MAX. CAP	CHECK ONLY		
6	1650	ANT.	*	MIN. CAP	CHECK ONLY		