
SERVICE HINT

PROBLEM:

AC line clicks are audible.

CAUSE:

Grounding problem of the input jacks.

SOLUTION:

Mount a ***FOIL*** capacitor 0.33uF, 400V between the housing and the ground of the RCA jacks. The best is to loosen the screws holding the RCA jacks and clamp one leg of the foil capacitor between the plastic of the RCA leg and the back panel; the other wire can be soldered to the ground of the RCA jack.

PRODUCTION:

Special thanks to Dynavox Switzerland for supplying this information