


## APHEX CX-1 PINOUT DATA

### *IMPORTANT NOTES:*

- Use HI-Level input and output with transformed units ONLY.
- Inputs on all units are balanced.

Pin#	Description of connection and use.
1	Chassis ground
2	HIGH-Level Output (Transformer use ONLY)
3	LOW-Level Output (NO Transformer)
4	Negative Output
5	Output Ground
6	N/C
7	N/C
8	Input Ground
9	Input LOW-Level (NO Transformer)
10	Input High-Level (Transformer Use ONLY)
11	Gain Trim
12	V+
13	
14	V-
15	N/C or Ext. Meter Feed (Not Buffered)

Input on Transformed units use pins 8 and 10.

Input on Non-Transformed units use pins 8 and 9.